3. Electrical Parts List

Location no.	Code no.	Description & Specifiation	Remarks
		******* MAXN72 Parts List *******	
	AH26-00063A	TRANS-POWER;E85.8X50,-,-,-,-,SILICON STEEL SHEET,230	
	AH38-10001A	WIRE-LEAD;1007#22,1500MM	
	AH39-00021A	LEAD-CONNECTOR ASSY;-,5264,GT201-6,6P,300MM,2547#28,2P SHIEL	
	AH39-00202A	LEAD CONNECTOR-ASSY;-,1533#28,-,3P,200MM,-,-,5264-3P,GIL-S-3	
	AH39-10002L	POWER CORD;CP2,KLCE-2F,2.15M,5239,VDE	
	AH42-20001Q	ANT-LOOP;-,KS980214-01,18.5uH,CONNECTOR	
	AH59-00004Q	REMOCON—ASSY;-,-,-,22KEY,MAX-N75,SAMSUNG	
	AH59-20006S	DECK;ADR241FTW,-,DC12V,-,-,MAXN75,-	
	AH92-00245A	**ASSY-PCB;SMK35/45,TUNER-T**	**S.N.A.**
TR6	2007-000030	R-CHIP;560OHM,5%,1/10W,DA,TP,2012	
TR101	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
TR102	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
TR103	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
TR104	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
TR19	2007-000282	R-CHIP;100KOHM,5%,1/10W,DA,TP,2012	
TR45	2007-000282	R-CHIP;100KOHM,5%,1/10W,DA,TP,2012	
TR47	2007-000282	R-CHIP;100KOHM,5%,1/10W,DA,TP,2012	
TR49	2007-000282	R-CHIP;100KOHM,5%,1/10W,DA,TP,2012	
RR2	2007-000290	R-CHIP;100OHM,5%,1/10W,DA,TP,2012	
TR24	2007-000290	R-CHIP;100OHM,5%,1/10W,DA,TP,2012	
TR43	2007-000290	R-CHIP;100OHM,5%,1/10W,DA,TP,2012	
TR2	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
TR21	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
TR22	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
TR46	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
TR48	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
TR50	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
TR53	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
TR54	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
TR56	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
TR10	2007-000308	R-CHIP;10OHM,5%,1/10W,DA,TP,2012	
TR20	2007-000409	R-CHIP;15KOHM,5%,1/10W,DA,TP,2012	
TR28	2007-000457	R-CHIP;18KOHM,5%,1/10W,DA,TP,2012	
TR52	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
TR9	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
TR35	2007-000493	R-CHIP;2.2KOHM,5%,1/10W,DA,TP,2012	
TR36	2007-000493	R-CHIP;2.2KOHM,5%,1/10W,DA,TP,2012	
TR40	2007-000493	R-CHIP;2.2KOHM,5%,1/10W,DA,TP,2012	
TR7	2007-000518	R-CHIP;2.7KOHM,5%,1/10W,DA,TP,2012	
TR11	2007-000572	R-CHIP;220OHM,5%,1/10W,DA,TP,2012	
TR105	2007-000586	R-CHIP;22KOHM,5%,1/10W,DA,TP,2012	
TR15	2007-000586	R-CHIP;22KOHM,5%,1/10W,DA,TP,2012	
TR37	2007-000586	R-CHIP;22KOHM,5%,1/10W,DA,TP,2012	
TR12	2007-000686	R-CHIP;3.3KOHM,5%,1/10W,DA,TP,2012	
TR29	2007-000686	R-CHIP;3.3KOHM,5%,1/10W,DA,TP,2012	
TR23	2007-000710	R-CHIP;3.9KOHM,5%,1/10W,DA,TP,2012	
TR8	2007-000822	R-CHIP;390OHM,5%,1/10W,DA,TP,2012	
TR4	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012	
TR51	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012	
TR17	2007-000981	R-CHIP;5.6KOHM,5%,1/10W,DA,TP,2012	
TR25	2007-001043	R-CHIP;56OHM,5%,1/10W,DA,TP,2012	
TR27	2007-001071	R-CHIP;6.8KOHM,5%,1/10W,DA,TP,2012	
TR38	2007-001177	R-CHIP;8.2KOHM,5%,1/10W,DA,TP,2012	
TR44	2007-001177	R-CHIP;8.2KOHM,5%,1/10W,DA,TP,2012	
TC41	2203-000239	C-CERAMIC,CHIP;0.1nF,5%,50V,NP0,TP,2012	
RC2	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
TC20	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
TC28	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
TC29	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
TC3	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
TC44	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
TC7	2203-000429	C-CERAMIC,CHIP;0.018nF,5%,50V,NP0,TP,2012	
TC1	2203-000609	C-CERAMIC,CHIP;22nF,10%,50V,X7R,TP,2012	
TC5	2203-000609	C-CERAMIC,CHIP;22nF,10%,50V,X7R,TP,2012	
TC99	2203-000609	C-CERAMIC,CHIP;22nF,10%,50V,X7R,TP,2012	
TC33	2203-000844	C-CERAMIC,CHIP;39nF,10%,50V,X7R,TP,2012,-	
RC7	2203-000979	C-CERAMIC,CHIP;47nF,10%,50V,X7R,TP,2012	
TC10	2203-000979	C-CERAMIC,CHIP;47nF,10%,50V,X7R,TP,2012	
TC13	2203-000979	C-CERAMIC,CHIP;47nF,10%,50V,X7R,TP,2012	
TC15	2203-000979	C-CERAMIC,CHIP;47nF,10%,50V,X7R,TP,2012	
TC35	2203-000979	C-CERAMIC,CHIP;47nF,10%,50V,X7R,TP,2012	
TC45	2203-000979	C-CERAMIC,CHIP;47nF,10%,50V,X7R,TP,2012	
TC6	2203-000979	C-CERAMIC,CHIP;47nF,10%,50V,X7R,TP,2012	
RC8	2203-001058	C-CERAMIC,CHIP;0.56nF,5%,50V,NP0,TP,2012	
TC61	2203-001105	C-CERAMIC,CHIP;6.8nF,10%,50V,X7R,TP,2012	
TC62	2203-001105	C-CERAMIC,CHIP;6.8nF,10%,50V,X7R,TP,2012	
TC32	2203-001132	C-CERAMIC,CHIP;0.68nF,5%,50V,NP0,TP,2012	
TC2	2203-001517	C-CERAMIC,CHIP;0.015nF,5%,50V,NP0,TP,2012	
RC4	2203-001524	C-CERAMIC,CHIP;0.047nF,5%,50V,NP0,TP,2012	
RC5	2203-001524	C-CERAMIC,CHIP;0.047nF,5%,50V,NP0,TP,2012	
TC63	2203-001551	C-CERAMIC,CHIP;1.5nF,10%,50V,X7R,TP,2012	
TC64	2203-001551	C-CERAMIC,CHIP;1.5nF,10%,50V,X7R,TP,2012	
TC50	2203-001611	C-CERAMIC,CHIP;0.022nF,5%,50V,NP0,TP,2012	
TC51	2203-001611	C-CERAMIC,CHIP;0.022nF,5%,50V,NP0,TP,2012	
TD3	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
TD4	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
TD5	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
TD6	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
TZD1	0403-000367	DIODE-ZENER;UZ7.5BSC,7.5V,7.33-7.64V,500mW	
RZD1	0403-000393	DIODE-ZENER;UZP5.1B,5.1V,4.8-5.4V,1W,DO-41	
TZD2	0403-000393	DIODE-ZENER;UZP5.1B,5.1V,4.8-5.4V,1W,DO-41	
TQ4	0501-000294	TR-SMALL SIGNAL;KSA708-Y,PNP,800mW,TO-92,TP,12	
TQ2	0501-000392	TR-SMALL SIGNAL;KSC838-O,NPN,250mW,TO-92,-,70-	
TQ3	0501-000392	TR-SMALL SIGNAL;KSC838-O,NPN,250mW,TO-92,-,70-	
TQ1	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,TP,120-	
TQ5	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,TP,120-	
TQ6	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,TP,120-	
TQ7	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,TP,120-	
TR30	2001-000117	R-CARBON(S);68OHM,5%,1/2W,AA,TP,2.4X6.4MM	
RR1A	2001-000118	R-CARBON(S);180ohm,5%,1/2W,AA,TP,2.4x6.4mm	
TR44	2001-000118	R-CARBON(S);180ohm,5%,1/2W,AA,TP,2.4x6.4mm	
TR58	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
TR5	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
-	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
TR39	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
TR1	2001-000331	R-CARBON;12KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
RR3	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
RR4	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
RR5	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
TR32	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
TR34	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
TR55	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
TR18	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
TR3	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
TR13	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
TR40	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
TR61	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
TR62	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
TR42	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
TR16	2001-000745	R-CARBON;4.7OHM,5%,1/8W,AA,TP,1.8X3.2MM	
TR41	2001-000802	R-CARBON;5.6Kohm,5%,1/8W,AA,TP,1.8x3.2m	
TR57	2001-000802	R-CARBON;5.6Kohm,5%,1/8W,AA,TP,1.8x3.2m	
TSR1	2103-000290	VR-SEMI;20Kohm,30%,1/10W,TOP	
TC14	2201-000565	C-CERAMIC,DISC;47nF,20%,50V,Y5V,12.5x4.0mm,5mm,TP	
TC39	2201-000565	C-CERAMIC,DISC;47nF,20%,50V,Y5V,12.5x4.0mm,5mm,TP	
RC9	2202-000796	C-CERAMIC,MLC-AXIAL;1nF,10%,50V,Y5P,TP,3.5x19,-	
TC40	2202-000796	C-CERAMIC,MLC-AXIAL;1nF,10%,50V,Y5P,TP,3.5x19,-	
TC42	2202-000796	C-CERAMIC,MLC-AXIAL;1nF,10%,50V,Y5P,TP,3.5x19,-	
TC48	2202-000807	C-CERAMIC,MLC-AXIAL;22NF,+80-20%,25V,Y5V,TP,3.5X19	
TC21	2401-000240	C-AL;100uF,20%,10V,GP,TP,5x11,5	
TC46	2401-000240	C-AL;100uF,20%,10V,GP,TP,5x11,5	
TC12	2401-000419	C-AL;10UF,20%,16V,GP,-,4X7,5	
TC26	2401-000419	C-AL;10UF,20%,16V,GP,-,4X7,5	
TC27	2401-000419	C-AL;10UF,20%,16V,GP,-,4X7,5	
TC30	2401-000419	C-AL;10UF,20%,16V,GP,-,4X7,5	
RC1	2401-000907	C-AL;22UF,20%,16V,GP,-,5X11,2MM	
TC34	2401-000907	C-AL;22UF,20%,16V,GP,-,5X11,2MM	
TC37	2401-001022	C-AL;3.3UF,20%,50V,GP,-,5X11,2MM	
TC38	2401-001164	C-AL;33UF,20%,16V,GP,-,5X11,2MM	
TC47	2401-001895	C-AL;100uF,20%,16V,GP,6.3x11mm,2.5m	
TC11	2401-001912	C-AL;1uF,20%,50V,GP,5x11mm,2mm,BK	
TC17	2401-001912	C-AL;1uF,20%,50V,GP,5x11mm,2mm,BK	
TC19	2401-001912	C-AL;1uF,20%,50V,GP,5x11mm,2mm,BK	
TC16	2401-001954	C-AL;4.7UF,20%,50V,GP,TP,5X11MM,5	
TC23	2401-001954	C-AL;4.7UF,20%,50V,GP,TP,5X11MM,5	
TC25	2401-001954	C-AL;4.7UF,20%,50V,GP,TP,5X11MM,5	
TC18	2401-001968	C-AL;470NF,20%,50V,GP,TP,5X11MM,5	
TC43	2401-001968	C-AL;470NF,20%,50V,GP,TP,5X11MM,5	
TC4	2401-001975	C-AL;47UF,20%,16V,GP,TP,5X11MM,5	
TC9	2401-001975	C-AL;47UF,20%,16V,GP,TP,5X11MM,5	
RC6	2401-002180	C-AL;2.2UF,20%,50V,GP,TP,5X11,5MM	
RIC1	AH14-10008E	IC;BU1923F,SOP,+5V	
VVC1	0405-000137	DIODE-VARACTOR;KV-1260,20V,100NA,T0-92S	
TFL4	14529-304-610	FILTER CERAMIC;AHCM2-450BL	
	2202-000263	C-CERAMIC,MLC-AXIAL;470pF,10%,50V,Y5P,TP,3.5x19,-	
TX1	2801-000734	CRYSTAL-UNIT;7.2MHZ,50PPM,28-AAM,12PF,30OHM	
RX1	2801-003601	CRYSTAL-UNIT;4.332MHz,30ppm,28-AAM,30pF,	
TFL2	2903-000105	FILTER-CERAMIC;BP,10.7MHZ+-25KHZ,180KHZ+-50KH	
TFL1	2903-000119	FILTER-CERAMIC;SFE10.7MJA-10-A	
TWA1	3710-001421	CONNECTOR-SOCKET;14P,1R,2mm,ANGLE,SN	
TJ2	3711-000814	CONNECTOR-HEADER;BOX,2P,1R,2.5mm,ANGLE,SN	
TJ1	3716-000210	TERMINAL-BLOCK;-,-,-,60V,7A	
HIC1	AH14-10007G	IC;LC72131,DIP,STICK PLL	
TIC1	AH14-10008B	IC;LA1837,DIP,RF+MPX	
TLPF1	AH26-00005A	TRANS-IF;-,LKS75M00-X000264-0,LOW PASS FILTER,-,7	
TLPF2	AH26-00005A	TRANS-IF;-,LKS75M00-X000264-0,LOW PASS FILTER,-,7	
TL2	AH26-10001E	TRANS-IF;KS940228-09,-,-,7.6X12.0,-,450KHZ,BULK,	
TL3	AH26-10020A	TRANS-DET;-,7KLL,DET,-,7.8MM,91PF,11.32M	
LW	AH27-00007A	COIL-OSC;LKS7FB00-0060BLO-0,-,LW OSC	
OSC	AH27-00007A	COIL-OSC;LKS7FB00-0060BLO-0,-,LW OSC	
MW	AH27-00008A	COIL-OSC;LKS75M00-0060LMO-0,-,MW OSC	
OSC	AH27-00008A	COIL-OSC;LKS75M00-0060LMO-0,-,MW OSC	

Location no.	Code no.	Description & Specifiation	Remarks
ANT	AH27-00011A	COIL-OSC;LKS75M00-X000262-0,-,LW ANT	
LW	AH27-00011A	COIL-OSC;LKS75M00-X000262-0,-,LW ANT	
ANT	AH27-00012A	COIL-OSC;LKS75M00-X000263-0,365UH,MW ANT	
MW	AH27-00012A	COIL-OSC;LKS75M00-X000263-0,365UH,MW ANT	
FM	AH40-10025S	TUNER-FM;KST-F404VA-1,4G,75ohm	
PACK	AH40-10025S	TUNER-FM;KST-F404VA-1,4G,75ohm	
FREE	AH61-20540A	HOLDER-TUNER;-,ABS,94HB,BLK,-,MAX940	
	AH65-30010A	CLAMP-WIRE;DALB-2,-,-,-	
	AH92-00580A	**ASSY PCB;MAX-N73,MAIN**	**S.N.A.**
AD1	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
AD10	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
AD2	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
AD4	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
AD7	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
AD8	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
AD9	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
CD1A	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
CD3	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
CD4	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
CD5	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
CD6	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
FD1	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
FD2	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
FD3	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
HD1	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
HD2	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
HD5	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
JD1	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
JD1A	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
JD2	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
JD2L	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
JD2R	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
JD3	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
JD4	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
LD1	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
RD4	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
RD6	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
HD3	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
HD4	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
RD1	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
RD2	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
RD3	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
RD5	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
RD9	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
RD7	0402-000151	DIODE-RECTIFIER;1N5392,100V,1.5A,DO-15,TP	
CZD1	0403-000354	DIODE-ZENER;UZ5.1B,5.1V,4.8-5.4V,500mW,DO-	
FZD3	0403-000354	DIODE-ZENER;UZ5.1B,5.1V,4.8-5.4V,500mW,DO-	
RZD4	0403-000354	DIODE-ZENER;UZ5.1B,5.1V,4.8-5.4V,500mW,DO-	
FZD1	0403-000363	DIODE-ZENER;UZ6.8BH,6.8V,6.8-7.2V,500mW,DO	
FZD2	0403-000363	DIODE-ZENER;UZ6.8BH,6.8V,6.8-7.2V,500mW,DO	
AZD1	0403-000369	DIODE-ZENER;UZ8.2BM,8.2V,7.9-8.5V,500MW	
AZD2	0403-000369	DIODE-ZENER;UZ8.2BM,8.2V,7.9-8.5V,500MW	
RZD3	0403-000379	DIODE-ZENER;UZP12B,12V,11.4-12.6V,1W,DO-41	
RZD5	0403-000396	DIODE-ZENER;UZP6.8B,6.8V,6.4-7.2V,1W,DO-41	
RZD1	0403-000570	DIODE-ZENER;UZP18B,18V,16.9-19.1V,1W,DO-41	
RZD2	0403-000570	DIODE-ZENER;UZP18B,18V,16.9-19.1V,1W,DO-41	
LQ3	0501-000010	TR-SMALL SIGNAL;KSC1008,NPN,800mW,TO-92,TP,120	
AQ9	0501-000294	TR-SMALL SIGNAL;KSA708-Y,PNP,800mW,TO-92,TP,12	
RQ4	0501-000294	TR-SMALL SIGNAL;KSA708-Y,PNP,800mW,TO-92,TP,12	
JQ8A	0501-000303	TR-SMALL SIGNAL;KSA733,PNP,250mW,TO-92,TP,120-	
LQ1	0501-000369	TR-SMALL SIGNAL;KSC2331-Y,NPN,1W,TO-92L,-,120-	
LQ2	0501-000369	TR-SMALL SIGNAL;KSC2331-Y,NPN,1W,TO-92L,-,120-	
AQ1L	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,TP,120-	
AQ1R	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,TP,120-	
AQ2L	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,TP,120-	
AQ2R	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,TP,120-	
CQ10	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,TP,120-	
CQ4	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,TP,120-	
CQ5	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,TP,120-	
CQ9	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,TP,120-	
FQ1L	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,TP,120-	
FQ1R	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,TP,120-	
JQ5	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,TP,120-	
JQ6	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,TP,120-	
JQ7	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,TP,120-	
RQ3	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,TP,120-	
AQ10	0501-000407	TR-SMALL SIGNAL;KSD471A-Y,NPN,800mW,TO-92,-,12	
HQ1L	0501-000407	TR-SMALL SIGNAL;KSD471A-Y,NPN,800mW,TO-92,-,12	
HQ1R	0501-000407	TR-SMALL SIGNAL;KSD471A-Y,NPN,800mW,TO-92,-,12	
JQ2L	0501-000407	TR-SMALL SIGNAL;KSD471A-Y,NPN,800mW,TO-92,-,12	
JQ2R	0501-000407	TR-SMALL SIGNAL;KSD471A-Y,NPN,800mW,TO-92,-,12	
CQ3	0501-000610	TR-SMALL SIGNAL;KSA928A-Y,PNP,1W,TO-92L,TP,160	
CQ6	0501-000610	TR-SMALL SIGNAL;KSA928A-Y,PNP,1W,TO-92L,TP,160	
CQ7	0501-000610	TR-SMALL SIGNAL;KSA928A-Y,PNP,1W,TO-92L,TP,160	
RQ1	0501-000610	TR-SMALL SIGNAL;KSA928A-Y,PNP,1W,TO-92L,TP,160	
AQ4	0504-000118	TR-DIGITAL;KSR1003,NPN,300MW,22K/22K,TO-92,TP	
CQ8	0504-000118	TR-DIGITAL;KSR1003,NPN,300MW,22K/22K,TO-92,TP	
JQ1	0504-000118	TR-DIGITAL;KSR1003,NPN,300MW,22K/22K,TO-92,TP	
JQ4	0504-000118	TR-DIGITAL;KSR1003,NPN,300MW,22K/22K,TO-92,TP	
JQ7L	0504-000118	TR-DIGITAL;KSR1003,NPN,300MW,22K/22K,TO-92,TP	
JQ7R	0504-000118	TR-DIGITAL;KSR1003,NPN,300MW,22K/22K,TO-92,TP	
JQ8	0504-000118	TR-DIGITAL;KSR1003,NPN,300MW,22K/22K,TO-92,TP	
AQ1	0504-001003	TR-DIGITAL;KSR2003,PNP,300MW,22K/22K,TO-92,TP	

Location no.	Code no.	Description & Specifiation	Remarks
CQ1	0504-001003	TR-DIGITAL;KSR2003,PNP,300MW,22K/22K,TO-92,TP	
CQ2	0504-001003	TR-DIGITAL;KSR2003,PNP,300MW,22K/22K,TO-92,TP	
FQ1	0504-001003	TR-DIGITAL;KSR2003,PNP,300MW,22K/22K,TO-92,TP	
JQ2	0504-001003	TR-DIGITAL;KSR2003,PNP,300MW,22K/22K,TO-92,TP	
JQ3	0504-001003	TR-DIGITAL;KSR2003,PNP,300MW,22K/22K,TO-92,TP	
JQ1L	0505-000197	FET-SILICON;2SK373Y,N,-,-,-,400MW,TO-92	
JQ1R	0505-000197	FET-SILICON;2SK373Y,N,-,-,-,400MW,TO-92	
JR13	2001-000005	R-CARBON;390ohm,5%,1/8W,AA,TP,1.8x3.2mm	
HR1	2001-000028	R-CARBON(S);100OHM,5%,1/2W,AA,TP,2.4X6.4MM	
HR2	2001-000028	R-CARBON(S);100OHM,5%,1/2W,AA,TP,2.4X6.4MM	
CR1	2001-000034	R-CARBON;220OHM,5%,1/4W,AA,TP,2.4X6.4MM	
FR12	2001-000034	R-CARBON;220OHM,5%,1/4W,AA,TP,2.4X6.4MM	
AR11	2001-000052	R-CARBON(S);3.3KOHM,5%,1/2W,AA,TP,2.4X6.4MM	
AR12	2001-000052	R-CARBON(S);3.3KOHM,5%,1/2W,AA,TP,2.4X6.4MM	
RR9	2001-000055	R-CARBON;4.7Kohm,5%,1/4W,AA,TP,2.4x6.4m	
LR1	2001-000109	R-CARBON(S);470OHM,5%,1/2W,AA,TP,2.4X6.4MM	
AR8L	2001-000221	R-CARBON;1.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
AR8R	2001-000221	R-CARBON;1.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
JR7	2001-000221	R-CARBON;1.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
FR4R	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
FR12L	2001-000258	R-CARBON;1.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
FR10L	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
FR10R	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
BR1	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
AR10A	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CR12	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CR2	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CR21	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CR25	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CR27	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CR28	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CR29	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CR3	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CR30	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CR31	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CR34	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CR36	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CR4	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CR5	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CR9	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
DR3L	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
FR3	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
FR7	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
HR4	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
JR11	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
JR8L	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
HR5L	2001-000302	R-CARBON;10OHM,5%,1/8W,AA,TP,1.8X3.2MM	
HR5R	2001-000302	R-CARBON;10OHM,5%,1/8W,AA,TP,1.8X3.2MM	
JR20	2001-000319	R-CARBON;120KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
BR1R	2001-000411	R-CARBON;18KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
JR10L	2001-000411	R-CARBON;18KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
JR10R	2001-000411	R-CARBON;18KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
AR4R	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CR26	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
RR17	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
RR7	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
AR24	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CR24	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
FR8L	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
HR5	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
HR9L	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
HR9R	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
BR1L	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
BR1R	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
AR19	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
FR1	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
FR13L	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
FR7	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
JW48	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
RR14	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
RR10	2001-000563	R-CARBON;27KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
AR3R	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
AR5R	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
HR1R	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
RR11	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
RR5	2001-000613	R-CARBON;3.9KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
AR10	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
AR1L	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CR14	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CR16	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CR18	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CR19	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CR20	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
HR3	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
JR12	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
JR13L	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
JW99	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
LR4	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
RR12	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
RR15	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
JR1	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
AR8	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
AR9	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
BR3L	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	

Location no.	Code no.	Description & Specifiation	Remarks
BR3R	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
FR11L	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
FR11R	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
JR14	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
DR2L	2001-000802	R-CARBON;5.6Kohm,5%,1/8W,AA,TP,1.8x3.2m	
JR1L	2001-000802	R-CARBON;5.6Kohm,5%,1/8W,AA,TP,1.8x3.2m	
RR18	2001-000890	R-CARBON;6.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
FR6L	2001-000977	R-CARBON;8.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
FR4	2001-001077	R-CARBON(S);150ohm,5%,1/2W,AA,TP,2.4x6.4mm	
FR8	2001-001077	R-CARBON(S);150ohm,5%,1/2W,AA,TP,2.4x6.4mm	
RR13	2001-001077	R-CARBON(S);150ohm,5%,1/2W,AA,TP,2.4x6.4mm	
LR3	2001-001096	R-CARBON(S);2.2OHM,5%,1/2W,AA,TP,2.4X6.4MM	
LR6	2001-001138	R-CARBON(S);390ohm,5%,1/2W,AA,TP,2.4x6.4mm	
RR16	2001-001138	R-CARBON(S);390ohm,5%,1/2W,AA,TP,2.4x6.4mm	
RR3	2001-001153	R-CARBON(S);47ohm,5%,1/2W,AA,TP,2.4x6.4mm	
RR4	2001-001153	R-CARBON(S);47ohm,5%,1/2W,AA,TP,2.4x6.4mm	
CR15	2001-001178	R-CARBON(S);680OHM,5%,1/2W,AA,TP,2.4X6.4MM	
CR17	2001-001178	R-CARBON(S);680OHM,5%,1/2W,AA,TP,2.4X6.4MM	
CR22	2001-001178	R-CARBON(S);680OHM,5%,1/2W,AA,TP,2.4X6.4MM	
AR13	2003-000008	R-METAL OXIDE(S);100ohm,5%,1W,AA,TP,3.3x9mm	
AR15	2003-000008	R-METAL OXIDE(S);100ohm,5%,1W,AA,TP,3.3x9mm	
JSR2L	2103-000122	VR-SEMI;100Kohm,30%,1/10W,TOP	
JSR2R	2103-000122	VR-SEMI;100Kohm,30%,1/10W,TOP	
JSR3L	2103-000122	VR-SEMI;100Kohm,30%,1/10W,TOP	
JSR3R	2103-000122	VR-SEMI;100Kohm,30%,1/10W,TOP	
JSR1L	2103-000248	VR-SEMI;200KOHM,30%,1/10W,TOP	
JSR1R	2103-000248	VR-SEMI;200KOHM,30%,1/10W,TOP	
CVR1	2103-000341	VR-SEMI;2Kohm,30%,1/10W,TOP	
CVR2	2103-000341	VR-SEMI;2Kohm,30%,1/10W,TOP	
RC11	2201-000161	C-CERAMIC,DISC;10nF,+80-20%,500V,Y5V,TP,13.5x	
RC12	2201-000161	C-CERAMIC,DISC;10nF,+80-20%,500V,Y5V,TP,13.5x	
JC3L	2201-000368	C-CERAMIC,DISC;220PF,10%,50V,SL,TP,6.5X3.0,5	
JC3R	2201-000368	C-CERAMIC,DISC;220PF,10%,50V,SL,TP,6.5X3.0,5	
HC3L	2201-000381	C-CERAMIC,DISC;22NF,20%,50V,Y5V,8.0x4.0mm,5mm,TP	
HC3R	2201-000381	C-CERAMIC,DISC;22NF,20%,50V,Y5V,8.0x4.0mm,5mm,TP	
CC2	2201-000470	C-CERAMIC,DISC;330pF,10%,50V,SL,TP,6.5x3,5	
AC5L	2201-000565	C-CERAMIC,DISC;47nF,20%,50V,Y5V,12.5x4.0mm,5mm,TP	
AC5R	2201-000565	C-CERAMIC,DISC;47nF,20%,50V,Y5V,12.5x4.0mm,5mm,TP	
AC7L	2201-000565	C-CERAMIC,DISC;47nF,20%,50V,Y5V,12.5x4.0mm,5mm,TP	
AC7R	2201-000565	C-CERAMIC,DISC;47nF,20%,50V,Y5V,12.5x4.0mm,5mm,TP	
-	2202-000796	C-CERAMIC,MLC-AXIAL;1nF,10%,50V,Y5P,TP,3.5x19,-	
JC2L	2202-000796	C-CERAMIC,MLC-AXIAL;1nF,10%,50V,Y5P,TP,3.5x19,-	
JC1LA	2202-000820	C-CERAMIC,MLC-AXIAL;5.6NF,20%,16V,Y5R,TP,3.5X19,-	
JC1RA	2202-000820	C-CERAMIC,MLC-AXIAL;5.6NF,20%,16V,Y5R,TP,3.5X19,-	
AC6L	2301-000375	C-FILM,PEF;100nF,5%,50V,TP,11x12.5x6.5,7m	
AC6R	2301-000375	C-FILM,PEF;100nF,5%,50V,TP,11x12.5x6.5,7m	
FC6	2301-000375	C-FILM,PEF;100nF,5%,50V,TP,11x12.5x6.5,7m	
LC4	2301-000404	C-FILM,PEF;2.2NF,10%,50V,TP,5.5X7X3.2MM,5	
LC1	2301-000407	C-FILM,PEF;2.7NF,10%,50V,TP,5.5X7X3MM,5MM	
AC2	2301-000412	C-FILM,PEF;22NF,10%,50V,TP,6.5X10.5X4MM,5	
JC6L	2301-000419	C-FILM,PEF;27nF,10%,50V,TP,7.5x10.5x4mm,5	
JC6R	2301-000419	C-FILM,PEF;27nF,10%,50V,TP,7.5x10.5x4mm,5	
FC10	2301-000449	C-FILM,PEF;47NF,10%,50V,TP,8X11X4.5MM,5MM	
LC5	2301-000456	C-FILM,PEF;56NF,10%,50V,TP,8X12X4.5MM,5MM	
CC1	2401-000240	C-AL;100uF,20%,10V,GP,TP,5x11,5	
RC15	2401-000357	C-AL;100UF,20%,50V,GP,-,8X11.5,3.5M	
AC12	2401-000385	C-AL;10uF,20%,100V,GP,TP,6.3x11,5	
AC9	2401-000385	C-AL;10uF,20%,100V,GP,TP,6.3x11,5	
BC1L	2401-000419	C-AL;10UF,20%,16V,GP,-,4X7,5	
BC1R	2401-000419	C-AL;10UF,20%,16V,GP,-,4X7,5	
BC2	2401-000419	C-AL;10UF,20%,16V,GP,-,4X7,5	
BC3L	2401-000419	C-AL;10UF,20%,16V,GP,-,4X7,5	
BC3R	2401-000419	C-AL;10UF,20%,16V,GP,-,4X7,5	
JC1L	2401-000419	C-AL;10UF,20%,16V,GP,-,4X7,5	
JC1R	2401-000419	C-AL;10UF,20%,16V,GP,-,4X7,5	
JC4	2401-000419	C-AL;10UF,20%,16V,GP,-,4X7,5	
JC6	2401-000419	C-AL;10UF,20%,16V,GP,-,4X7,5	
AC10	2401-000475	C-AL;10UF,20%,50V,GP,-,5X11,2MM	
AC11	2401-000475	C-AL;10UF,20%,50V,GP,-,5X11,2MM	
FC12L	2401-000475	C-AL;10UF,20%,50V,GP,-,5X11,2MM	
FC12R	2401-000475	C-AL;10UF,20%,50V,GP,-,5X11,2MM	
FC14L	2401-000475	C-AL;10UF,20%,50V,GP,-,5X11,2MM	
FC14R	2401-000475	C-AL;10UF,20%,50V,GP,-,5X11,2MM	
FC17L	2401-000475	C-AL;10UF,20%,50V,GP,-,5X11,2MM	
FC17R	2401-000475	C-AL;10UF,20%,50V,GP,-,5X11,2MM	
RC8	2401-000475	C-AL;10UF,20%,50V,GP,-,5X11,2MM	
FC3	2401-000778	C-AL;220uF,20%,10V,GP,-,6.3x11,2.5m	
FC8	2401-000778	C-AL;220uF,20%,10V,GP,-,6.3x11,2.5m	
JC15	2401-000778	C-AL;220uF,20%,10V,GP,-,6.3x11,2.5m	
JC5	2401-000778	C-AL;220uF,20%,10V,GP,-,6.3x11,2.5m	
HC1	2401-000795	C-AL;220UF,20%,16V,GP,-,8X11.5,3.5M	
HC2	2401-000795	C-AL;220UF,20%,16V,GP,-,8X11.5,3.5M	
RC16	2401-000795	C-AL;220UF,20%,16V,GP,-,8X11.5,3.5M	
FC2	2401-000970	C-AL;22uF,20%,50V,WT,TP,5x11,5	
AC1	2401-001465	C-AL;47UF,20%,10V,GP,-,5X11,2MM	
BC2L	2401-001465	C-AL;47UF,20%,10V,GP,-,5X11,2MM	
BC2R	2401-001465	C-AL;47UF,20%,10V,GP,-,5X11,2MM	
FC12	2401-001465	C-AL;47UF,20%,10V,GP,-,5X11,2MM	
FC5	2401-001465	C-AL;47UF,20%,10V,GP,-,5X11,2MM	
JC3	2401-001465	C-AL;47UF,20%,10V,GP,-,5X11,2MM	
AC13	2401-001895	C-AL;100uF,20%,16V,GP,6.3x11mm,2.5m	
AC4L	2401-001895	C-AL;100uF,20%,16V,GP,6.3x11mm,2.5m	
AC4R	2401-001895	C-AL;100uF,20%,16V,GP,6.3x11mm,2.5m	

Location no.	Code no.	Description & Specifiation	Remarks
DC1	2401-001895	C-AL;100uF,20%,16V,GP,6.3x11mm,2.5m	
FC16L	2401-001895	C-AL;100uF,20%,16V,GP,6.3x11mm,2.5m	
FC16R	2401-001895	C-AL;100uF,20%,16V,GP,6.3x11mm,2.5m	
LC2	2401-001895	C-AL;100uF,20%,16V,GP,6.3x11mm,2.5m	
RC10	2401-001895	C-AL;100uF,20%,16V,GP,6.3x11mm,2.5m	
RC14	2401-001895	C-AL;100uF,20%,16V,GP,6.3x11mm,2.5m	
DC3L	2401-001912	C-AL;1uF,20%,50V,GP,5x11mm,2mm,BK	
DC3R	2401-001912	C-AL;1uF,20%,50V,GP,5x11mm,2mm,BK	
DC5L	2401-001912	C-AL;1uF,20%,50V,GP,5x11mm,2mm,BK	
DC5R	2401-001912	C-AL;1uF,20%,50V,GP,5x11mm,2mm,BK	
JC7L	2401-001912	C-AL;1uF,20%,50V,GP,5x11mm,2mm,BK	
JC7R	2401-001912	C-AL;1uF,20%,50V,GP,5x11mm,2mm,BK	
JC8L	2401-001912	C-AL;1uF,20%,50V,GP,5x11mm,2mm,BK	
JC8R	2401-001912	C-AL;1uF,20%,50V,GP,5x11mm,2mm,BK	
RC7	2401-001912	C-AL;1uF,20%,50V,GP,5x11mm,2mm,BK	
RC6	2401-001938	C-AL;22UF,20%,25V,GP,BK,5X11MM,2MM	
AL2L	2401-001954	C-AL;4.7UF,20%,50V,GP,TP,5X11MM,5	
AR2R	2401-001954	C-AL;4.7UF,20%,50V,GP,TP,5X11MM,5	
FC18	2401-001954	C-AL;4.7UF,20%,50V,GP,TP,5X11MM,5	
FC19L	2401-001954	C-AL;4.7UF,20%,50V,GP,TP,5X11MM,5	
FC19R	2401-001954	C-AL;4.7UF,20%,50V,GP,TP,5X11MM,5	
FC2L	2401-001954	C-AL;4.7UF,20%,50V,GP,TP,5X11MM,5	
FC2R	2401-001954	C-AL;4.7UF,20%,50V,GP,TP,5X11MM,5	
FC8L	2401-001954	C-AL;4.7UF,20%,50V,GP,TP,5X11MM,5	
FC8R	2401-001954	C-AL;4.7UF,20%,50V,GP,TP,5X11MM,5	
HC3	2401-001954	C-AL;4.7UF,20%,50V,GP,TP,5X11MM,5	
RC5	2401-001954	C-AL;4.7UF,20%,50V,GP,TP,5X11MM,5	
AC4	2401-001975	C-AL;47UF,20%,16V,GP,TP,5X11MM,5	
BC1	2401-001975	C-AL;47UF,20%,16V,GP,TP,5X11MM,5	
HC2L	2401-001975	C-AL;47UF,20%,16V,GP,TP,5X11MM,5	
HC2R	2401-001975	C-AL;47UF,20%,16V,GP,TP,5X11MM,5	
JC1	2401-001975	C-AL;47UF,20%,16V,GP,TP,5X11MM,5	
LC6	2401-001975	C-AL;47UF,20%,16V,GP,TP,5X11MM,5	
FC20	2401-002180	C-AL;2.2UF,20%,50V,GP,TP,5X11,5MM	
HC1L	2401-002180	C-AL;2.2UF,20%,50V,GP,TP,5X11,5MM	
HC1R	2401-002180	C-AL;2.2UF,20%,50V,GP,TP,5X11,5MM	
JW151	2701-000178	INDUCTOR-AXIAL;33uH,10%,3x7mm	
RL3	2701-000178	INDUCTOR-AXIAL;33uH,10%,3x7mm	
LL2	2701-000298	INDUCTOR-AXIAL;470uH,10%,4.2x9.8mm	
RL1	2701-000298	INDUCTOR-AXIAL;470uH,10%,4.2x9.8mm	
RL2	2701-000298	INDUCTOR-AXIAL;470uH,10%,4.2x9.8mm	
	3602-000147	FUSE-CLIP;250V,7.5A,30MOHM	
RBD1	0402-001258	DIODE-BRIDGE;GBU606,600V,6A,SIP-4,BK	
RBD2	0402-001258	DIODE-BRIDGE;GBU606,600V,6A,SIP-4,BK	
	0904-001316	IC-I/O CONTROLLER;M66010,24BIT,SOP,32P,200MIL,1.	
FIC3	1201-000163	IC-OP AMP;4560,SOP,8P,173MIL,DUAL,100V/mV,PLASTIC,	
HIC1	1201-000163	IC-OP AMP;4560,SOP,8P,173MIL,DUAL,100V/mV,PLASTIC,	
AIC1	1201-001333	IC-POWER AMP;411,SIP,22P;-,SINGLE,40dB,P	
RIC1	1203-001653	IC-VOLTAGE REGULATOR;4959,MULTIWATT,15P,700MIL,PLAS	
FIC2	1204-000156	IC-EQUALIZER;BA3834S,DIP,18P;-,PLASTIC,7V,-	
JIC1	1204-001471	IC-EQUALIZER;HA12211NT,DIP,30P;-,PLASTIC,15	
BIC1	1204-001474	IC-EQUALIZER;KA22241,SIP,9,-;PLASTIC,16,550	
FIC1	1204-001652	IC-SOUND PROCESSOR;M62433FP,QFP,80P;-,PLASTIC,7V,1370mW,-20	
RR8	2003-000455	R-METAL OXIDE(S);100ohm,5%,2W,AA,TP,4x12mm	
AR10L	2003-000471	R-METAL OXIDE(S);10ohm,5%,2W,AA,TP,4x12mm	
AR10R	2003-000471	R-METAL OXIDE(S);10ohm,5%,2W,AA,TP,4x12mm	
RR1	2003-000502	R-METAL OXIDE(S);150ohm,5%,2W,AA,TP,4x12mm	
PC1	2201-000546	C-CERAMIC,DISC;4.7NF,20%,400V,Y5U,BK,16X7,10	
PC2	2201-000546	C-CERAMIC,DISC;4.7NF,20%,400V,Y5U,BK,16X7,10	
GND	2202-000807	C-CERAMIC,MLC-AXIAL;22NF,+80-20%,25V,Y5V,TP,3.5X19	
HR5L	2202-000807	C-CERAMIC,MLC-AXIAL;22NF,+80-20%,25V,Y5V,TP,3.5X19	
HR5R	2202-000807	C-CERAMIC,MLC-AXIAL;22NF,+80-20%,25V,Y5V,TP,3.5X19	
AC7	2401-000230	C-AL;100uF,20%,100V,GP,TP,12.5x20,5	
AC8	2401-000230	C-AL;100uF,20%,100V,GP,TP,12.5x20,5	
RC13	2401-000230	C-AL;100uF,20%,100V,GP,TP,12.5x20,5	
RC1	2401-001942	C-AL;3300uF,20%,35V,GP,BK,18x35.5mm	
RC2	2401-003116	C-AL;4700uF,20%,35V,-,BK,18X35.5,7.	
RC3	2401-003385	C-AL;3300uF,20%,80V,GP,BK,25.4x50,1	
RC4	2401-003385	C-AL;3300uF,20%,80V,GP,BK,25.4x50,1	
BACK	2701-000178	INDUCTOR-AXIAL;33uH,10%,3x7mm	
MANU	2701-000178	INDUCTOR-AXIAL;33uH,10%,3x7mm	
RF2	3601-000216	FUSE-CARTRIDGE;250V,2.5A,TIME-LAG,GLASS,5x20mm	
CW1	3708-000181	CONNECTOR-FPC/FC/PIC;16P,1.25mm,STRAIGHT,SN	
MW1	3708-000258	CONNECTOR-FPC/FC/PIC;30P,1.25mm,STRAIGHT,SN	
PJ2	3711-000190	CONNECTOR-HEADER;1WALL,2P,1R,7.92MM,STRAIGHT,SN	
AW2	3711-000820	CONNECTOR-HEADER;BOX,2P,1R,2.5mm,STRAIGHT,SN	
JCW2	3711-000907	CONNECTOR-HEADER;BOX,3P,1R,2mm,STRAIGHT,SN	
CCW1	3711-002809	CONNECTOR-HEADER;BOX,8P,1R,2mm,STRAIGHT,SN	
JCW3	3711-003107	CONNECTOR-HEADER;BOX,3P,1R,2.5mm,STRAIGHT,SN	
JCW1	3711-003111	CONNECTOR-HEADER;BOX,6P,1R,2.5mm,-,BRAS	
RW1	3711-003112	CONNECTOR-HEADER;BOX,8P,1R,2.5MM,STRAIGHT,SN	
TCW1	3711-004109	CONNECTOR-HEADER;3WALL,14P,1R,2mm,STRAIGHT,SN	
SPK	3716-000209	TERMINAL-BLOCK;,-,-,60V,7A	
H1	3722-000363	JACK-PHONE;9P,6.4MM,AU,BLK,-	
AUX	3722-000377	JACK-RCA;4P/2C,3.5MM,SN,BLK,#16-22	
JLF1L	AH26-10002X	COIL-TRAP;KS940830-05,BIAS-TRAP,30DB,7.6,51PF,105K	
JLF1R	AH26-10002X	COIL-TRAP;KS940830-05,BIAS-TRAP,30DB,7.6,51PF,105K	
LL1	AH26-10003C	COIL-TRAP;PCHNS-5371EQJ,BIAS-TRAP,-,-,850PF,105KHZ	
PL1	AH27-10001F	COIL-CHOKE;27UH,K,Q30,-,-,DR(6.5*7.5),-,-,	
PL2	AH27-10001F	COIL-CHOKE;27UH,K,Q30,-,-,DR(6.5*7.5),-,-,	
AL1L	AH27-90001A	COIL-SPRING;,2.2UH,-,-,SPRING	
AL1R	AH27-90001A	COIL-SPRING;,2.2UH,-,-,SPRING	
AL2L	AH27-90001A	COIL-SPRING;,2.2UH,-,-,SPRING	

Location no.	Code no.	Description & Specifiation	Remarks
AL2R	AH27-90001A	COIL-SPRING;,2.2UH,-,-,SPRING	
FAN	AH31-12006A	MOTOR-DC-FAN;D0825A-12M,12V DC/0.17A,-	
RW1	AH39-20560P	LEAD CONNECTOR-ASSY;-,5264,51088,8p,300m	
MAIN	AH41-00145A	PCB MAIN;MAX-N75,1 LAYER,-,Æâî,-,330x197x1.6T,-	
JW149	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
JR4	2007-000032	R-CHIP;390KOHM,5%,1/10W,DA,TP,2012	
JW113	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
JW1A	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
JW2A	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
JW3A	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
AR8L	2007-000221	R-CHIP;1.2KOHM,5%,1/10W,DA,TP,2012	
AR8R	2007-000221	R-CHIP;1.2KOHM,5%,1/10W,DA,TP,2012	
JR8	2007-000221	R-CHIP;1.2KOHM,5%,1/10W,DA,TP,2012	
FR4L	2007-000241	R-CHIP;1.5KOHM,5%,1/10W,DA,TP,2012	
HR3L	2007-000241	R-CHIP;1.5KOHM,5%,1/10W,DA,TP,2012	
HR3R	2007-000241	R-CHIP;1.5KOHM,5%,1/10W,DA,TP,2012	
FR12R	2007-000267	R-CHIP;1.8KOHM,5%,1/10W,DA,TP,2012	
FR9	2007-000282	R-CHIP;100KOHM,5%,1/10W,DA,TP,2012	
AR5	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
CR10	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
CR11	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
CR35	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
CR7	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
DR3L	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
DR3R	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
FR13	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
FR14	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
FR2	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
FR5	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
JR15	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
JR20	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
JR5	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
JR8R	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
JR9	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
LR2	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
BR6L	2007-000355	R-CHIP;12KOHM,5%,1/10W,DA,TP,2012	
BR6R	2007-000355	R-CHIP;12KOHM,5%,1/10W,DA,TP,2012	
JR4L	2007-000401	R-CHIP;150OHM,5%,1/10W,DA,TP,2012	
JR4R	2007-000401	R-CHIP;150OHM,5%,1/10W,DA,TP,2012	
-	2007-000409	R-CHIP;15KOHM,5%,1/10W,DA,TP,2012	
JR5L	2007-000409	R-CHIP;15KOHM,5%,1/10W,DA,TP,2012	
JR5R	2007-000409	R-CHIP;15KOHM,5%,1/10W,DA,TP,2012	
BR1L	2007-000457	R-CHIP;18KOHM,5%,1/10W,DA,TP,2012	
AR4L	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
FR18	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
BR2	2007-000477	R-CHIP;1MOHM,5%,1/10W,DA,TP,2012	
AR4	2007-000493	R-CHIP;2.2KOHM,5%,1/10W,DA,TP,2012	
FR20	2007-000493	R-CHIP;2.2KOHM,5%,1/10W,DA,TP,2012	
FR3L	2007-000493	R-CHIP;2.2KOHM,5%,1/10W,DA,TP,2012	
FR3R	2007-000493	R-CHIP;2.2KOHM,5%,1/10W,DA,TP,2012	
FR8R	2007-000493	R-CHIP;2.2KOHM,5%,1/10W,DA,TP,2012	
FR9L	2007-000493	R-CHIP;2.2KOHM,5%,1/10W,DA,TP,2012	
FR9R	2007-000493	R-CHIP;2.2KOHM,5%,1/10W,DA,TP,2012	
HR2L	2007-000493	R-CHIP;2.2KOHM,5%,1/10W,DA,TP,2012	
HR2R	2007-000493	R-CHIP;2.2KOHM,5%,1/10W,DA,TP,2012	
HR4L	2007-000493	R-CHIP;2.2KOHM,5%,1/10W,DA,TP,2012	
HR4R	2007-000493	R-CHIP;2.2KOHM,5%,1/10W,DA,TP,2012	
FR7L	2007-000518	R-CHIP;2.7KOHM,5%,1/10W,DA,TP,2012	
FR7R	2007-000518	R-CHIP;2.7KOHM,5%,1/10W,DA,TP,2012	
FR10	2007-000586	R-CHIP;22KOHM,5%,1/10W,DA,TP,2012	
FR13R	2007-000586	R-CHIP;22KOHM,5%,1/10W,DA,TP,2012	
FR1R	2007-000586	R-CHIP;22KOHM,5%,1/10W,DA,TP,2012	
FR2L	2007-000586	R-CHIP;22KOHM,5%,1/10W,DA,TP,2012	
FR2R	2007-000586	R-CHIP;22KOHM,5%,1/10W,DA,TP,2012	
FR6	2007-000586	R-CHIP;22KOHM,5%,1/10W,DA,TP,2012	
JR3	2007-000586	R-CHIP;22KOHM,5%,1/10W,DA,TP,2012	
JR7L	2007-000586	R-CHIP;22KOHM,5%,1/10W,DA,TP,2012	
JR7R	2007-000586	R-CHIP;22KOHM,5%,1/10W,DA,TP,2012	
AR3L	2007-000686	R-CHIP;3.3KOHM,5%,1/10W,DA,TP,2012	
AR5L	2007-000686	R-CHIP;3.3KOHM,5%,1/10W,DA,TP,2012	
HR1L	2007-000686	R-CHIP;3.3KOHM,5%,1/10W,DA,TP,2012	
AR1	2007-000774	R-CHIP;33KOHM,5%,1/10W,DA,TP,2012	
AR6	2007-000774	R-CHIP;33KOHM,5%,1/10W,DA,TP,2012	
FR15	2007-000774	R-CHIP;33KOHM,5%,1/10W,DA,TP,2012	
BR2L	2007-000822	R-CHIP;390OHM,5%,1/10W,DA,TP,2012	
BR2R	2007-000822	R-CHIP;390OHM,5%,1/10W,DA,TP,2012	
FR18L	2007-000822	R-CHIP;390OHM,5%,1/10W,DA,TP,2012	
FR18R	2007-000822	R-CHIP;390OHM,5%,1/10W,DA,TP,2012	
AR1R	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012	
CR37	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012	
JR13R	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012	
JR6	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012	
RR6	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012	
AR2L	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012	
AR2R	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012	
AR7	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012	
JR1R	2007-000981	R-CHIP;5.6KOHM,5%,1/10W,DA,TP,2012	
JR7	2007-000981	R-CHIP;5.6KOHM,5%,1/10W,DA,TP,2012	
AR6L	2007-001039	R-CHIP;56KOHM,5%,1/10W,DA,TP,2012	
AR6R	2007-001039	R-CHIP;56KOHM,5%,1/10W,DA,TP,2012	
AR7L	2007-001039	R-CHIP;56KOHM,5%,1/10W,DA,TP,2012	
AR7R	2007-001039	R-CHIP;56KOHM,5%,1/10W,DA,TP,2012	
CR39	2007-001177	R-CHIP;8.2KOHM,5%,1/10W,DA,TP,2012	
CR6	2007-001177	R-CHIP;8.2KOHM,5%,1/10W,DA,TP,2012	
CR8	2007-001177	R-CHIP;8.2KOHM,5%,1/10W,DA,TP,2012	
FR6R	2007-001177	R-CHIP;8.2KOHM,5%,1/10W,DA,TP,2012	
JR10	2007-001177	R-CHIP;8.2KOHM,5%,1/10W,DA,TP,2012	
JR12L	2007-001177	R-CHIP;8.2KOHM,5%,1/10W,DA,TP,2012	
JR12R	2007-001177	R-CHIP;8.2KOHM,5%,1/10W,DA,TP,2012	
JR5L	2007-001177	R-CHIP;8.2KOHM,5%,1/10W,DA,TP,2012	
JR5R	2007-001177	R-CHIP;8.2KOHM,5%,1/10W,DA,TP,2012	
FC5L	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	
FC5R	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	
FC7	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	
FC9	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	
FC6L	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
FC6R	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
JC2	2203-000361	C-CERAMIC,CHIP;0.15nF,5%,50V,NP0,TP,2012	
FC5	2203-000374	C-CERAMIC,CHIP;15nF,10%,50V,X7R,TP,2012	
FC11L	2203-000533	C-CERAMIC,CHIP;2.7nF,10%,50V,X7R,TP,2012,-	
FC11R	2203-000533	C-CERAMIC,CHIP;2.7nF,10%,50V,X7R,TP,2012,-	
FC8L	2203-000533	C-CERAMIC,CHIP;2.7nF,10%,50V,X7R,TP,2012,-	
FC8R	2203-000533	C-CERAMIC,CHIP;2.7nF,10%,50V,X7R,TP,2012,-	
JC11L	2203-000595	C-CERAMIC,CHIP;0.22nF,5%,50V,NP0,TP,2012	
JC11R	2203-000595	C-CERAMIC,CHIP;0.22nF,5%,50V,NP0,TP,2012	
FC7L	2203-000671	C-CERAMIC,CHIP;27nF,10%,50V,X7R,TP,2012,-	
FC7R	2203-000671	C-CERAMIC,CHIP;27nF,10%,50V,X7R,TP,2012,-	
FC3L	2203-000761	C-CERAMIC,CHIP;330nF,10%,16V,X7R,TP,2012,-	
FC3R	2203-000761	C-CERAMIC,CHIP;330nF,10%,16V,X7R,TP,2012,-	
AC1L	2203-000787	C-CERAMIC,CHIP;0.33nF,5%,50V,NP0,TP,2012	
AC1R	2203-000787	C-CERAMIC,CHIP;0.33nF,5%,50V,NP0,TP,2012	
CC3	2203-000787	C-CERAMIC,CHIP;0.33nF,5%,50V,NP0,TP,2012	
CC4	2203-000787	C-CERAMIC,CHIP;0.33nF,5%,50V,NP0,TP,2012	
CC5	2203-000787	C-CERAMIC,CHIP;0.33nF,5%,50V,NP0,TP,2012	
FC4L	2203-000802	C-CERAMIC,CHIP;33nF,10%,50V,X7R,TP,2012	
FC4R	2203-000802	C-CERAMIC,CHIP;33nF,10%,50V,X7R,TP,2012	
JC10L	2203-000892	C-CERAMIC,CHIP;4.7nF,10%,50V,X7R,TP,2012	
JC10R	2203-000892	C-CERAMIC,CHIP;4.7nF,10%,50V,X7R,TP,2012	
AC11L	2203-000953	C-CERAMIC,CHIP;0.47nF,5%,50V,NP0,TP,2012	
AC11R	2203-000953	C-CERAMIC,CHIP;0.47nF,5%,50V,NP0,TP,2012	
FC1	2203-000953	C-CERAMIC,CHIP;0.47nF,5%,50V,NP0,TP,2012	
JC10L	2203-000979	C-CERAMIC,CHIP;47nF,10%,50V,X7R,TP,2012	
JC10R	2203-000979	C-CERAMIC,CHIP;47nF,10%,50V,X7R,TP,2012	
JC22	2203-000979	C-CERAMIC,CHIP;47nF,10%,50V,X7R,TP,2012	
JC27	2203-000979	C-CERAMIC,CHIP;47nF,10%,50V,X7R,TP,2012	
FC13L	2203-001058	C-CERAMIC,CHIP;0.56nF,5%,50V,NP0,TP,2012	
FC13R	2203-001058	C-CERAMIC,CHIP;0.56nF,5%,50V,NP0,TP,2012	
JC4L	2203-001058	C-CERAMIC,CHIP;0.56nF,5%,50V,NP0,TP,2012	
JC4R	2203-001058	C-CERAMIC,CHIP;0.56nF,5%,50V,NP0,TP,2012	
JC5L	2203-001058	C-CERAMIC,CHIP;0.56nF,5%,50V,NP0,TP,2012	
JC5R	2203-001058	C-CERAMIC,CHIP;0.56nF,5%,50V,NP0,TP,2012	
AC3L	2203-001090	C-CERAMIC,CHIP;0.005nF,0.25pF,50V,NP0,TP,2012	
AC3R	2203-001090	C-CERAMIC,CHIP;0.005nF,0.25pF,50V,NP0,TP,2012	
FC9L	2203-001214	C-CERAMIC,CHIP;8.2nF,10%,50V,X7R,TP,2012,-	
FC9R	2203-001214	C-CERAMIC,CHIP;8.2nF,10%,50V,X7R,TP,2012,-	
FC10L	2203-001230	C-CERAMIC,CHIP;0.82nF,5%,50V,NP0,TP,2012	
FC10R	2203-001230	C-CERAMIC,CHIP;0.82nF,5%,50V,NP0,TP,2012	
FC4	2203-001537	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,2012	
JC2R	2203-001537	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,2012	
FC1L	2203-001611	C-CERAMIC,CHIP;0.022nF,5%,50V,NP0,TP,2012	
FC1R	2203-001611	C-CERAMIC,CHIP;0.022nF,5%,50V,NP0,TP,2012	
	AH92-00581A	**ASSY PCB;MAX-N73,FRONT**	**S.N.A.**
UIR1	0601-000564	LED-IR;SIDE-VIEW,1.5MM,100MW,5V,940MM	
ULD17	0601-001238	LED;ROUND,RED,3.1mm,697nm	
ULD21	0601-001432	LED;ROUND,BLUE,3mm,455nm	
ULD22	0601-001432	LED;ROUND,BLUE,3mm,455nm	
UPQ1	0603-000116	PHOTO-TR;NPN,30V,6V,40MA,100MW,-	
UPQ2	0603-000116	PHOTO-TR;NPN,30V,6V,40MA,100MW,-	
UPQ3	0603-000116	PHOTO-TR;NPN,30V,6V,40MA,100MW,-	
QJACK1	0603-001051	OPTIC TRANSMITTER;5V,6Mb/s,5m,-15dBm,660nm,20mA	
UIC5	1003-001162	IC-MOTOR DRIVER;KA3082,SIP,10PIN,25MIL,DOUBLE,	
UIC3	1203-000276	IC-POSI.FIXED REG.;7805,TO-220,3P,-,PLASTIC,4.8/5	
UX2	2801-001394	CRYSTAL-UNIT;32.768KHz,20ppm,28-AAY,12.5pF,	
UX1	2802-000181	RESONATOR-CERAMIC;6MHZ,0.3%,BK,9.0X4.0X7.5MM	
OFT1	2901-001139	FILTER-EMI ON BOARD;50V,.5A,-,390PF,7X2.5X5MM,TP,RADIAL	
ELE1	3406-001047	SWITCH-ROTARY;5V DC,0.5mA,-,12mm	
JOG	3406-001054	SWITCH-ROTARY;5V DC,0.5mA,-,7.5mm	
UCW3	3708-000122	CONNECTOR-FPC/FC/PIC;11P,1.25mm,ANGLE,SN	
UCW12	3708-000331	CONNECTOR-FPC/FC/PIC;9P,1.25mm,ANGLE,SN	
UCW10	3708-000448	CONNECTOR-FPC/FC/PIC;6P,1.25MM,STRAIGHT,	
UCW7	3708-000448	CONNECTOR-FPC/FC/PIC;6P,1.25MM,STRAIGHT,	
UCW5	3708-000450	CONNECTOR-FPC/FC/PIC;11P,1.25MM,STRAIGHT,	
UCW2	3708-000454	CONNECTOR-FPC/FC/PIC;22P,1.25MM,STRAIGHT,	
UCW4	3708-000492	CONNECTOR-FPC/FC/PIC;9P,1.25MM,-,SN	
UCW15	3708-001027	CONNECTOR-FPC/FC/PIC;6P,1.25MM,ANGLE,SN	
UCW16	3708-001027	CONNECTOR-FPC/FC/PIC;6P,1.25MM,ANGLE,SN	
UCW1	3708-001488	CONNECTOR-FPC/FC/PIC;30P,1.25mm,ANGLE,SN	
UCW11	3711-000826	CONNECTOR-HEADER;BOX,2P,1R,2mm,ANGLE,SN	
OCW1	3711-000907	CONNECTOR-HEADER;BOX,3P,1R,2mm,STRAIGHT,SN	
UCW6	3711-000907	CONNECTOR-HEADER;BOX,3P,1R,2mm,STRAIGHT,SN	
UCW9	3711-000907	CONNECTOR-HEADER;BOX,3P,1R,2mm,STRAIGHT,SN	
UCW3	3809-000142	CABLE-FLAT;300V,80C,200mm,11P,2mm,UL2877	
UCW4	3809-000142	CABLE-FLAT;300V,80C,200mm,11P,2mm,UL2877	
UCW5	3809-000142	CABLE-FLAT;300V,80C,200mm,11P,2mm,UL2877	
UCW10	3809-000148	CABLE-FLAT;300V,80C,250mm,9P,2mm,UL2877	

Location no.	Code no.	Description & Specifiation	Remarks
UCW11	3809-000148	CABLE-FLAT;300V,80C,250mm,9P,2mm,UL2877	
UCW12	3809-000148	CABLE-FLAT;300V,80C,250mm,9P,2mm,UL2877	
UCW4	3809-000148	CABLE-FLAT;300V,80C,250mm,9P,2mm,UL2877	
UCW5	3809-000148	CABLE-FLAT;300V,80C,250mm,9P,2mm,UL2877	
UCW6	3809-000148	CABLE-FLAT;300V,80C,250mm,9P,2mm,UL2877	
UCW7	3809-000148	CABLE-FLAT;300V,80C,250mm,9P,2mm,UL2877	
UCW8	3809-000148	CABLE-FLAT;300V,80C,250mm,9P,2mm,UL2877	
UCW9	3809-000148	CABLE-FLAT;300V,80C,250mm,9P,2mm,UL2877	
UCW10	3809-000199	CABLE-FLAT;30V,80C,300mm,6P,1.25mm,UL2896	
UCW11	3809-000199	CABLE-FLAT;30V,80C,300mm,6P,1.25mm,UL2896	
UCW12	3809-000199	CABLE-FLAT;30V,80C,300mm,6P,1.25mm,UL2896	
UCW13	3809-000199	CABLE-FLAT;30V,80C,300mm,6P,1.25mm,UL2896	
UCW14	3809-000199	CABLE-FLAT;30V,80C,300mm,6P,1.25mm,UL2896	
UCW15	3809-000199	CABLE-FLAT;30V,80C,300mm,6P,1.25mm,UL2896	
UCW7	3809-000199	CABLE-FLAT;30V,80C,300mm,6P,1.25mm,UL2896	
UCW8	3809-000199	CABLE-FLAT;30V,80C,300mm,6P,1.25mm,UL2896	
UCW9	3809-000199	CABLE-FLAT;30V,80C,300mm,6P,1.25mm,UL2896	
-	3809-001034	CABLE-FLAT;30V,80C,170MM,22P,1.25MM,UL289	
UCW1	3809-001184	CABLE-FLAT;30V,80C,160mm,30P,1.25mm,UL2896	
-	3809-001187	CABLE-FLAT;30V,80C,70mm,6P,1.25mm,UL2896	
REMO1	AC59-60060A	MODULE-REMOCON;GP1U281R,SHARP,38KHZ,-,-,-	
VFD	AH07-00020A	VF DISPLAY;HNA-15LM05,22SEG,138.2x48.3,MAX-N75	
OIC1	AH14-10004R	IC;M74HCU04,SOP,TAPE 14P	
MOTOR	AH31-10024A	MOTOR-DC;FF-130SH-14230,5VDC/150MA,	
OCW1	AH39-00023A	LEAD CONNECTOR-ASSY;-,51004-03,51004-03,03P,300MM,2547#28	
UCW6	AH39-00085A	LEAD CONNECTOR-ASSY;-,51004,5295,3P,150MM,1007#28	
UCW13	AH39-00192A	LEAD CONNECTOR-ASSY;-,-,-,-,#1007,28,50MM,BK/WH,BK,35023-2P,	
UCW17	AH39-00193A	LEAD CONNECTOR-ASSY;-,-,-,-,#1007,28,80MM,BK/WH,BK,-,51004-2	
	AH61-00373A	HOLDER-VFD;-,ABS 94HB,-,BLK,-,MAX-N75	
	AH61-00428A	HOLDER-SENSOR;-,ABS 94HB,-,BLK,-,MAX-N75	
UJW11	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
UJW23	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
UJW28	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
UJW29	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
UJW3	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
UJW30	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
UJW31	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
UJW50	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
UJW51	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
UJW62	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
UR146	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
UR16	2007-000221	R-CHIP;1.2KOHM,5%,1/10W,DA,TP,2012	
UR32	2007-000221	R-CHIP;1.2KOHM,5%,1/10W,DA,TP,2012	
UR17	2007-000241	R-CHIP;1.5KOHM,5%,1/10W,DA,TP,2012	
UR11	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
UR13	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
UR136	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
UR137	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
UR138	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
UR145	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
UR155	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
UR64	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
UR65	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
UR80	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
UJW52	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
UR15	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
UR31	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
UR66	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
UR67	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
UR68	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
UR69	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
UR70	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
UR71	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
UR72	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
UR73	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
UR75	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
UR76	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
UR77	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
UR78	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
UR200	2007-000477	R-CHIP;1MOHM,5%,1/10W,DA,TP,2012	
UR35	2007-000493	R-CHIP;2.2KOHM,5%,1/10W,DA,TP,2012	
UR5	2007-000493	R-CHIP;2.2KOHM,5%,1/10W,DA,TP,2012	
UR6	2007-000493	R-CHIP;2.2KOHM,5%,1/10W,DA,TP,2012	
UR90	2007-000493	R-CHIP;2.2KOHM,5%,1/10W,DA,TP,2012	
UR3	2007-000565	R-CHIP;220KOHM,5%,1/10W,DA,TP,2012	
UR20	2007-000686	R-CHIP;3.3KOHM,5%,1/10W,DA,TP,2012	
UR36	2007-000686	R-CHIP;3.3KOHM,5%,1/10W,DA,TP,2012	
UR156	2007-000876	R-CHIP;4.7MOHM,5%,1/10W,DA,TP,2012	
UR82	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012	
UR83	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012	
UR84	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012	
UR85	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012	
UR87	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012	
UR88	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012	
UR1A	2007-000981	R-CHIP;5.6KOHM,5%,1/10W,DA,TP,2012	
UR1	2007-001024	R-CHIP;560KOHM,5%,1/10W,DA,TP,2012	
UR38	2007-001071	R-CHIP;6.8KOHM,5%,1/10W,DA,TP,2012	
UR30	2007-001201	R-CHIP;820OHM,5%,1/10W,DA,TP,2012	
UR2	2007-001654	R-CHIP;10MOHM,1%,1/10W,DA,TP,2012	
UR30	2203-000595	C-CERAMIC,CHIP;0.22nF,5%,50V,NP0,TP,2012	
UR31	2203-000595	C-CERAMIC,CHIP;0.22nF,5%,50V,NP0,TP,2012	
UR32	2203-000595	C-CERAMIC,CHIP;0.22nF,5%,50V,NP0,TP,2012	
UC18	2203-000979	C-CERAMIC,CHIP;47nF,10%,50V,X7R,TP,2012	
UC13	2203-001611	C-CERAMIC,CHIP;0.022nF,5%,50V,NP0,TP,2012	
UC14	2203-001611	C-CERAMIC,CHIP;0.022nF,5%,50V,NP0,TP,2012	
UC11	2203-001619	C-CERAMIC,CHIP;0.027nF,5%,50V,NP0,TP,2012	
UC12	2203-001619	C-CERAMIC,CHIP;0.027nF,5%,50V,NP0,TP,2012	
UIC1	AH11-00015A	MASK ROM;LC86P6548-XXXX,100P,QFP,-,8BIT,-	
UIC2	AH14-10004M	IC;NJU3713G,SOP,TAPE 18P	
UD11	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
UD12	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
UD13	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
UD14	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
UD15	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
UD20	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
UD21	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
UD22	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
UD23	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
UZD1	0403-000344	DIODE-ZENER;UZ3.9B,3.9V,3.7-4.1V,500MW,	
UQ2	0504-000118	TR-DIGITAL;KSR1003,NPN,300MW,22K/22K,TO-92,TP	
UQ4	0504-000118	TR-DIGITAL;KSR1003,NPN,300MW,22K/22K,TO-92,TP	
UQ6	0504-000118	TR-DIGITAL;KSR1003,NPN,300MW,22K/22K,TO-92,TP	
UQ8	0504-000118	TR-DIGITAL;KSR1003,NPN,300MW,22K/22K,TO-92,TP	
UQ9	0504-000122	TR-DIGITAL;KSR1009Y,NPN,300mW,4.7K,TO-92,	
UQ10	0504-000128	TR-DIGITAL;-,NPN,200MW,22K/22K,SOT-23,TP	
UQ11	0504-000128	TR-DIGITAL;-,NPN,200MW,22K/22K,SOT-23,TP	
ULD10	0601-001232	LED;TR,LED,1PCS,130-260%	
ULD11	0601-001232	LED;TR,LED,1PCS,130-260%	
ULD12	0601-001232	LED;TR,LED,1PCS,130-260%	
ULD13	0601-001232	LED;TR,LED,1PCS,130-260%	
ULD18	0601-001232	LED;TR,LED,1PCS,130-260%	
ULD19	0601-001232	LED;TR,LED,1PCS,130-260%	
ULD2	0601-001232	LED;TR,LED,1PCS,130-260%	
ULD20	0601-001232	LED;TR,LED,1PCS,130-260%	
ULD4	0601-001232	LED;TR,LED,1PCS,130-260%	
ULD5	0601-001232	LED;TR,LED,1PCS,130-260%	
ULD7	0601-001232	LED;TR,LED,1PCS,130-260%	
ULD8	0601-001232	LED;TR,LED,1PCS,130-260%	
ULD3	0601-001236	LED;ROUND,AMB,3.1mm,610nm	
ULD6	0601-001236	LED;ROUND,AMB,3.1mm,610nm	
ULD9	0601-001236	LED;ROUND,AMB,3.1mm,610nm	
ULD1	0601-001238	LED;ROUND,RED,3.1mm,697nm	
ULD14	0601-001238	LED;ROUND,RED,3.1mm,697nm	
ULD15	0601-001238	LED;ROUND,RED,3.1mm,697nm	
ULD16	0601-001238	LED;ROUND,RED,3.1mm,697nm	
UR58	2001-000005	R-CARBON;390ohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR59	2001-000005	R-CARBON;390ohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR63	2001-000005	R-CARBON;390ohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR25	2001-000010	R-CARBON;68KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR53	2001-000010	R-CARBON;68KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR42	2001-000028	R-CARBON(S);100OHM,5%,1/2W,AA,TP,2.4X6.4MM	
UR44	2001-000221	R-CARBON;1.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR33	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR45	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR18	2001-000258	R-CARBON;1.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR34	2001-000258	R-CARBON;1.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR46	2001-000258	R-CARBON;1.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR121	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR166	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR167	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR100	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR101	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR102	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR103	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR104	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR105	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR106	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR135	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR139	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR140	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR141	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR142	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR143	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR144	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR23	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR39	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR51	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR7	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR8	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR92	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR93	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR94	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR95	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR96	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR97	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR98	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR99	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR4	2001-000362	R-CARBON;150OHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR57	2001-000362	R-CARBON;150OHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR60	2001-000362	R-CARBON;150OHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR62	2001-000362	R-CARBON;150OHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR41	2001-000405	R-CARBON;180OHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR54	2001-000405	R-CARBON;180OHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR55	2001-000405	R-CARBON;180OHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR56	2001-000405	R-CARBON;180OHM,5%,1/8W,AA,TP,1.8X3.2MM	
UJW16	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	

Location no.	Code no.	Description & Specifiation	Remarks
UJW19	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR107	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR108	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR109	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR110	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR112	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR113	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR115	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR116	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR117	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR118	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR119	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR120	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR122	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR123	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR124	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR125	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR126	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR127	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR128	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR129	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR168	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR43	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR79	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR19	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR47	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR24	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR52	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR86	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR89	2001-000554	R-CARBON;270OHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR48	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR147	2001-000708	R-CARBON;39OHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR164	2001-000708	R-CARBON;39OHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR165	2001-000708	R-CARBON;39OHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR12	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR130	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR150	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR151	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR154	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR21	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR37	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR49	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR91	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR111	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR114	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR22	2001-000890	R-CARBON;6.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR38	2001-000890	R-CARBON;6.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR50	2001-000890	R-CARBON;6.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR14	2001-000995	R-CARBON;820OHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR26	2001-000995	R-CARBON;820OHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR40	2001-001107	R-CARBON(S);220ohm,5%,1/2W,AA,TP,2.4x6.4mm	
UR157	2003-000468	R-METAL OXIDE(S);10ohm,5%,1W,AA,TP,3.3x9mm	
OC3	2201-000381	C-CERAMIC,DISC;22NF,20%,50V,Y5V,8.0x4.0mm,5mm,TP	
OC2	2201-000487	C-CERAMIC,DISC;33pF,5%,50V,SL,TP,5x3,5m	
UC8	2201-000565	C-CERAMIC,DISC;47nF,20%,50V,Y5V,12.5x4.0mm,5mm,TP	
UC9	2201-000565	C-CERAMIC,DISC;47nF,20%,50V,Y5V,12.5x4.0mm,5mm,TP	
UC16	2201-000783	C-CERAMIC,DISC;100nF,+80-20%,50V,Y5V,TP,8x3,5	
OC4	2401-000240	C-AL;100uF,20%,10V,GP,TP,5x11,5	
UC17	2401-000243	C-AL;100uF,20%,10V,GP,TP,6.3x5,5	
UC4	2401-000243	C-AL;100uF,20%,10V,GP,TP,6.3x5,5	
UC5	2401-000475	C-AL;10UF,20%,50V,GP,-,5X11,2MM	
UC6	2401-000475	C-AL;10UF,20%,50V,GP,-,5X11,2MM	
UC3	2401-000752	C-AL;220NF,20%,50V,GP,BK,3X5,1MM	
UC20	2401-001912	C-AL;1uF,20%,50V,GP,5x11mm,2mm,BK	
UC28	2401-001936	C-AL;22UF,20%,16V,GP,TP,5X11MM,5MM	
UC10	2401-001975	C-AL;47UF,20%,16V,GP,TP,5X11MM,5	
UC2	2401-002180	C-AL;2.2UF,20%,50V,GP,TP,5X11,5MM	
UC1	2409-000123	C-EDL;47000UF,4UA,5.5V,-,BK,-,5MM	
OBD1	3301-000297	CORE-FERRITE BEAD;AA,3.6x1.2x5.7mm,1400,2900G	
OBD2	3301-000297	CORE-FERRITE BEAD;AA,3.6x1.2x5.7mm,1400,2900G	
USW1	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW10	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW11	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW12	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW13	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW14	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW15	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW16	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW17	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW18	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW19	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW2	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW20	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW21	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW22	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW23	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW24	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW25	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW26	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW27	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW28	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW29	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW3	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	

Location no.	Code no.	Description & Specifiation	Remarks
USW30	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW31	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW32	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW33	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW34	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW35	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW36	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW37	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW4	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW5	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW6	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW7	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW8	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW9	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
		G3V1-H DECK CDP;CDP PACK	
		AH92-00005A ASSY-PCB-CD MAIN;G3VI,CD PACK	**S.N.A.**
NQ1502	0501-000314	TR-SMALL SIGNAL;KSA812,PNP,150mW,SOT-23,TP,90-	
NIC928	0904-001442	IC-DSP;9286,8Bit,QFP,80P,-,16.9344MHz,TR,CMOS,P	
NIC925	1003-000179	IC-MOTOR DRIVER;KA9258D,SOP,28P,-,SINGLE,-,ST,	
NIC922	1204-001286	IC-ASP;KB9223,QFP,80P,-,PLASTIC,6V,20	
NR109	2007-000282	R-CHIP;100KOHM,5%,1/10W,DA,TP,2012	
NR203	2007-000282	R-CHIP;100KOHM,5%,1/10W,DA,TP,2012	
NR300	2007-000282	R-CHIP;100KOHM,5%,1/10W,DA,TP,2012	
NR57L	2007-000282	R-CHIP;100KOHM,5%,1/10W,DA,TP,2012	
NR57R	2007-000282	R-CHIP;100KOHM,5%,1/10W,DA,TP,2012	
NR606	2007-000282	R-CHIP;100KOHM,5%,1/10W,DA,TP,2012	
NR602	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
NR603	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
NR104	2007-000338	R-CHIP;120KOHM,5%,1/10W,DA,TP,2012	
NR107	2007-000338	R-CHIP;120KOHM,5%,1/10W,DA,TP,2012	
NR100	2007-000355	R-CHIP;12KOHM,5%,1/10W,DA,TP,2012	
NR120	2007-000355	R-CHIP;12KOHM,5%,1/10W,DA,TP,2012	
NR121	2007-000355	R-CHIP;12KOHM,5%,1/10W,DA,TP,2012	
NR204	2007-000355	R-CHIP;12KOHM,5%,1/10W,DA,TP,2012	
NR103	2007-000395	R-CHIP;150KOHM,5%,1/10W,DA,TP,2012	
NR119	2007-000395	R-CHIP;150KOHM,5%,1/10W,DA,TP,2012	
NR13	2007-000395	R-CHIP;150KOHM,5%,1/10W,DA,TP,2012	
NR400	2007-000409	R-CHIP;15KOHM,5%,1/10W,DA,TP,2012	
NR115	2007-000444	R-CHIP;180KOHM,5%,1/10W,DA,TP,2012	
NR10	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
NR11	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
NR12	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
NR4	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
NR5	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
NR54L	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
NR54R	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
NR6	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
NR604	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
NR7	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
NR804	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
SR3	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
SR4	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
NR114	2007-000477	R-CHIP;1MOHM,5%,1/10W,DA,TP,2012	
NR50L	2007-000586	R-CHIP;22KOHM,5%,1/10W,DA,TP,2012	
NR50R	2007-000586	R-CHIP;22KOHM,5%,1/10W,DA,TP,2012	
NR101	2007-000593	R-CHIP;22OHM,5%,1/10W,DA,TP,2012	
NR200	2007-000653	R-CHIP;27KOHM,5%,1/10W,DA,TP,2012	
NR52L	2007-000653	R-CHIP;27KOHM,5%,1/10W,DA,TP,2012	
NR52R	2007-000653	R-CHIP;27KOHM,5%,1/10W,DA,TP,2012	
NR201	2007-000686	R-CHIP;3.3KOHM,5%,1/10W,DA,TP,2012	
NR202	2007-000686	R-CHIP;3.3KOHM,5%,1/10W,DA,TP,2012	
NR105	2007-000830	R-CHIP;39KOHM,5%,1/10W,DA,TP,2012	
NR995	2007-000830	R-CHIP;39KOHM,5%,1/10W,DA,TP,2012	
NR996	2007-000830	R-CHIP;39KOHM,5%,1/10W,DA,TP,2012	
NR997	2007-000830	R-CHIP;39KOHM,5%,1/10W,DA,TP,2012	
NR998	2007-000830	R-CHIP;39KOHM,5%,1/10W,DA,TP,2012	
NR53L	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012	
NR53R	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012	
NR55L	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012	
NR55R	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012	
SR2	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012	
NR117	2007-000898	R-CHIP;430Kohm,5%,1/10W,DA,TP,2012	
NR108	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012	
NR111	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012	
NR112	2007-001039	R-CHIP;56KOHM,5%,1/10W,DA,TP,2012	
NR116	2007-001195	R-CHIP;820KOHM,5%,1/10W,DA,TP,2012	
NR994	2007-001208	R-CHIP;82KOHM,5%,1/10W,DA,TP,2012	
NR999	2007-001208	R-CHIP;82KOHM,5%,1/10W,DA,TP,2012	
	2007-001216	R-CHIP;82OHM,5%,1/10W,DA,TP,2012	
NC107	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	
NC108	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	
NC119	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	
NC120	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	
NC121	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	
NC600	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	
NC901	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	
NC1	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
NC103	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
NC112	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
NC113	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
NC116	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	

Location no.	Code no.	Description & Specifiation	Remarks
NC205	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
NC502	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
NC503	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
NC504	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
NC53L	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
NC53R	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
NC602	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
NC800	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
NC804	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
NC905	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
SC1	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
SC2	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
SC6	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
NC190	2203-000335	C-CERAMIC,CHIP;0.012nF,5%,50V,NP0,TP,2012	
NC190	2203-000429	C-CERAMIC,CHIP;0.018nF,5%,50V,NP0,TP,2012	
NC117	2203-000477	C-CERAMIC,CHIP;1uF,+80-20%,16V,Y5V,TP,2012,-	
NC110	2203-000495	C-CERAMIC,CHIP;2.2nF,10%,50V,X7R,TP,2012	
NC118	2203-000787	C-CERAMIC,CHIP;0.33nF,5%,50V,NP0,TP,2012	
NC101	2203-000802	C-CERAMIC,CHIP;33nF,10%,50V,X7R,TP,2012	
NC111	2203-000802	C-CERAMIC,CHIP;33nF,10%,50V,X7R,TP,2012	
NC125	2203-000802	C-CERAMIC,CHIP;33nF,10%,50V,X7R,TP,2012	
NC100	2203-000892	C-CERAMIC,CHIP;4.7nF,10%,50V,X7R,TP,2012	
NC106	2203-000892	C-CERAMIC,CHIP;4.7nF,10%,50V,X7R,TP,2012	
NC200	2203-000979	C-CERAMIC,CHIP;47nF,10%,50V,X7R,TP,2012	
NC667	2203-000979	C-CERAMIC,CHIP;47nF,10%,50V,X7R,TP,2012	
NC115	2203-001137	C-CERAMIC,CHIP;68nF,+80-20%,50V,Y5V,TP,2012,-	
NC104	2203-001537	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,2012	
NC52L	2203-001537	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,2012	
NC52R	2203-001537	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,2012	
NC603	2203-001537	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,2012	
NC903	2203-001537	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,2012	
NC102	2203-001551	C-CERAMIC,CHIP;1.5nF,10%,50V,X7R,TP,2012	
NC201	2203-001551	C-CERAMIC,CHIP;1.5nF,10%,50V,X7R,TP,2012	
NC202	2203-001619	C-CERAMIC,CHIP;0.027nF,5%,50V,NP0,TP,2012	
NC203	2203-001619	C-CERAMIC,CHIP;0.027nF,5%,50V,NP0,TP,2012	
NL105	3301-000325	CORE-FERRITE BEAD;AB,3.2x2.5x1.3mm,-,-	
SIC1	1003-001162	IC-MOTOR DRIVER;KA3082,SIP,10PIN,25MIL,DOUBLE,	
SIC2	1003-001162	IC-MOTOR DRIVER;KA3082,SIP,10PIN,25MIL,DOUBLE,	
NXF100	2802-000211	RESONATOR-CERAMIC;16.93MHZ,0.5%,TP,10.0X5.0X10.0	
SCW5	3708-001131	CONNECTOR-FPC/FC/PIC;5P,1.25mm,STRAIGHT,SN	
WCW1	3708-001252	CONNECTOR-FPC/FC/PIC;16P,1mm,STRAIGHT-F,SN	
SCW1	3708-001438	CONNECTOR-FPC/FC/PIC;22P,1.25mm,ANGLE,SN	
NCW500	3711-000906	CONNECTOR-HEADER;BOX,3P,1R,2mm,ANGLE,SN	
SCW7	3711-003379	CONNECTOR-HEADER;NOWALL,3P,1R,2.5mm,STRAIGHT,SN	
NCW101	AH39-00060A	LEAD CONNECTOR-ASSY;-,51015-08,51004-08,8P,300MM,1007#28	
NCW102	AH39-20561P	LEAD CONNECTOR-ASSY;-,5295,PHR,6P,150mm,1007#28	
ND200	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
ND201	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
ND202	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
ND203	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
SZD1	0403-000352	DIODE-ZENER;UZ4.7BM,4.7V,4.4-5.0V,500mW,DO	
SZD2	0403-000361	DIODE-ZENER;UZ6.2BSB,6.2V,5.99-6.24V,50	
NQ1501	0501-000610	TR-SMALL SIGNAL;KSA928A-Y,PNP,1W,TO-92L,TP,160	
SR1	2001-000027	R-CARBON;100OHM,5%,1/4W,AA,TP,2.4X6.4MM	
NR106	2001-000319	R-CARBON;120KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
NR1	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
NR2	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
NR3	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
NR8	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
NR113	2001-000977	R-CARBON;8.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
NR555	2008-000140	R-FUSIBLE;2.2OHM,5%,1/2W,AA,TP,3.5X9.4MM	
NC400	2202-000243	C-CERAMIC,MLC-AXIAL;33PF,5%,50V,SL,3.5X19,-,TP	
NC300	2202-000796	C-CERAMIC,MLC-AXIAL;1nF,10%,50V,Y5P,TP,3.5x19,-	
NC106	2202-000817	C-CERAMIC,MLC-AXIAL;4.7NF,20%,16V,Y5R,TP,3.5X19,-	
NC117	2301-000389	C-FILM,PEF;150nF,5%,50V,TP,12.5x15x7.5,7m	
NC105	2401-000240	C-AL;100uF,20%,10V,GP,TP,5x11,5	
NC501	2401-000240	C-AL;100uF,20%,10V,GP,TP,5x11,5	
NC702	2401-000240	C-AL;100uF,20%,10V,GP,TP,5x11,5	
NC904	2401-000240	C-AL;100uF,20%,10V,GP,TP,5x11,5	
SC14	2401-000240	C-AL;100uF,20%,10V,GP,TP,5x11,5	
NC114	2401-000419	C-AL;10UF,20%,16V,GP,-,4X7,5	
NC301	2401-000778	C-AL;220uF,20%,10V,GP,-,6.3x11,2.5m	
NC700	2401-000778	C-AL;220uF,20%,10V,GP,-,6.3x11,2.5m	
NC701	2401-000778	C-AL;220uF,20%,10V,GP,-,6.3x11,2.5m	
SC5	2401-000795	C-AL;220UF,20%,16V,GP,-,8X11.5,3.5M	
NC703	2401-001102	C-AL;330UF,20%,16V,GP,TP,8X12,5	
NC124	2401-001324	C-AL;470nF,20%,50V,GP,BK,3x5,1mm	
NC204	2401-001324	C-AL;470nF,20%,50V,GP,BK,3x5,1mm	
NC666	2401-001895	C-AL;100uF,20%,16V,GP,6.3x11mm,2.5m	
NC122	2401-001952	C-AL;4.7UF,20%,50V,-,TP,6.3X7,5	
NC50L	2401-001952	C-AL;4.7UF,20%,50V,-,TP,6.3X7,5	
NC50R	2401-001952	C-AL;4.7UF,20%,50V,-,TP,6.3X7,5	
NC54	2401-001952	C-AL;4.7UF,20%,50V,-,TP,6.3X7,5	
NC55L	2401-001952	C-AL;4.7UF,20%,50V,-,TP,6.3X7,5	
NC55R	2401-001952	C-AL;4.7UF,20%,50V,-,TP,6.3X7,5	
NL101	2701-000111	INDUCTOR-AXIAL;100uH,10%,2.5x3.4mm	
NL102	2701-000111	INDUCTOR-AXIAL;100uH,10%,2.5x3.4mm	
NL100	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
SL1	2701-000179	INDUCTOR-AXIAL;33uH,10%,4.2x9.8mm	
NL300	3301-000297	CORE-FERRITE BEAD;AA,3.6x1.2x5.7mm,1400,2900G	
NL301	3301-000297	CORE-FERRITE BEAD;AA,3.6x1.2x5.7mm,1400,2900G	
NL302	3301-000297	CORE-FERRITE BEAD;AA,3.6x1.2x5.7mm,1400,2900G	
NIC05	AC14-12001G	IC;KA78L05,T,-	

Location no.	Code no.	Description & Specifiation	Remarks
SCO4	AC14-12001G	IC;KA78L05,T,-	
	AJ59-20150R	DECK-CDP PCB ASSY;G3A1-6NG,-,-,-,-	
	CMS300-R	CMS300,CD MECHA;MAXN72/73/75	
	AH81-00253A	A/S-PARTS-SPEAKER SYSTEM;SPEAKER SYSTEM,PS N72	

***** MAXN73 Parts List *****

AH26-00063A	TRANS-POWER;E85.8X50,-,-,-,-,SILICON STEEL SHEET,230	
AH39-00021A	LEAD-CONNECTOR ASSY;-,5264,GT201-6,6P,300MM,2547#28,2P SHIEL	
AH39-00202A	LEAD CONNECTOR-ASSY;-,1533#28,-,3P,200MM,-,-,5264-3P,GIL-S-3	
AH39-10002L	POWER CORD;CP2,KLCE-2F,2.15M,5239,VDE	
AH42-20001Q	ANT-LOOP;-,KS980214-01,18.5uH,CONNECTOR	
AH59-00004Q	REMOCON—ASSY;-,-,-,22KEY,MAX-N75,SAMSUNG	
AH59-20006S	DECK;ADR241FTW,-,DC12V,-,-,MAXN75,-	

AH92-00245A ASSY-PCB;SMK35/45,TUNER-T S.N.A.

TR6	2007-000030	R-CHIP;560HM,5%,1/10W,DA,TP,2012
TR101	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216
TR102	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216
TR103	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216
TR104	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216
TR19	2007-000282	R-CHIP;100KOHM,5%,1/10W,DA,TP,2012
TR45	2007-000282	R-CHIP;100KOHM,5%,1/10W,DA,TP,2012
TR47	2007-000282	R-CHIP;100KOHM,5%,1/10W,DA,TP,2012
TR49	2007-000282	R-CHIP;100KOHM,5%,1/10W,DA,TP,2012
RR2	2007-000290	R-CHIP;100OHM,5%,1/10W,DA,TP,2012
TR24	2007-000290	R-CHIP;100OHM,5%,1/10W,DA,TP,2012
TR43	2007-000290	R-CHIP;100OHM,5%,1/10W,DA,TP,2012
TR2	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012
TR21	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012
TR22	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012
TR46	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012
TR48	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012
TR50	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012
TR53	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012
TR54	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012
TR56	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012
TR10	2007-000308	R-CHIP;10OHM,5%,1/10W,DA,TP,2012
TR20	2007-000409	R-CHIP;15KOHM,5%,1/10W,DA,TP,2012
TR28	2007-000457	R-CHIP;18KOHM,5%,1/10W,DA,TP,2012
TR52	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012
TR9	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012
TR35	2007-000493	R-CHIP;2.2KOHM,5%,1/10W,DA,TP,2012
TR36	2007-000493	R-CHIP;2.2KOHM,5%,1/10W,DA,TP,2012
TR40	2007-000493	R-CHIP;2.2KOHM,5%,1/10W,DA,TP,2012
TR7	2007-000518	R-CHIP;2.7KOHM,5%,1/10W,DA,TP,2012
TR11	2007-000572	R-CHIP;220OHM,5%,1/10W,DA,TP,2012
TR105	2007-000586	R-CHIP;22KOHM,5%,1/10W,DA,TP,2012
TR15	2007-000586	R-CHIP;22KOHM,5%,1/10W,DA,TP,2012
TR37	2007-000586	R-CHIP;22KOHM,5%,1/10W,DA,TP,2012
TR12	2007-000686	R-CHIP;3.3KOHM,5%,1/10W,DA,TP,2012
TR29	2007-000686	R-CHIP;3.3KOHM,5%,1/10W,DA,TP,2012
TR23	2007-000710	R-CHIP;3.9KOHM,5%,1/10W,DA,TP,2012
TR8	2007-000822	R-CHIP;390OHM,5%,1/10W,DA,TP,2012
TR4	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012
TR51	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012
TR17	2007-000981	R-CHIP;5.6KOHM,5%,1/10W,DA,TP,2012
TR25	2007-001043	R-CHIP;56OHM,5%,1/10W,DA,TP,2012
TR27	2007-001071	R-CHIP;6.8KOHM,5%,1/10W,DA,TP,2012
TR38	2007-001177	R-CHIP;8.2KOHM,5%,1/10W,DA,TP,2012
TR44	2007-001177	R-CHIP;8.2KOHM,5%,1/10W,DA,TP,2012
TC41	2203-000239	C-CERAMIC,CHIP;0.1nF,5%,50V,NP0,TP,2012
RC2	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012
TC20	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012
TC28	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012
TC29	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012
TC3	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012
TC44	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012
TC7	2203-000429	C-CERAMIC,CHIP;0.018nF,5%,50V,NP0,TP,2012
TC1	2203-000609	C-CERAMIC,CHIP;22nF,10%,50V,X7R,TP,2012
TC5	2203-000609	C-CERAMIC,CHIP;22nF,10%,50V,X7R,TP,2012
TC99	2203-000609	C-CERAMIC,CHIP;22nF,10%,50V,X7R,TP,2012
TC33	2203-000844	C-CERAMIC,CHIP;39nF,10%,50V,X7R,TP,2012,-
RC7	2203-000979	C-CERAMIC,CHIP;47nF,10%,50V,X7R,TP,2012
TC10	2203-000979	C-CERAMIC,CHIP;47nF,10%,50V,X7R,TP,2012
TC13	2203-000979	C-CERAMIC,CHIP;47nF,10%,50V,X7R,TP,2012
TC15	2203-000979	C-CERAMIC,CHIP;47nF,10%,50V,X7R,TP,2012
TC35	2203-000979	C-CERAMIC,CHIP;47nF,10%,50V,X7R,TP,2012
TC45	2203-000979	C-CERAMIC,CHIP;47nF,10%,50V,X7R,TP,2012
TC6	2203-000979	C-CERAMIC,CHIP;47nF,10%,50V,X7R,TP,2012
RC8	2203-001058	C-CERAMIC,CHIP;0.56nF,5%,50V,NP0,TP,2012
TC61	2203-001105	C-CERAMIC,CHIP;6.8nF,10%,50V,X7R,TP,2012
TC62	2203-001105	C-CERAMIC,CHIP;6.8nF,10%,50V,X7R,TP,2012
TC32	2203-001132	C-CERAMIC,CHIP;0.68nF,5%,50V,NP0,TP,2012
TC2	2203-001517	C-CERAMIC,CHIP;0.015nF,5%,50V,NP0,TP,2012
RC4	2203-001524	C-CERAMIC,CHIP;0.047nF,5%,50V,NP0,TP,2012
RC5	2203-001524	C-CERAMIC,CHIP;0.047nF,5%,50V,NP0,TP,2012
TC63	2203-001551	C-CERAMIC,CHIP;1.5nF,10%,50V,X7R,TP,2012
TC64	2203-001551	C-CERAMIC,CHIP;1.5nF,10%,50V,X7R,TP,2012
TC50	2203-001611	C-CERAMIC,CHIP;0.022nF,5%,50V,NP0,TP,2012
TC51	2203-001611	C-CERAMIC,CHIP;0.022nF,5%,50V,NP0,TP,2012
TD3	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP
TD4	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP

Location no.	Code no.	Description & Specifiation	Remarks
TD5	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
TD6	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
TZD1	0403-000367	DIODE-ZENER;UZ7.5BSC,7.5V,7.33-7.64V,500mW	
RZD1	0403-000393	DIODE-ZENER;UZP5.1B,5.1V,4.8-5.4V,1W,DO-41	
TZD2	0403-000393	DIODE-ZENER;UZP5.1B,5.1V,4.8-5.4V,1W,DO-41	
TQ4	0501-000294	TR-SMALL SIGNAL;KSA708-Y,PNP,800mW,TO-92,TP,12	
TQ2	0501-000392	TR-SMALL SIGNAL;KSC838-O,NPN,250mW,TO-92,-,70-	
TQ3	0501-000392	TR-SMALL SIGNAL;KSC838-O,NPN,250mW,TO-92,-,70-	
TQ1	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,TP,120-	
TQ5	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,TP,120-	
TQ6	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,TP,120-	
TQ7	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,TP,120-	
TR30	2001-000117	R-CARBON(S);68OHM,5%,1/2W,AA,TP,2.4X6.4MM	
RR1A	2001-000118	R-CARBON(S);180ohm,5%,1/2W,AA,TP,2.4x6.4mm	
TR44	2001-000118	R-CARBON(S);180ohm,5%,1/2W,AA,TP,2.4x6.4mm	
TR58	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
TR5	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
-	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
TR39	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
TR1	2001-000331	R-CARBON;12KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
RR3	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
RR4	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
RR5	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
TR32	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
TR34	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
TR55	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
TR18	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
TR3	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
TR13	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
TR40	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
TR61	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
TR62	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
TR42	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
TR16	2001-000745	R-CARBON;4.7OHM,5%,1/8W,AA,TP,1.8X3.2MM	
TR41	2001-000802	R-CARBON;5.6Kohm,5%,1/8W,AA,TP,1.8x3.2m	
TR57	2001-000802	R-CARBON;5.6Kohm,5%,1/8W,AA,TP,1.8x3.2m	
TSR1	2103-000290	VR-SEMI;20Kohm,30%,1/10W,TOP	
TC14	2201-000565	C-CERAMIC,DISC;47nF,20%,50V,Y5V,12.5x4.0mm,5mm,TP	
TC39	2201-000565	C-CERAMIC,DISC;47nF,20%,50V,Y5V,12.5x4.0mm,5mm,TP	
RC9	2202-000796	C-CERAMIC,MLC-AXIAL;1nF,10%,50V,Y5P,TP,3.5x19,-	
TC40	2202-000796	C-CERAMIC,MLC-AXIAL;1nF,10%,50V,Y5P,TP,3.5x19,-	
TC42	2202-000796	C-CERAMIC,MLC-AXIAL;1nF,10%,50V,Y5P,TP,3.5x19,-	
TC48	2202-000807	C-CERAMIC,MLC-AXIAL;22NF,+80-20%,25V,Y5V,TP,3.5X19	
TC21	2401-000240	C-AL;100uF,20%,10V,GP,TP,5x11,5	
TC46	2401-000240	C-AL;100uF,20%,10V,GP,TP,5x11,5	
TC12	2401-000419	C-AL;10UF,20%,16V,GP,-,4X7,5	
TC26	2401-000419	C-AL;10UF,20%,16V,GP,-,4X7,5	
TC27	2401-000419	C-AL;10UF,20%,16V,GP,-,4X7,5	
TC30	2401-000419	C-AL;10UF,20%,16V,GP,-,4X7,5	
RC1	2401-000907	C-AL;22UF,20%,16V,GP,-,5X11,2MM	
TC34	2401-000907	C-AL;22UF,20%,16V,GP,-,5X11,2MM	
TC37	2401-001022	C-AL;3.3UF,20%,50V,GP,-,5X11,2MM	
TC38	2401-001164	C-AL;33UF,20%,16V,GP,-,5X11,2MM	
TC47	2401-001895	C-AL;100uF,20%,16V,GP,6.3x11mm,2.5m	
TC11	2401-001912	C-AL;1uF,20%,50V,GP,5x11mm,2mm,BK	
TC17	2401-001912	C-AL;1uF,20%,50V,GP,5x11mm,2mm,BK	
TC19	2401-001912	C-AL;1uF,20%,50V,GP,5x11mm,2mm,BK	
TC16	2401-001954	C-AL;4.7UF,20%,50V,GP,TP,5X11MM,5	
TC23	2401-001954	C-AL;4.7UF,20%,50V,GP,TP,5X11MM,5	
TC25	2401-001954	C-AL;4.7UF,20%,50V,GP,TP,5X11MM,5	
TC18	2401-001968	C-AL;470NF,20%,50V,GP,TP,5X11MM,5	
TC43	2401-001968	C-AL;470NF,20%,50V,GP,TP,5X11MM,5	
TC4	2401-001975	C-AL;47UF,20%,16V,GP,TP,5X11MM,5	
TC9	2401-001975	C-AL;47UF,20%,16V,GP,TP,5X11MM,5	
RC6	2401-002180	C-AL;2.2UF,20%,50V,GP,TP,5X11,5MM	
RIC1	AH14-10008E	IC;BU1923F,SOP,+5V	
VVC1	0405-000137	DIODE-VARACTOR;KV-1260,20V,100NA,T0-92S	
TFL4	14529-304-610	FILTER CERAMIC;AHCM2-450BL	
	2202-000263	C-CERAMIC,MLC-AXIAL;470pF,10%,50V,Y5P,TP,3.5x19,-	
TX1	2801-000734	CRYSTAL-UNIT;7.2MHZ,50PPM,28-AAM,12PF,30OHM	
RX1	2801-003601	CRYSTAL-UNIT;4.332MHz,30ppm,28-AAM,30pF,	
TFL2	2903-000105	FILTER-CERAMIC;BP,10.7MHZ+-25KHZ,180KHZ+-50KH	
TFL1	2903-000119	FILTER-CERAMIC;SFE10.7MJA-10-A	
TWA1	3710-001421	CONNECTOR-SOCKET;14P,1R,2mm,ANGLE,SN	
TJ2	3711-000814	CONNECTOR-HEADER;BOX,2P,1R,2.5mm,ANGLE,SN	
TJ1	3716-000210	TERMINAL-BLOCK;-,-,-,60V,7A	
HIC1	AH14-10007G	IC;LC72131,DIP,STICK PLL	
TIC1	AH14-10008B	IC;LA1837,DIP,RF+MPX	
TLPF1	AH26-00005A	TRANS-IF;-,LKS75M00-X000264-0,LOW PASS FILTER,-,7	
TLPF2	AH26-00005A	TRANS-IF;-,LKS75M00-X000264-0,LOW PASS FILTER,-,7	
TL2	AH26-10001E	TRANS-IF;KS940228-09,-,-,7.6X12.0,-,450KHZ,BULK,	
TL3	AH26-10020A	TRANS-DET;-,7KLL,DET,-,7.8MM,91PF,11.32M	
LW	AH27-00007A	COIL-OSC;LKS7FB00-0060BLO-0,-,LW OSC	
OSC	AH27-00007A	COIL-OSC;LKS7FB00-0060BLO-0,-,LW OSC	
MW	AH27-00008A	COIL-OSC;LKS75M00-0060LMO-0,-,MW OSC	
OSC	AH27-00008A	COIL-OSC;LKS75M00-0060LMO-0,-,MW OSC	
ANT	AH27-00011A	COIL-OSC;LKS75M00-X000262-0,-,LW ANT	
LW	AH27-00011A	COIL-OSC;LKS75M00-X000262-0,-,LW ANT	
ANT	AH27-00012A	COIL-OSC;LKS75M00-X000263-0,365UH,MW ANT	
MW	AH27-00012A	COIL-OSC;LKS75M00-X000263-0,365UH,MW ANT	
FM	AH40-10025S	TUNER-FM;KST-F404VA-1,4G,75ohm	
PACK	AH40-10025S	TUNER-FM;KST-F404VA-1,4G,75ohm	
FREE	AH61-20540A	HOLDER-TUNER;-,ABS,94HB,BLK,-,MAX940	

Location no.	Code no.	Description & Specifiation	Remarks
	AH65-30010A	CLAMP-WIRE;DALB-2,-,-,-	
	AH92-00580A	**ASSY PCB;MAX-N73,MAIN**	**S.N.A.**
AD1	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
AD10	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
AD2	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
AD4	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
AD7	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
AD8	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
AD9	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
CD1A	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
CD3	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
CD4	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
CD5	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
CD6	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
FD1	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
FD2	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
FD3	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
HD1	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
HD2	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
HD5	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
JD1	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
JD1A	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
JD2	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
JD2L	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
JD2R	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
JD3	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
JD4	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
LD1	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
RD4	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
RD6	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
HD3	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
HD4	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
RD1	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
RD2	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
RD3	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
RD5	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
RD9	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
RD7	0402-000151	DIODE-RECTIFIER;1N5392,100V,1.5A,DO-15,TP	
CZD1	0403-000354	DIODE-ZENER;UZ5.1B,5.1V,4.8-5.4V,500mW,DO-	
FZD3	0403-000354	DIODE-ZENER;UZ5.1B,5.1V,4.8-5.4V,500mW,DO-	
RZD4	0403-000354	DIODE-ZENER;UZ5.1B,5.1V,4.8-5.4V,500mW,DO-	
FZD1	0403-000363	DIODE-ZENER;UZ6.8BH,6.8V,6.8-7.2V,500mW,DO	
FZD2	0403-000363	DIODE-ZENER;UZ6.8BH,6.8V,6.8-7.2V,500mW,DO	
AZD1	0403-000369	DIODE-ZENER;UZ8.2BM,8.2V,7.9-8.5V,500MW	
AZD2	0403-000369	DIODE-ZENER;UZ8.2BM,8.2V,7.9-8.5V,500MW	
RZD3	0403-000379	DIODE-ZENER;UZP12B,12V,11.4-12.6V,1W,DO-41	
RZD5	0403-000396	DIODE-ZENER;UZP6.8B,6.8V,6.4-7.2V,1W,DO-41	
RZD1	0403-000570	DIODE-ZENER;UZP18B,18V,16.9-19.1V,1W,DO-41	
RZD2	0403-000570	DIODE-ZENER;UZP18B,18V,16.9-19.1V,1W,DO-41	
LQ3	0501-000010	TR-SMALL SIGNAL;KSC1008,NPN,800mW,TO-92,TP,120	
AQ9	0501-000294	TR-SMALL SIGNAL;KSA708-Y,PNP,800mW,TO-92,TP,12	
RQ4	0501-000294	TR-SMALL SIGNAL;KSA708-Y,PNP,800mW,TO-92,TP,12	
JQ8A	0501-000303	TR-SMALL SIGNAL;KSA733,PNP,250mW,TO-92,TP,120-	
LQ1	0501-000369	TR-SMALL SIGNAL;KSC2331-Y,NPN,1W,TO-92L,-,120-	
LQ2	0501-000369	TR-SMALL SIGNAL;KSC2331-Y,NPN,1W,TO-92L,-,120-	
AQ1L	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,TP,120-	
AQ1R	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,TP,120-	
AQ2L	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,TP,120-	
AQ2R	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,TP,120-	
CQ10	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,TP,120-	
CQ4	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,TP,120-	
CQ5	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,TP,120-	
CQ9	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,TP,120-	
FQ1L	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,TP,120-	
FQ1R	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,TP,120-	
JQ5	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,TP,120-	
JQ6	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,TP,120-	
JQ7	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,TP,120-	
RQ3	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,TP,120-	
AQ10	0501-000407	TR-SMALL SIGNAL;KSD471A-Y,NPN,800mW,TO-92,-,12	
HQ1L	0501-000407	TR-SMALL SIGNAL;KSD471A-Y,NPN,800mW,TO-92,-,12	
HQ1R	0501-000407	TR-SMALL SIGNAL;KSD471A-Y,NPN,800mW,TO-92,-,12	
JQ2L	0501-000407	TR-SMALL SIGNAL;KSD471A-Y,NPN,800mW,TO-92,-,12	
JQ2R	0501-000407	TR-SMALL SIGNAL;KSD471A-Y,NPN,800mW,TO-92,-,12	
CQ3	0501-000610	TR-SMALL SIGNAL;KSA928A-Y,PNP,1W,TO-92L,TP,160	
CQ6	0501-000610	TR-SMALL SIGNAL;KSA928A-Y,PNP,1W,TO-92L,TP,160	
CQ7	0501-000610	TR-SMALL SIGNAL;KSA928A-Y,PNP,1W,TO-92L,TP,160	
RQ1	0501-000610	TR-SMALL SIGNAL;KSA928A-Y,PNP,1W,TO-92L,TP,160	
AQ4	0504-000118	TR-DIGITAL;KSR1003,NPN,300MW,22K/22K,TO-92,TP	
CQ8	0504-000118	TR-DIGITAL;KSR1003,NPN,300MW,22K/22K,TO-92,TP	
JQ1	0504-000118	TR-DIGITAL;KSR1003,NPN,300MW,22K/22K,TO-92,TP	
JQ4	0504-000118	TR-DIGITAL;KSR1003,NPN,300MW,22K/22K,TO-92,TP	
JQ7L	0504-000118	TR-DIGITAL;KSR1003,NPN,300MW,22K/22K,TO-92,TP	
JQ7R	0504-000118	TR-DIGITAL;KSR1003,NPN,300MW,22K/22K,TO-92,TP	
JQ8	0504-000118	TR-DIGITAL;KSR1003,NPN,300MW,22K/22K,TO-92,TP	
AQ1	0504-001003	TR-DIGITAL;KSR2003,PNP,300MW,22K/22K,TO-92,TP	
CQ1	0504-001003	TR-DIGITAL;KSR2003,PNP,300MW,22K/22K,TO-92,TP	
CQ2	0504-001003	TR-DIGITAL;KSR2003,PNP,300MW,22K/22K,TO-92,TP	
FQ1	0504-001003	TR-DIGITAL;KSR2003,PNP,300MW,22K/22K,TO-92,TP	
JQ2	0504-001003	TR-DIGITAL;KSR2003,PNP,300MW,22K/22K,TO-92,TP	
JQ3	0504-001003	TR-DIGITAL;KSR2003,PNP,300MW,22K/22K,TO-92,TP	
JQ1L	0505-000197	FET-SILICON;2SK373Y,N,-,-,-,400MW,TO-92	

Location no.	Code no.	Description & Specifiation	Remarks
JQ1R	0505-000197	FET-SILICON;2SK373Y,N,-,-,-,400MW,TO-92	
JR13	2001-000005	R-CARBON;390ohm,5%,1/8W,AA,TP,1.8x3.2mm	
HR1	2001-000028	R-CARBON(S);100OHM,5%,1/2W,AA,TP,2.4X6.4MM	
HR2	2001-000028	R-CARBON(S);100OHM,5%,1/2W,AA,TP,2.4X6.4MM	
CR1	2001-000034	R-CARBON;220OHM,5%,1/4W,AA,TP,2.4X6.4MM	
FR12	2001-000034	R-CARBON;220OHM,5%,1/4W,AA,TP,2.4X6.4MM	
AR11	2001-000052	R-CARBON(S);3.3KOHM,5%,1/2W,AA,TP,2.4X6.4MM	
AR12	2001-000052	R-CARBON(S);3.3KOHM,5%,1/2W,AA,TP,2.4X6.4MM	
RR9	2001-000055	R-CARBON;4.7Kohm,5%,1/4W,AA,TP,2.4x6.4m	
LR1	2001-000109	R-CARBON(S);470OHM,5%,1/2W,AA,TP,2.4X6.4MM	
AR8L	2001-000221	R-CARBON;1.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
AR8R	2001-000221	R-CARBON;1.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
JR7	2001-000221	R-CARBON;1.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
FR4R	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
FR12L	2001-000258	R-CARBON;1.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
FR10L	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
FR10R	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
BR1	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
AR10A	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CR12	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CR2	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CR21	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CR25	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CR27	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CR28	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CR29	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CR3	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CR30	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CR31	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CR34	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CR36	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CR4	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CR5	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CR9	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
DR3L	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
FR3	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
FR7	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
HR4	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
JR11	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
JR8L	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
HR5L	2001-000302	R-CARBON;10OHM,5%,1/8W,AA,TP,1.8X3.2MM	
HR5R	2001-000302	R-CARBON;10OHM,5%,1/8W,AA,TP,1.8X3.2MM	
JR20	2001-000319	R-CARBON;120KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
BR1R	2001-000411	R-CARBON;18KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
JR10L	2001-000411	R-CARBON;18KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
JR10R	2001-000411	R-CARBON;18KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
AR4R	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CR26	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
RR17	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
RR7	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
AR24	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CR24	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
FR8L	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
HR5	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
HR9L	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
HR9R	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
BR1L	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
BR1R	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
AR19	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
FR1	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
FR13L	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
FR7	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
JW48	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
RR14	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
RR10	2001-000563	R-CARBON;27KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
AR3R	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
AR5R	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
HR1R	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
RR11	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
RR5	2001-000613	R-CARBON;3.9KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
AR10	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
AR1L	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CR14	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CR16	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CR18	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CR19	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CR20	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
HR3	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
JR12	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
JR13L	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
JW99	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
LR4	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
RR12	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
RR15	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
JR1	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
AR8	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
AR9	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
BR3L	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
BR3R	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
FR11L	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
FR11R	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
JR14	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
DR2L	2001-000802	R-CARBON;5.6Kohm,5%,1/8W,AA,TP,1.8x3.2m	

Location no.	Code no.	Description & Specifiation	Remarks
JR1L	2001-000802	R-CARBON;5.6Kohm,5%,1/8W,AA,TP,1.8x3.2m	
RR18	2001-000890	R-CARBON;6.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
FR6L	2001-000977	R-CARBON;8.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
FR4	2001-001077	R-CARBON(S);150ohm,5%,1/2W,AA,TP,2.4x6.4mm	
FR8	2001-001077	R-CARBON(S);150ohm,5%,1/2W,AA,TP,2.4x6.4mm	
RR13	2001-001077	R-CARBON(S);150ohm,5%,1/2W,AA,TP,2.4x6.4mm	
LR3	2001-001096	R-CARBON(S);2.2OHM,5%,1/2W,AA,TP,2.4X6.4MM	
LR6	2001-001138	R-CARBON(S);390ohm,5%,1/2W,AA,TP,2.4x6.4mm	
RR16	2001-001138	R-CARBON(S);390ohm,5%,1/2W,AA,TP,2.4x6.4mm	
RR3	2001-001153	R-CARBON(S);47ohm,5%,1/2W,AA,TP,2.4x6.4mm	
RR4	2001-001153	R-CARBON(S);47ohm,5%,1/2W,AA,TP,2.4x6.4mm	
CR15	2001-001178	R-CARBON(S);680OHM,5%,1/2W,AA,TP,2.4X6.4MM	
CR17	2001-001178	R-CARBON(S);680OHM,5%,1/2W,AA,TP,2.4X6.4MM	
CR22	2001-001178	R-CARBON(S);680OHM,5%,1/2W,AA,TP,2.4X6.4MM	
AR13	2003-000008	R-METAL OXIDE(S);100ohm,5%,1W,AA,TP,3.3x9mm	
AR15	2003-000008	R-METAL OXIDE(S);100ohm,5%,1W,AA,TP,3.3x9mm	
JSR2L	2103-000122	VR-SEMI;100Kohm,30%,1/10W,TOP	
JSR2R	2103-000122	VR-SEMI;100Kohm,30%,1/10W,TOP	
JSR3L	2103-000122	VR-SEMI;100Kohm,30%,1/10W,TOP	
JSR3R	2103-000122	VR-SEMI;100Kohm,30%,1/10W,TOP	
JSR1L	2103-000248	VR-SEMI;200KOHM,30%,1/10W,TOP	
JSR1R	2103-000248	VR-SEMI;200KOHM,30%,1/10W,TOP	
CVR1	2103-000341	VR-SEMI;2Kohm,30%,1/10W,TOP	
CVR2	2103-000341	VR-SEMI;2Kohm,30%,1/10W,TOP	
RC11	2201-000161	C-CERAMIC,DISC;10nF,+80-20%,500V,Y5V,TP,13.5x	
RC12	2201-000161	C-CERAMIC,DISC;10nF,+80-20%,500V,Y5V,TP,13.5x	
JC3L	2201-000368	C-CERAMIC,DISC;220PF,10%,50V,SL,TP,6.5X3.0,5	
JC3R	2201-000368	C-CERAMIC,DISC;220PF,10%,50V,SL,TP,6.5X3.0,5	
HC3L	2201-000381	C-CERAMIC,DISC;22NF,20%,50V,Y5V,8.0x4.0mm,5mm,TP	
HC3R	2201-000381	C-CERAMIC,DISC;22NF,20%,50V,Y5V,8.0x4.0mm,5mm,TP	
CC2	2201-000470	C-CERAMIC,DISC;330pF,10%,50V,SL,TP,6.5x3,5	
AC5L	2201-000565	C-CERAMIC,DISC;47nF,20%,50V,Y5V,12.5x4.0mm,5mm,TP	
AC5R	2201-000565	C-CERAMIC,DISC;47nF,20%,50V,Y5V,12.5x4.0mm,5mm,TP	
AC7L	2201-000565	C-CERAMIC,DISC;47nF,20%,50V,Y5V,12.5x4.0mm,5mm,TP	
AC7R	2201-000565	C-CERAMIC,DISC;47nF,20%,50V,Y5V,12.5x4.0mm,5mm,TP	
-	2202-000796	C-CERAMIC,MLC-AXIAL;1nF,10%,50V,Y5P,TP,3.5x19,-	
JC2L	2202-000796	C-CERAMIC,MLC-AXIAL;1nF,10%,50V,Y5P,TP,3.5x19,-	
JC1LA	2202-000820	C-CERAMIC,MLC-AXIAL;5.6NF,20%,16V,Y5R,TP,3.5X19,-	
JC1RA	2202-000820	C-CERAMIC,MLC-AXIAL;5.6NF,20%,16V,Y5R,TP,3.5X19,-	
AC6L	2301-000375	C-FILM,PEF;100nF,5%,50V,TP,11x12.5x6.5,7m	
AC6R	2301-000375	C-FILM,PEF;100nF,5%,50V,TP,11x12.5x6.5,7m	
FC6	2301-000375	C-FILM,PEF;100nF,5%,50V,TP,11x12.5x6.5,7m	
LC4	2301-000404	C-FILM,PEF;2.2NF,10%,50V,TP,5.5X7X3.2MM,5	
LC1	2301-000407	C-FILM,PEF;2.7NF,10%,50V,TP,5.5X7X3MM,5MM	
AC2	2301-000412	C-FILM,PEF;22NF,10%,50V,TP,6.5X10.5X4MM,5	
JC6L	2301-000419	C-FILM,PEF;27nF,10%,50V,TP,7.5x10.5x4mm,5	
JC6R	2301-000419	C-FILM,PEF;27nF,10%,50V,TP,7.5x10.5x4mm,5	
FC10	2301-000449	C-FILM,PEF;47NF,10%,50V,TP,8X11X4.5MM,5MM	
LC5	2301-000456	C-FILM,PEF;56NF,10%,50V,TP,8X12X4.5MM,5MM	
CC1	2401-000240	C-AL;100uF,20%,10V,GP,TP,5x11,5	
RC15	2401-000357	C-AL;100UF,20%,50V,GP,-,8X11.5,3.5M	
AC12	2401-000385	C-AL;10uF,20%,100V,GP,TP,6.3x11,5	
AC9	2401-000385	C-AL;10uF,20%,100V,GP,TP,6.3x11,5	
BC1L	2401-000419	C-AL;10UF,20%,16V,GP,-,4X7,5	
BC1R	2401-000419	C-AL;10UF,20%,16V,GP,-,4X7,5	
BC2	2401-000419	C-AL;10UF,20%,16V,GP,-,4X7,5	
BC3L	2401-000419	C-AL;10UF,20%,16V,GP,-,4X7,5	
BC3R	2401-000419	C-AL;10UF,20%,16V,GP,-,4X7,5	
JC1L	2401-000419	C-AL;10UF,20%,16V,GP,-,4X7,5	
JC1R	2401-000419	C-AL;10UF,20%,16V,GP,-,4X7,5	
JC4	2401-000419	C-AL;10UF,20%,16V,GP,-,4X7,5	
JC6	2401-000419	C-AL;10UF,20%,16V,GP,-,4X7,5	
AC10	2401-000475	C-AL;10UF,20%,50V,GP,-,5X11,2MM	
AC11	2401-000475	C-AL;10UF,20%,50V,GP,-,5X11,2MM	
FC12L	2401-000475	C-AL;10UF,20%,50V,GP,-,5X11,2MM	
FC12R	2401-000475	C-AL;10UF,20%,50V,GP,-,5X11,2MM	
FC14L	2401-000475	C-AL;10UF,20%,50V,GP,-,5X11,2MM	
FC14R	2401-000475	C-AL;10UF,20%,50V,GP,-,5X11,2MM	
FC17L	2401-000475	C-AL;10UF,20%,50V,GP,-,5X11,2MM	
FC17R	2401-000475	C-AL;10UF,20%,50V,GP,-,5X11,2MM	
RC8	2401-000475	C-AL;10UF,20%,50V,GP,-,5X11,2MM	
FC3	2401-000778	C-AL;220uF,20%,10V,GP,-,6.3x11,2.5m	
FC8	2401-000778	C-AL;220uF,20%,10V,GP,-,6.3x11,2.5m	
JC15	2401-000778	C-AL;220uF,20%,10V,GP,-,6.3x11,2.5m	
JC5	2401-000778	C-AL;220uF,20%,10V,GP,-,6.3x11,2.5m	
HC1	2401-000795	C-AL;220UF,20%,16V,GP,-,8X11.5,3.5M	
HC2	2401-000795	C-AL;220UF,20%,16V,GP,-,8X11.5,3.5M	
RC16	2401-000795	C-AL;220UF,20%,16V,GP,-,8X11.5,3.5M	
FC2	2401-000970	C-AL;22uF,20%,50V,WT,TP,5x11,5	
AC1	2401-001465	C-AL;47UF,20%,10V,GP,-,5X11,2MM	
BC2L	2401-001465	C-AL;47UF,20%,10V,GP,-,5X11,2MM	
BC2R	2401-001465	C-AL;47UF,20%,10V,GP,-,5X11,2MM	
FC12	2401-001465	C-AL;47UF,20%,10V,GP,-,5X11,2MM	
FC5	2401-001465	C-AL;47UF,20%,10V,GP,-,5X11,2MM	
JC3	2401-001465	C-AL;47UF,20%,10V,GP,-,5X11,2MM	
AC13	2401-001895	C-AL;100uF,20%,16V,GP,6.3x11mm,2.5m	
AC4L	2401-001895	C-AL;100uF,20%,16V,GP,6.3x11mm,2.5m	
AC4R	2401-001895	C-AL;100uF,20%,16V,GP,6.3x11mm,2.5m	
DC1	2401-001895	C-AL;100uF,20%,16V,GP,6.3x11mm,2.5m	
FC16L	2401-001895	C-AL;100uF,20%,16V,GP,6.3x11mm,2.5m	
FC16R	2401-001895	C-AL;100uF,20%,16V,GP,6.3x11mm,2.5m	
LC2	2401-001895	C-AL;100uF,20%,16V,GP,6.3x11mm,2.5m	
RC10	2401-001895	C-AL;100uF,20%,16V,GP,6.3x11mm,2.5m	

Location no.	Code no.	Description & Specifiation	Remarks
RC14	2401-001895	C-AL;100uF,20%,16V,GP,6.3x11mm,2.5m	
DC3L	2401-001912	C-AL;1uF,20%,50V,GP,5x11mm,2mm,BK	
DC3R	2401-001912	C-AL;1uF,20%,50V,GP,5x11mm,2mm,BK	
DC5L	2401-001912	C-AL;1uF,20%,50V,GP,5x11mm,2mm,BK	
DC5R	2401-001912	C-AL;1uF,20%,50V,GP,5x11mm,2mm,BK	
JC7L	2401-001912	C-AL;1uF,20%,50V,GP,5x11mm,2mm,BK	
JC7R	2401-001912	C-AL;1uF,20%,50V,GP,5x11mm,2mm,BK	
JC8L	2401-001912	C-AL;1uF,20%,50V,GP,5x11mm,2mm,BK	
JC8R	2401-001912	C-AL;1uF,20%,50V,GP,5x11mm,2mm,BK	
RC7	2401-001912	C-AL;1uF,20%,50V,GP,5x11mm,2mm,BK	
RC6	2401-001938	C-AL;22UF,20%,25V,GP,BK,5X11MM,2MM	
AL2L	2401-001954	C-AL;4.7UF,20%,50V,GP,TP,5X11MM,5	
AR2R	2401-001954	C-AL;4.7UF,20%,50V,GP,TP,5X11MM,5	
FC18	2401-001954	C-AL;4.7UF,20%,50V,GP,TP,5X11MM,5	
FC19L	2401-001954	C-AL;4.7UF,20%,50V,GP,TP,5X11MM,5	
FC19R	2401-001954	C-AL;4.7UF,20%,50V,GP,TP,5X11MM,5	
FC2L	2401-001954	C-AL;4.7UF,20%,50V,GP,TP,5X11MM,5	
FC2R	2401-001954	C-AL;4.7UF,20%,50V,GP,TP,5X11MM,5	
FC8L	2401-001954	C-AL;4.7UF,20%,50V,GP,TP,5X11MM,5	
FC8R	2401-001954	C-AL;4.7UF,20%,50V,GP,TP,5X11MM,5	
HC3	2401-001954	C-AL;4.7UF,20%,50V,GP,TP,5X11MM,5	
RC5	2401-001954	C-AL;4.7UF,20%,50V,GP,TP,5X11MM,5	
AC4	2401-001975	C-AL;47UF,20%,16V,GP,TP,5X11MM,5	
BC1	2401-001975	C-AL;47UF,20%,16V,GP,TP,5X11MM,5	
HC2L	2401-001975	C-AL;47UF,20%,16V,GP,TP,5X11MM,5	
HC2R	2401-001975	C-AL;47UF,20%,16V,GP,TP,5X11MM,5	
JC1	2401-001975	C-AL;47UF,20%,16V,GP,TP,5X11MM,5	
LC6	2401-001975	C-AL;47UF,20%,16V,GP,TP,5X11MM,5	
FC20	2401-002180	C-AL;2.2UF,20%,50V,GP,TP,5X11,5MM	
HC1L	2401-002180	C-AL;2.2UF,20%,50V,GP,TP,5X11,5MM	
HC1R	2401-002180	C-AL;2.2UF,20%,50V,GP,TP,5X11,5MM	
JW151	2701-000178	INDUCTOR-AXIAL;33uH,10%,3x7mm	
RL3	2701-000178	INDUCTOR-AXIAL;33uH,10%,3x7mm	
LL2	2701-000298	INDUCTOR-AXIAL;470uH,10%,4.2x9.8mm	
RL1	2701-000298	INDUCTOR-AXIAL;470uH,10%,4.2x9.8mm	
RL2	2701-000298	INDUCTOR-AXIAL;470uH,10%,4.2x9.8mm	
	3602-000147	FUSE-CLIP;250V,7.5A,30MOHM	
RBD1	0402-001258	DIODE-BRIDGE;GBU606,600V,6A,SIP-4,BK	
RBD2	0402-001258	DIODE-BRIDGE;GBU606,600V,6A,SIP-4,BK	
	0904-001316	IC-I/O CONTROLLER;M66010,24BIT,SOP,32P,200MIL,1.	
FIC3	1201-000163	IC-OP AMP;4560,SOP,8P,173MIL,DUAL,100V/mV,PLASTIC,	
HIC1	1201-000163	IC-OP AMP;4560,SOP,8P,173MIL,DUAL,100V/mV,PLASTIC,	
AIC1	1201-001333	IC-POWER AMP;411,SIP,22P,-,SINGLE,40dB,P	
RIC1	1203-001653	IC-VOLTAGE REGULATOR;4959,MULTIWATT,15P,700MIL,PLAS	
FIC2	1204-000156	IC-EQUALIZER;BA3834S,DIP,18P,-,PLASTIC,7V,-	
JIC1	1204-001471	IC-EQUALIZER;HA12211NT,DIP,30P,-,PLASTIC,15	
BIC1	1204-001474	IC-EQUALIZER;KA22241,SIP,9,-,PLASTIC,16,550	
FIC1	1204-001652	IC-SOUND PROCESSOR;M62433FP,QFP,80P,-,PLASTIC,7V,1370mW,-20	
RR8	2003-000455	R-METAL OXIDE(S);100ohm,5%,2W,AA,TP,4x12mm	
AR10L	2003-000471	R-METAL OXIDE(S);10ohm,5%,2W,AA,TP,4x12mm	
AR10R	2003-000471	R-METAL OXIDE(S);10ohm,5%,2W,AA,TP,4x12mm	
RR1	2003-000502	R-METAL OXIDE(S);150ohm,5%,2W,AA,TP,4x12mm	
PC1	2201-000546	C-CERAMIC,DISC;4.7NF,20%,400V,Y5U,BK,16X7,10	
PC2	2201-000546	C-CERAMIC,DISC;4.7NF,20%,400V,Y5U,BK,16X7,10	
GND	2202-000807	C-CERAMIC,MLC-AXIAL;22NF,+80-20%,25V,Y5V,TP,3.5X19	
HR5L	2202-000807	C-CERAMIC,MLC-AXIAL;22NF,+80-20%,25V,Y5V,TP,3.5X19	
HR5R	2202-000807	C-CERAMIC,MLC-AXIAL;22NF,+80-20%,25V,Y5V,TP,3.5X19	
AC7	2401-000230	C-AL;100uF,20%,100V,GP,TP,12.5x20,5	
AC8	2401-000230	C-AL;100uF,20%,100V,GP,TP,12.5x20,5	
RC13	2401-000230	C-AL;100uF,20%,100V,GP,TP,12.5x20,5	
RC1	2401-001942	C-AL;3300uF,20%,35V,GP,BK,18x35.5mm	
RC2	2401-003116	C-AL;4700uF,20%,35V,-,BK,18X35.5,7.	
RC3	2401-003385	C-AL;3300uF,20%,80V,GP,BK,25.4x50,1	
RC4	2401-003385	C-AL;3300uF,20%,80V,GP,BK,25.4x50,1	
BACK	2701-000178	INDUCTOR-AXIAL;33uH,10%,3x7mm	
MANU	2701-000178	INDUCTOR-AXIAL;33uH,10%,3x7mm	
RF2	3601-000216	FUSE-CARTRIDGE;250V,2.5A,TIME-LAG,GLASS,5x20mm	
CW1	3708-000181	CONNECTOR-FPC/FC/PIC;16P,1.25mm,STRAIGHT,SN	
MW1	3708-000258	CONNECTOR-FPC/FC/PIC;30P,1.25mm,STRAIGHT,SN	
PJ2	3711-000190	CONNECTOR-HEADER;1WALL,2P,1R,7.92MM,STRAIGHT,SN	
AW2	3711-000820	CONNECTOR-HEADER;BOX,2P,1R,2.5mm,STRAIGHT,SN	
JCW2	3711-000907	CONNECTOR-HEADER;BOX,3P,1R,2mm,STRAIGHT,SN	
CCW1	3711-002809	CONNECTOR-HEADER;BOX,8P,1R,2mm,STRAIGHT,SN	
JCW3	3711-003107	CONNECTOR-HEADER;BOX,3P,1R,2.5mm,STRAIGHT,SN	
JCW1	3711-003111	CONNECTOR-HEADER;BOX,6P,1R,2.5mm,-,BRAS	
RW1	3711-003112	CONNECTOR-HEADER;BOX,8P,1R,2.5MM,STRAIGHT,SN	
TCW1	3711-004109	CONNECTOR-HEADER;3WALL,14P,1R,2mm,STRAIGHT,SN	
SPK	3716-000209	TERMINAL-BLOCK;,-,-,60V,7A	
H1	3722-000363	JACK-PHONE;9P,6.4MM,AU,BLK,-	
AUX	3722-000377	JACK-RCA;4P/2C,3.5MM,SN,BLK,#16~22	
JLF1L	AH26-10002X	COIL-TRAP;KS940830-05,BIAS-TRAP,30DB,7.6,51PF,105K	
JLF1R	AH26-10002X	COIL-TRAP;KS940830-05,BIAS-TRAP,30DB,7.6,51PF,105K	
LL1	AH26-10003C	COIL-TRAP;PCHNS-5371EQJ,BIAS-TRAP,-,-,850PF,105KHZ	
PL1	AH27-10001F	COIL-CHOKE;27UH,K,Q30,-,-,DR(6.5*7.5),-,-,	
PL2	AH27-10001F	COIL-CHOKE;27UH,K,Q30,-,-,DR(6.5*7.5),-,-,	
AL1L	AH27-90001A	COIL-SPRING;,2.2UH,-,-,SPRING	
AL1R	AH27-90001A	COIL-SPRING;,2.2UH,-,-,SPRING	
AL2L	AH27-90001A	COIL-SPRING;,2.2UH,-,-,SPRING	
AL2R	AH27-90001A	COIL-SPRING;,2.2UH,-,-,SPRING	
FAN	AH31-12006A	MOTOR-DC-FAN;D0825A-12M,12V DC/0.17A,-	
RW1	AH39-20560P	LEAD CONNECTOR-ASSY;-,5264,51088,8p,300m	
MAIN	AH41-00145A	PCB MAIN;MAX-N75,1 LAYER,-,Æäì,-,330x197x1.6T,-,	
JW149	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	

Location no.	Code no.	Description & Specifiation	Remarks
JR4	2007-000032	R-CHIP;390KOHM,5%,1/10W,DA,TP,2012	
JW113	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
JW1A	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
JW2A	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
JW3A	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
AR8L	2007-000221	R-CHIP;1.2KOHM,5%,1/10W,DA,TP,2012	
AR8R	2007-000221	R-CHIP;1.2KOHM,5%,1/10W,DA,TP,2012	
JR8	2007-000221	R-CHIP;1.2KOHM,5%,1/10W,DA,TP,2012	
FR4L	2007-000241	R-CHIP;1.5KOHM,5%,1/10W,DA,TP,2012	
HR3L	2007-000241	R-CHIP;1.5KOHM,5%,1/10W,DA,TP,2012	
HR3R	2007-000241	R-CHIP;1.5KOHM,5%,1/10W,DA,TP,2012	
FR12R	2007-000267	R-CHIP;1.8KOHM,5%,1/10W,DA,TP,2012	
FR9	2007-000282	R-CHIP;100KOHM,5%,1/10W,DA,TP,2012	
AR5	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
CR10	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
CR11	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
CR35	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
CR7	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
DR3L	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
DR3R	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
FR13	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
FR14	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
FR2	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
FR5	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
JR15	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
JR20	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
JR5	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
JR8R	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
JR9	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
LR2	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
BR6L	2007-000355	R-CHIP;12KOHM,5%,1/10W,DA,TP,2012	
BR6R	2007-000355	R-CHIP;12KOHM,5%,1/10W,DA,TP,2012	
JR4L	2007-000401	R-CHIP;150OHM,5%,1/10W,DA,TP,2012	
JR4R	2007-000401	R-CHIP;150OHM,5%,1/10W,DA,TP,2012	
-	2007-000409	R-CHIP;15KOHM,5%,1/10W,DA,TP,2012	
JR5L	2007-000409	R-CHIP;15KOHM,5%,1/10W,DA,TP,2012	
JR5R	2007-000409	R-CHIP;15KOHM,5%,1/10W,DA,TP,2012	
BR1L	2007-000457	R-CHIP;18KOHM,5%,1/10W,DA,TP,2012	
AR4L	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
FR18	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
BR2	2007-000477	R-CHIP;1MOHM,5%,1/10W,DA,TP,2012	
AR4	2007-000493	R-CHIP;2.2KOHM,5%,1/10W,DA,TP,2012	
FR20	2007-000493	R-CHIP;2.2KOHM,5%,1/10W,DA,TP,2012	
FR3L	2007-000493	R-CHIP;2.2KOHM,5%,1/10W,DA,TP,2012	
FR3R	2007-000493	R-CHIP;2.2KOHM,5%,1/10W,DA,TP,2012	
FR8R	2007-000493	R-CHIP;2.2KOHM,5%,1/10W,DA,TP,2012	
FR9L	2007-000493	R-CHIP;2.2KOHM,5%,1/10W,DA,TP,2012	
FR9R	2007-000493	R-CHIP;2.2KOHM,5%,1/10W,DA,TP,2012	
HR2L	2007-000493	R-CHIP;2.2KOHM,5%,1/10W,DA,TP,2012	
HR2R	2007-000493	R-CHIP;2.2KOHM,5%,1/10W,DA,TP,2012	
HR4L	2007-000493	R-CHIP;2.2KOHM,5%,1/10W,DA,TP,2012	
HR4R	2007-000493	R-CHIP;2.2KOHM,5%,1/10W,DA,TP,2012	
FR7L	2007-000518	R-CHIP;2.7KOHM,5%,1/10W,DA,TP,2012	
FR7R	2007-000518	R-CHIP;2.7KOHM,5%,1/10W,DA,TP,2012	
FR10	2007-000586	R-CHIP;22KOHM,5%,1/10W,DA,TP,2012	
FR13R	2007-000586	R-CHIP;22KOHM,5%,1/10W,DA,TP,2012	
FR1R	2007-000586	R-CHIP;22KOHM,5%,1/10W,DA,TP,2012	
FR2L	2007-000586	R-CHIP;22KOHM,5%,1/10W,DA,TP,2012	
FR2R	2007-000586	R-CHIP;22KOHM,5%,1/10W,DA,TP,2012	
FR6	2007-000586	R-CHIP;22KOHM,5%,1/10W,DA,TP,2012	
JR3	2007-000586	R-CHIP;22KOHM,5%,1/10W,DA,TP,2012	
JR7L	2007-000586	R-CHIP;22KOHM,5%,1/10W,DA,TP,2012	
JR7R	2007-000586	R-CHIP;22KOHM,5%,1/10W,DA,TP,2012	
AR3L	2007-000686	R-CHIP;3.3KOHM,5%,1/10W,DA,TP,2012	
AR5L	2007-000686	R-CHIP;3.3KOHM,5%,1/10W,DA,TP,2012	
HR1L	2007-000686	R-CHIP;3.3KOHM,5%,1/10W,DA,TP,2012	
AR1	2007-000774	R-CHIP;33KOHM,5%,1/10W,DA,TP,2012	
AR6	2007-000774	R-CHIP;33KOHM,5%,1/10W,DA,TP,2012	
FR15	2007-000774	R-CHIP;33KOHM,5%,1/10W,DA,TP,2012	
BR2L	2007-000822	R-CHIP;390OHM,5%,1/10W,DA,TP,2012	
BR2R	2007-000822	R-CHIP;390OHM,5%,1/10W,DA,TP,2012	
FR18L	2007-000822	R-CHIP;390OHM,5%,1/10W,DA,TP,2012	
FR18R	2007-000822	R-CHIP;390OHM,5%,1/10W,DA,TP,2012	
AR1R	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012	
CR37	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012	
JR13R	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012	
JR6	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012	
RR6	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012	
AR2L	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012	
AR2R	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012	
AR7	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012	
JR1R	2007-000981	R-CHIP;5.6KOHM,5%,1/10W,DA,TP,2012	
JR7	2007-000981	R-CHIP;5.6KOHM,5%,1/10W,DA,TP,2012	
AR6L	2007-001039	R-CHIP;56KOHM,5%,1/10W,DA,TP,2012	
AR6R	2007-001039	R-CHIP;56KOHM,5%,1/10W,DA,TP,2012	
AR7L	2007-001039	R-CHIP;56KOHM,5%,1/10W,DA,TP,2012	
AR7R	2007-001039	R-CHIP;56KOHM,5%,1/10W,DA,TP,2012	
CR39	2007-001177	R-CHIP;8.2KOHM,5%,1/10W,DA,TP,2012	
CR6	2007-001177	R-CHIP;8.2KOHM,5%,1/10W,DA,TP,2012	
CR8	2007-001177	R-CHIP;8.2KOHM,5%,1/10W,DA,TP,2012	
FR6R	2007-001177	R-CHIP;8.2KOHM,5%,1/10W,DA,TP,2012	
JR10	2007-001177	R-CHIP;8.2KOHM,5%,1/10W,DA,TP,2012	
JR12L	2007-001177	R-CHIP;8.2KOHM,5%,1/10W,DA,TP,2012	

Location no.	Code no.	Description & Specifiation	Remarks
JR12R	2007-001177	R-CHIP;8.2KOHM,5%,1/10W,DA,TP,2012	
JR5L	2007-001177	R-CHIP;8.2KOHM,5%,1/10W,DA,TP,2012	
JR5R	2007-001177	R-CHIP;8.2KOHM,5%,1/10W,DA,TP,2012	
FC5L	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	
FC5R	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	
FC7	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	
FC9	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	
FC6L	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
FC6R	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
JC2	2203-000361	C-CERAMIC,CHIP;0.15nF,5%,50V,NP0,TP,2012	
FC5	2203-000374	C-CERAMIC,CHIP;15nF,10%,50V,X7R,TP,2012	
FC11L	2203-000533	C-CERAMIC,CHIP;2.7nF,10%,50V,X7R,TP,2012,-	
FC11R	2203-000533	C-CERAMIC,CHIP;2.7nF,10%,50V,X7R,TP,2012,-	
FC8L	2203-000533	C-CERAMIC,CHIP;2.7nF,10%,50V,X7R,TP,2012,-	
FC8R	2203-000533	C-CERAMIC,CHIP;2.7nF,10%,50V,X7R,TP,2012,-	
JC11L	2203-000595	C-CERAMIC,CHIP;0.22nF,5%,50V,NP0,TP,2012	
JC11R	2203-000595	C-CERAMIC,CHIP;0.22nF,5%,50V,NP0,TP,2012	
FC7L	2203-000671	C-CERAMIC,CHIP;27nF,10%,50V,X7R,TP,2012,-	
FC7R	2203-000671	C-CERAMIC,CHIP;27nF,10%,50V,X7R,TP,2012,-	
FC3L	2203-000761	C-CERAMIC,CHIP;330nF,10%,16V,X7R,TP,2012,-	
FC3R	2203-000761	C-CERAMIC,CHIP;330nF,10%,16V,X7R,TP,2012,-	
AC1L	2203-000787	C-CERAMIC,CHIP;0.33nF,5%,50V,NP0,TP,2012	
AC1R	2203-000787	C-CERAMIC,CHIP;0.33nF,5%,50V,NP0,TP,2012	
CC3	2203-000787	C-CERAMIC,CHIP;0.33nF,5%,50V,NP0,TP,2012	
CC4	2203-000787	C-CERAMIC,CHIP;0.33nF,5%,50V,NP0,TP,2012	
CC5	2203-000787	C-CERAMIC,CHIP;0.33nF,5%,50V,NP0,TP,2012	
FC4L	2203-000802	C-CERAMIC,CHIP;33nF,10%,50V,X7R,TP,2012	
FC4R	2203-000802	C-CERAMIC,CHIP;33nF,10%,50V,X7R,TP,2012	
JC10L	2203-000892	C-CERAMIC,CHIP;4.7nF,10%,50V,X7R,TP,2012	
JC10R	2203-000892	C-CERAMIC,CHIP;4.7nF,10%,50V,X7R,TP,2012	
AC11L	2203-000953	C-CERAMIC,CHIP;0.47nF,5%,50V,NP0,TP,2012	
AC11R	2203-000953	C-CERAMIC,CHIP;0.47nF,5%,50V,NP0,TP,2012	
FC1	2203-000953	C-CERAMIC,CHIP;0.47nF,5%,50V,NP0,TP,2012	
JC10L	2203-000979	C-CERAMIC,CHIP;47nF,10%,50V,X7R,TP,2012	
JC10R	2203-000979	C-CERAMIC,CHIP;47nF,10%,50V,X7R,TP,2012	
JC22	2203-000979	C-CERAMIC,CHIP;47nF,10%,50V,X7R,TP,2012	
JC27	2203-000979	C-CERAMIC,CHIP;47nF,10%,50V,X7R,TP,2012	
FC13L	2203-001058	C-CERAMIC,CHIP;0.56nF,5%,50V,NP0,TP,2012	
FC13R	2203-001058	C-CERAMIC,CHIP;0.56nF,5%,50V,NP0,TP,2012	
JC4L	2203-001058	C-CERAMIC,CHIP;0.56nF,5%,50V,NP0,TP,2012	
JC4R	2203-001058	C-CERAMIC,CHIP;0.56nF,5%,50V,NP0,TP,2012	
JC5L	2203-001058	C-CERAMIC,CHIP;0.56nF,5%,50V,NP0,TP,2012	
JC5R	2203-001058	C-CERAMIC,CHIP;0.56nF,5%,50V,NP0,TP,2012	
AC3L	2203-001090	C-CERAMIC,CHIP;0.005nF,0.25pF,50V,NP0,TP,2012	
AC3R	2203-001090	C-CERAMIC,CHIP;0.005nF,0.25pF,50V,NP0,TP,2012	
FC9L	2203-001214	C-CERAMIC,CHIP;8.2nF,10%,50V,X7R,TP,2012,-	
FC9R	2203-001214	C-CERAMIC,CHIP;8.2nF,10%,50V,X7R,TP,2012,-	
FC10L	2203-001230	C-CERAMIC,CHIP;0.82nF,5%,50V,NP0,TP,2012	
FC10R	2203-001230	C-CERAMIC,CHIP;0.82nF,5%,50V,NP0,TP,2012	
FC4	2203-001537	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,2012	
JC2R	2203-001537	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,2012	
FC1L	2203-001611	C-CERAMIC,CHIP;0.022nF,5%,50V,NP0,TP,2012	
FC1R	2203-001611	C-CERAMIC,CHIP;0.022nF,5%,50V,NP0,TP,2012	
	AH92-00581A	**ASSY PCB;MAX-N73,FRONT**	**S.N.A.**
UIR1	0601-000564	LED-IR;SIDE-VIEW,1.5MM,100MW,5V,940MM	
ULD17	0601-001238	LED;ROUND,RED,3.1mm,697nm	
ULD21	0601-001432	LED;ROUND,BLUE,3mm,455nm	
ULD22	0601-001432	LED;ROUND,BLUE,3mm,455nm	
UPQ1	0603-000116	PHOTO-TR;NPN,30V,6V,40MA,100MW,-	
UPQ2	0603-000116	PHOTO-TR;NPN,30V,6V,40MA,100MW,-	
UPQ3	0603-000116	PHOTO-TR;NPN,30V,6V,40MA,100MW,-	
OJACK1	0603-001051	OPTIC TRANSMITTER;5V,6Mb/s,5m,-15dBm,660nm,20mA	
UIC5	1003-001162	IC-MOTOR DRIVER;KA3082,SIP,10PIN,25MIL,DOUBLE,	
UIC3	1203-000276	IC-POSI.FIXED REG.;7805,TO-220,3P,-,PLASTIC,4.8/5	
UX2	2801-001394	CRYSTAL-UNIT;32.768KHz,20ppm,28-AAY,12.5pF,	
UX1	2802-000181	RESONATOR-CERAMIC;6MHZ,0.3%,BK,9.0X4.0X7.5MM	
OFT1	2901-001139	FILTER-EMI ON BOARD;50V,.5A,-,390PF,7X2.5X5MM,TP,RADIAL	
ELE1	3406-001047	SWITCH-ROTARY;5V DC,0.5mA,-,12mm	
JOG	3406-001054	SWITCH-ROTARY;5V DC,0.5mA,-,7.5mm	
UCW3	3708-000122	CONNECTOR-FPC/FC/PIC;11P,1.25mm,ANGLE,SN	
UCW12	3708-000331	CONNECTOR-FPC/FC/PIC;9P,1.25mm,ANGLE,SN	
UCW10	3708-000448	CONNECTOR-FPC/FC/PIC;6P,1.25MM,STRAIGHT,	
UCW7	3708-000448	CONNECTOR-FPC/FC/PIC;6P,1.25MM,STRAIGHT,	
UCW5	3708-000450	CONNECTOR-FPC/FC/PIC;11P,1.25MM,STRAIGHT,	
UCW2	3708-000454	CONNECTOR-FPC/FC/PIC;22P,1.25MM,STRAIGHT,	
UCW4	3708-000492	CONNECTOR-FPC/FC/PIC;9P,1.25MM,-,SN	
UCW15	3708-001027	CONNECTOR-FPC/FC/PIC;6P,1.25MM,ANGLE,SN	
UCW16	3708-001027	CONNECTOR-FPC/FC/PIC;6P,1.25MM,ANGLE,SN	
UCW1	3708-001488	CONNECTOR-FPC/FC/PIC;30P,1.25mm,ANGLE,SN	
UCW11	3711-000826	CONNECTOR-HEADER;BOX,2P,1R,2mm,ANGLE,SN	
OCW1	3711-000907	CONNECTOR-HEADER;BOX,3P,1R,2mm,STRAIGHT,SN	
UCW6	3711-000907	CONNECTOR-HEADER;BOX,3P,1R,2mm,STRAIGHT,SN	
UCW9	3711-000907	CONNECTOR-HEADER;BOX,3P,1R,2mm,STRAIGHT,SN	
UCW3	3809-000142	CABLE-FLAT;300V,80C,200mm,11P,2mm,UL2877	
UCW4	3809-000142	CABLE-FLAT;300V,80C,200mm,11P,2mm,UL2877	
UCW5	3809-000142	CABLE-FLAT;300V,80C,200mm,11P,2mm,UL2877	
UCW10	3809-000148	CABLE-FLAT;300V,80C,250mm,9P,2mm,UL2877	
UCW11	3809-000148	CABLE-FLAT;300V,80C,250mm,9P,2mm,UL2877	
UCW12	3809-000148	CABLE-FLAT;300V,80C,250mm,9P,2mm,UL2877	
UCW4	3809-000148	CABLE-FLAT;300V,80C,250mm,9P,2mm,UL2877	
UCW5	3809-000148	CABLE-FLAT;300V,80C,250mm,9P,2mm,UL2877	
UCW6	3809-000148	CABLE-FLAT;300V,80C,250mm,9P,2mm,UL2877	

Location no.	Code no.	Description & Specifiation	Remarks
UCW7	3809-000148	CABLE-FLAT;300V,80C,250mm,9P,2mm,UL2877	
UCW8	3809-000148	CABLE-FLAT;300V,80C,250mm,9P,2mm,UL2877	
UCW9	3809-000148	CABLE-FLAT;300V,80C,250mm,9P,2mm,UL2877	
UCW10	3809-000199	CABLE-FLAT;30V,80C,300mm,6P,1.25mm,UL2896	
UCW11	3809-000199	CABLE-FLAT;30V,80C,300mm,6P,1.25mm,UL2896	
UCW12	3809-000199	CABLE-FLAT;30V,80C,300mm,6P,1.25mm,UL2896	
UCW13	3809-000199	CABLE-FLAT;30V,80C,300mm,6P,1.25mm,UL2896	
UCW14	3809-000199	CABLE-FLAT;30V,80C,300mm,6P,1.25mm,UL2896	
UCW15	3809-000199	CABLE-FLAT;30V,80C,300mm,6P,1.25mm,UL2896	
UCW7	3809-000199	CABLE-FLAT;30V,80C,300mm,6P,1.25mm,UL2896	
UCW8	3809-000199	CABLE-FLAT;30V,80C,300mm,6P,1.25mm,UL2896	
UCW9	3809-000199	CABLE-FLAT;30V,80C,300mm,6P,1.25mm,UL2896	
-	3809-001034	CABLE-FLAT;30V,80C,170MM,22P,1.25MM,UL289	
UCW1	3809-001184	CABLE-FLAT;30V,80C,160mm,30P,1.25mm,UL2896	
-	3809-001187	CABLE-FLAT;30V,80C,70mm,6P,1.25mm,UL2896	
REMO1	AC59-60060A	MODULE-REMOCON;GP1U281R,SHARP,38KHZ,-,-,-	
VFD	AH07-00020A	VF DISPLAY;HNA-15LM05,22SEG,138.2x48.3,MAX-N75	
OIC1	AH14-10004R	IC;M74HCU04,SOP,TAPE 14P	
MOTOR	AH31-10024A	MOTOR-DC;FF-130SH-14230,5VDC/150MA,	
OCW1	AH39-00023A	LEAD CONNECTOR-ASSY;-,51004-03,51004-03,03P,300MM,2547#28	
UCW6	AH39-00085A	LEAD CONNECTOR-ASSY;-,51004,5295,3P,150MM,1007#28	
UCW13	AH39-00192A	LEAD CONNECTOR-ASSY;-,-,-,-,#1007,28,50MM,BK/WH,BK,35023-2P,	
UCW17	AH39-00193A	LEAD CONNECTOR-ASSY;-,-,-,-,#1007,28,80MM,BK/WH,BK,-,51004-2	
	AH61-00373A	HOLDER-VFD;-,ABS 94HB,-,BLK,-,MAX-N75	
	AH61-00428A	HOLDER-SENSOR;-,ABS 94HB,-,BLK,-,MAX-N75	
UJW11	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
UJW23	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
UJW28	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
UJW29	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
UJW3	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
UJW30	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
UJW31	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
UJW50	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
UJW51	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
UJW62	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
UR146	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
UR16	2007-000221	R-CHIP;1.2KOHM,5%,1/10W,DA,TP,2012	
UR32	2007-000221	R-CHIP;1.2KOHM,5%,1/10W,DA,TP,2012	
UR17	2007-000241	R-CHIP;1.5KOHM,5%,1/10W,DA,TP,2012	
UR11	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
UR13	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
UR136	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
UR137	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
UR138	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
UR145	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
UR155	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
UR64	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
UR65	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
UR80	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
UJW52	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
UR15	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
UR31	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
UR66	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
UR67	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
UR68	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
UR69	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
UR70	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
UR71	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
UR72	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
UR73	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
UR75	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
UR76	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
UR77	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
UR78	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
UR200	2007-000477	R-CHIP;1MOHM,5%,1/10W,DA,TP,2012	
UR35	2007-000493	R-CHIP;2.2KOHM,5%,1/10W,DA,TP,2012	
UR5	2007-000493	R-CHIP;2.2KOHM,5%,1/10W,DA,TP,2012	
UR6	2007-000493	R-CHIP;2.2KOHM,5%,1/10W,DA,TP,2012	
UR90	2007-000493	R-CHIP;2.2KOHM,5%,1/10W,DA,TP,2012	
UR3	2007-000565	R-CHIP;220KOHM,5%,1/10W,DA,TP,2012	
UR20	2007-000686	R-CHIP;3.3KOHM,5%,1/10W,DA,TP,2012	
UR36	2007-000686	R-CHIP;3.3KOHM,5%,1/10W,DA,TP,2012	
UR156	2007-000876	R-CHIP;4.7MOHM,5%,1/10W,DA,TP,2012	
UR82	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012	
UR83	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012	
UR84	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012	
UR85	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012	
UR87	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012	
UR88	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012	
UR1A	2007-000981	R-CHIP;5.6KOHM,5%,1/10W,DA,TP,2012	
UR1	2007-001024	R-CHIP;560KOHM,5%,1/10W,DA,TP,2012	
UR38	2007-001071	R-CHIP;6.8KOHM,5%,1/10W,DA,TP,2012	
UR30	2007-001201	R-CHIP;820OHM,5%,1/10W,DA,TP,2012	
UR2	2007-001654	R-CHIP;10MOHM,1%,1/10W,DA,TP,2012	
UR30	2203-000595	C-CERAMIC,CHIP;0.22nF,5%,50V,NP0,TP,2012	
UR31	2203-000595	C-CERAMIC,CHIP;0.22nF,5%,50V,NP0,TP,2012	
UR32	2203-000595	C-CERAMIC,CHIP;0.22nF,5%,50V,NP0,TP,2012	
UC18	2203-000979	C-CERAMIC,CHIP;47nF,10%,50V,X7R,TP,2012	
UC13	2203-001611	C-CERAMIC,CHIP;0.022nF,5%,50V,NP0,TP,2012	
UC14	2203-001611	C-CERAMIC,CHIP;0.022nF,5%,50V,NP0,TP,2012	
UC11	2203-001619	C-CERAMIC,CHIP;0.027nF,5%,50V,NP0,TP,2012	
UC12	2203-001619	C-CERAMIC,CHIP;0.027nF,5%,50V,NP0,TP,2012	
UIC1	AH11-00015A	MASK ROM;LC86P6548-XXXX,100P,QFP,-,8BIT,-	

Location no.	Code no.	Description & Specifiation	Remarks
UIC2	AH14-10004M	IC;NJU3713G,SOP,TAPE 18P	
UD11	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
UD12	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
UD13	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
UD14	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
UD15	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
UD20	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
UD21	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
UD22	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
UD23	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
UZD1	0403-000344	DIODE-ZENER;UZ3.9B,3.9V,3.7-4.1V,500MW,	
UQ2	0504-000118	TR-DIGITAL;KSR1003,NPN,300MW,22K/22K,TO-92,TP	
UQ4	0504-000118	TR-DIGITAL;KSR1003,NPN,300MW,22K/22K,TO-92,TP	
UQ6	0504-000118	TR-DIGITAL;KSR1003,NPN,300MW,22K/22K,TO-92,TP	
UQ8	0504-000118	TR-DIGITAL;KSR1003,NPN,300MW,22K/22K,TO-92,TP	
UQ9	0504-000122	TR-DIGITAL;KSR1009Y,NPN,300mW,4.7K,TO-92,	
UQ10	0504-000128	TR-DIGITAL;-,NPN,200MW,22K/22K,SOT-23,TP	
UQ11	0504-000128	TR-DIGITAL;-,NPN,200MW,22K/22K,SOT-23,TP	
ULD10	0601-001232	LED;TR,LED,1PCS,130-260%	
ULD11	0601-001232	LED;TR,LED,1PCS,130-260%	
ULD12	0601-001232	LED;TR,LED,1PCS,130-260%	
ULD13	0601-001232	LED;TR,LED,1PCS,130-260%	
ULD18	0601-001232	LED;TR,LED,1PCS,130-260%	
ULD19	0601-001232	LED;TR,LED,1PCS,130-260%	
ULD2	0601-001232	LED;TR,LED,1PCS,130-260%	
ULD20	0601-001232	LED;TR,LED,1PCS,130-260%	
ULD4	0601-001232	LED;TR,LED,1PCS,130-260%	
ULD5	0601-001232	LED;TR,LED,1PCS,130-260%	
ULD7	0601-001232	LED;TR,LED,1PCS,130-260%	
ULD8	0601-001232	LED;TR,LED,1PCS,130-260%	
ULD3	0601-001236	LED;ROUND,AMB,3.1mm,610nm	
ULD6	0601-001236	LED;ROUND,AMB,3.1mm,610nm	
ULD9	0601-001236	LED;ROUND,AMB,3.1mm,610nm	
ULD1	0601-001238	LED;ROUND,RED,3.1mm,697nm	
ULD14	0601-001238	LED;ROUND,RED,3.1mm,697nm	
ULD15	0601-001238	LED;ROUND,RED,3.1mm,697nm	
ULD16	0601-001238	LED;ROUND,RED,3.1mm,697nm	
UR58	2001-000005	R-CARBON;390ohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR59	2001-000005	R-CARBON;390ohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR63	2001-000005	R-CARBON;390ohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR25	2001-000010	R-CARBON;68KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR53	2001-000010	R-CARBON;68KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR42	2001-000028	R-CARBON(S);100OHM,5%,1/2W,AA,TP,2.4X6.4MM	
UR44	2001-000221	R-CARBON;1.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR33	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR45	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR18	2001-000258	R-CARBON;1.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR34	2001-000258	R-CARBON;1.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR46	2001-000258	R-CARBON;1.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR121	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR166	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR167	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR100	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR101	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR102	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR103	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR104	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR105	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR106	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR135	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR139	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR140	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR141	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR142	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR143	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR144	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR23	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR39	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR51	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR7	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR8	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR92	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR93	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR94	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR95	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR96	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR97	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR98	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR99	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR4	2001-000362	R-CARBON;150OHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR57	2001-000362	R-CARBON;150OHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR60	2001-000362	R-CARBON;150OHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR62	2001-000362	R-CARBON;150OHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR41	2001-000405	R-CARBON;180OHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR54	2001-000405	R-CARBON;180OHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR55	2001-000405	R-CARBON;180OHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR56	2001-000405	R-CARBON;180OHM,5%,1/8W,AA,TP,1.8X3.2MM	
UJW16	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UJW19	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR107	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR108	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR109	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR110	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	

Location no.	Code no.	Description & Specifiation	Remarks
UR112	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR113	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR115	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR116	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR117	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR118	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR119	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR120	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR122	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR123	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR124	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR125	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR126	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR127	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR128	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR129	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR168	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR43	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR79	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR19	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR47	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR24	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR52	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR86	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR89	2001-000554	R-CARBON;270OHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR48	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR147	2001-000708	R-CARBON;39OHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR164	2001-000708	R-CARBON;39OHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR165	2001-000708	R-CARBON;39OHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR12	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR130	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR150	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR151	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR154	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR21	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR37	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR49	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR91	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR111	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR114	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR22	2001-000890	R-CARBON;6.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR38	2001-000890	R-CARBON;6.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR50	2001-000890	R-CARBON;6.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR14	2001-000995	R-CARBON;820OHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR26	2001-000995	R-CARBON;820OHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR40	2001-001107	R-CARBON(S);220ohm,5%,1/2W,AA,TP,2.4x6.4mm	
UR157	2003-000468	R-METAL OXIDE(S);10ohm,5%,1W,AA,TP,3.3x9mm	
OC3	2201-000381	C-CERAMIC,DISC;22NF,20%,50V,Y5V,8.0x4.0mm,5mm,TP	
OC2	2201-000487	C-CERAMIC,DISC;33pF,5%,50V,SL,TP,5x3,5m	
UC8	2201-000565	C-CERAMIC,DISC;47nF,20%,50V,Y5V,12.5x4.0mm,5mm,TP	
UC9	2201-000565	C-CERAMIC,DISC;47nF,20%,50V,Y5V,12.5x4.0mm,5mm,TP	
UC16	2201-000783	C-CERAMIC,DISC;100nF,+80-20%,50V,Y5V,TP,8x3,5	
OC4	2401-000240	C-AL;100uF,20%,10V,GP,TP,5x11,5	
UC17	2401-000243	C-AL;100uF,20%,10V,GP,TP,6.3x5,5	
UC4	2401-000243	C-AL;100uF,20%,10V,GP,TP,6.3x5,5	
UC5	2401-000475	C-AL;10UF,20%,50V,GP,-,5X11,2MM	
UC6	2401-000475	C-AL;10UF,20%,50V,GP,-,5X11,2MM	
UC3	2401-000752	C-AL;220NF,20%,50V,GP,BK,3X5,1MM	
UC20	2401-001912	C-AL;1uF,20%,50V,GP,5x11mm,2mm,BK	
UC28	2401-001936	C-AL;22UF,20%,16V,GP,TP,5X11MM,5MM	
UC10	2401-001975	C-AL;47UF,20%,16V,GP,TP,5X11MM,5	
UC2	2401-002180	C-AL;2.2UF,20%,50V,GP,TP,5X11,5MM	
UC1	2409-000123	C-EDL;47000UF,4UA,5.5V,-,BK,-,5MM	
OBD1	3301-000297	CORE-FERRITE BEAD;AA,3.6x1.2x5.7mm,1400,2900G	
OBD2	3301-000297	CORE-FERRITE BEAD;AA,3.6x1.2x5.7mm,1400,2900G	
USW1	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW10	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW11	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW12	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW13	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW14	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW15	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW16	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW17	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW18	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW19	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW2	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW20	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW21	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW22	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW23	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW24	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW25	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW26	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW27	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW28	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW29	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW3	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW30	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW31	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW32	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW33	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW34	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	

Location no.	Code no.	Description & Specifiation	Remarks
USW35	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW36	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW37	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW4	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW5	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW6	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW7	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW8	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW9	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
	G3V1-H	**DECK CDP;CDP PACK**	**S.N.A.**
	AH92-00005A	**ASSY-PCB-CD MAIN;G3VI,CD PACK**	**S.N.A.**
NQ1502	0501-000314	TR-SMALL SIGNAL;KSA812,PNP,150mW,SOT-23,TP,90-	
NIC928	0904-001442	IC-DSP;9286,8Bit,QFP,80P,-,16.9344MHz,TR,CMOS,P	
NIC925	1003-000179	IC-MOTOR DRIVER;KA9258D,SOP,28P,-,SINGLE,-,ST,	
NIC922	1204-001286	IC-ASP;KB9223,QFP,80P,-,PLASTIC,6V,20	
NR109	2007-000282	R-CHIP;100KOHM,5%,1/10W,DA,TP,2012	
NR203	2007-000282	R-CHIP;100KOHM,5%,1/10W,DA,TP,2012	
NR300	2007-000282	R-CHIP;100KOHM,5%,1/10W,DA,TP,2012	
NR57L	2007-000282	R-CHIP;100KOHM,5%,1/10W,DA,TP,2012	
NR57R	2007-000282	R-CHIP;100KOHM,5%,1/10W,DA,TP,2012	
NR606	2007-000282	R-CHIP;100KOHM,5%,1/10W,DA,TP,2012	
NR602	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
NR603	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
NR104	2007-000338	R-CHIP;120KOHM,5%,1/10W,DA,TP,2012	
NR107	2007-000338	R-CHIP;120KOHM,5%,1/10W,DA,TP,2012	
NR100	2007-000355	R-CHIP;12KOHM,5%,1/10W,DA,TP,2012	
NR120	2007-000355	R-CHIP;12KOHM,5%,1/10W,DA,TP,2012	
NR121	2007-000355	R-CHIP;12KOHM,5%,1/10W,DA,TP,2012	
NR204	2007-000355	R-CHIP;12KOHM,5%,1/10W,DA,TP,2012	
NR103	2007-000395	R-CHIP;150KOHM,5%,1/10W,DA,TP,2012	
NR119	2007-000395	R-CHIP;150KOHM,5%,1/10W,DA,TP,2012	
NR13	2007-000395	R-CHIP;150KOHM,5%,1/10W,DA,TP,2012	
NR400	2007-000409	R-CHIP;15KOHM,5%,1/10W,DA,TP,2012	
NR115	2007-000444	R-CHIP;180KOHM,5%,1/10W,DA,TP,2012	
NR10	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
NR11	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
NR12	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
NR4	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
NR5	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
NR54L	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
NR54R	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
NR6	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
NR604	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
NR7	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
NR804	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
SR3	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
SR4	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
NR114	2007-000477	R-CHIP;1MOHM,5%,1/10W,DA,TP,2012	
NR50L	2007-000586	R-CHIP;22KOHM,5%,1/10W,DA,TP,2012	
NR50R	2007-000586	R-CHIP;22KOHM,5%,1/10W,DA,TP,2012	
NR101	2007-000593	R-CHIP;22OHM,5%,1/10W,DA,TP,2012	
NR200	2007-000653	R-CHIP;27KOHM,5%,1/10W,DA,TP,2012	
NR52L	2007-000653	R-CHIP;27KOHM,5%,1/10W,DA,TP,2012	
NR52R	2007-000653	R-CHIP;27KOHM,5%,1/10W,DA,TP,2012	
NR201	2007-000686	R-CHIP;3.3KOHM,5%,1/10W,DA,TP,2012	
NR202	2007-000686	R-CHIP;3.3KOHM,5%,1/10W,DA,TP,2012	
NR105	2007-000830	R-CHIP;39KOHM,5%,1/10W,DA,TP,2012	
NR995	2007-000830	R-CHIP;39KOHM,5%,1/10W,DA,TP,2012	
NR996	2007-000830	R-CHIP;39KOHM,5%,1/10W,DA,TP,2012	
NR997	2007-000830	R-CHIP;39KOHM,5%,1/10W,DA,TP,2012	
NR998	2007-000830	R-CHIP;39KOHM,5%,1/10W,DA,TP,2012	
NR53L	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012	
NR53R	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012	
NR55L	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012	
NR55R	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012	
SR2	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012	
NR117	2007-000898	R-CHIP;430Kohm,5%,1/10W,DA,TP,2012	
NR108	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012	
NR111	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012	
NR112	2007-001039	R-CHIP;56KOHM,5%,1/10W,DA,TP,2012	
NR116	2007-001195	R-CHIP;820KOHM,5%,1/10W,DA,TP,2012	
NR994	2007-001208	R-CHIP;82KOHM,5%,1/10W,DA,TP,2012	
NR999	2007-001208	R-CHIP;82KOHM,5%,1/10W,DA,TP,2012	
	2007-001216	R-CHIP;82OHM,5%,1/10W,DA,TP,2012	
NC107	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	
NC108	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	
NC119	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	
NC120	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	
NC121	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	
NC600	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	
NC901	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	
NC1	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
NC103	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
NC112	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
NC113	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
NC116	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
NC205	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
NC502	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
NC503	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
NC504	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
NC53L	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	

Location no.	Code no.	Description & Specifiation	Remarks
NC53R	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
NC602	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
NC800	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
NC804	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
NC905	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
SC1	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
SC2	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
SC6	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
NC190	2203-000335	C-CERAMIC,CHIP;0.012nF,5%,50V,NP0,TP,2012	
NC190	2203-000429	C-CERAMIC,CHIP;0.018nF,5%,50V,NP0,TP,2012	
NC117	2203-000477	C-CERAMIC,CHIP;1uF,+80-20%,16V,Y5V,TP,2012,-	
NC110	2203-000495	C-CERAMIC,CHIP;2.2nF,10%,50V,X7R,TP,2012	
NC118	2203-000787	C-CERAMIC,CHIP;0.33nF,5%,50V,NP0,TP,2012	
NC101	2203-000802	C-CERAMIC,CHIP;33nF,10%,50V,X7R,TP,2012	
NC111	2203-000802	C-CERAMIC,CHIP;33nF,10%,50V,X7R,TP,2012	
NC125	2203-000802	C-CERAMIC,CHIP;33nF,10%,50V,X7R,TP,2012	
NC100	2203-000892	C-CERAMIC,CHIP;4.7nF,10%,50V,X7R,TP,2012	
NC106	2203-000892	C-CERAMIC,CHIP;4.7nF,10%,50V,X7R,TP,2012	
NC200	2203-000979	C-CERAMIC,CHIP;47nF,10%,50V,X7R,TP,2012	
NC667	2203-000979	C-CERAMIC,CHIP;47nF,10%,50V,X7R,TP,2012	
NC115	2203-001137	C-CERAMIC,CHIP;68nF,+80-20%,50V,Y5V,TP,2012,-	
NC104	2203-001537	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,2012	
NC52L	2203-001537	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,2012	
NC52R	2203-001537	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,2012	
NC603	2203-001537	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,2012	
NC903	2203-001537	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,2012	
NC102	2203-001551	C-CERAMIC,CHIP;1.5nF,10%,50V,X7R,TP,2012	
NC201	2203-001551	C-CERAMIC,CHIP;1.5nF,10%,50V,X7R,TP,2012	
NC202	2203-001619	C-CERAMIC,CHIP;0.027nF,5%,50V,NP0,TP,2012	
NC203	2203-001619	C-CERAMIC,CHIP;0.027nF,5%,50V,NP0,TP,2012	
NL105	3301-000325	CORE-FERRITE BEAD;AB,3.2x2.5x1.3mm,-,-	
SIC1	1003-001162	IC-MOTOR DRIVER;KA3082,SIP,10PIN,25MIL,DOUBLE,	
SIC2	1003-001162	IC-MOTOR DRIVER;KA3082,SIP,10PIN,25MIL,DOUBLE,	
NXF100	2802-000211	RESONATOR-CERAMIC;16.93MHZ,0.5%,TP,10.0X5.0X10.0	
SCW5	3708-001131	CONNECTOR-FPC/FC/PIC;5P,1.25mm,STRAIGHT,SN	
WCW1	3708-001252	CONNECTOR-FPC/FC/PIC;16P,1mm,STRAIGHT-F,SN	
SCW1	3708-001438	CONNECTOR-FPC/FC/PIC;22P,1.25mm,ANGLE,SN	
NCW500	3711-000906	CONNECTOR-HEADER;BOX,3P,1R,2mm,ANGLE,SN	
SCW7	3711-003379	CONNECTOR-HEADER;NOWALL,3P,1R,2.5mm,STRAIGHT,SN	
NCW101	AH39-00060A	LEAD CONNECTOR-ASSY;-,51015-08,51004-08,8P,300MM,1007#28	
NCW102	AH39-20561P	LEAD CONNECTOR-ASSY;-,5295,PHR,6P,150mm,1007#28	
ND200	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
ND201	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
ND202	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
ND203	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
SZD1	0403-000352	DIODE-ZENER;UZ4.7BM,4.7V,4.4-5.0V,500mW,DO	
SZD2	0403-000361	DIODE-ZENER;UZ6.2BSB,6.2V,5.99-6.24V,50	
NQ1501	0501-000610	TR-SMALL SIGNAL;KSA928A-Y,PNP,1W,TO-92L,TP,160	
SR1	2001-000027	R-CARBON;100OHM,5%,1/4W,AA,TP,2.4X6.4MM	
NR106	2001-000319	R-CARBON;120KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
NR1	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
NR2	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
NR3	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
NR8	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
NR113	2001-000977	R-CARBON;8.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
NR555	2008-000140	R-FUSIBLE;2.2OHM,5%,1/2W,AA,TP,3.5X9.4MM	
NC400	2202-000243	C-CERAMIC,MLC-AXIAL;33PF,5%,50V,SL,3.5X19,-,TP	
NC300	2202-000796	C-CERAMIC,MLC-AXIAL;1nF,10%,50V,Y5P,TP,3.5x19,-	
NC106	2202-000817	C-CERAMIC,MLC-AXIAL;4.7NF,20%,16V,Y5R,TP,3.5X19,-	
NC117	2301-000389	C-FILM,PEF;150nF,5%,50V,TP,12.5x15x7.5,7m	
NC105	2401-000240	C-AL;100uF,20%,10V,GP,TP,5x11,5	
NC501	2401-000240	C-AL;100uF,20%,10V,GP,TP,5x11,5	
NC702	2401-000240	C-AL;100uF,20%,10V,GP,TP,5x11,5	
NC904	2401-000240	C-AL;100uF,20%,10V,GP,TP,5x11,5	
SC14	2401-000240	C-AL;100uF,20%,10V,GP,TP,5x11,5	
NC114	2401-000419	C-AL;10UF,20%,16V,GP,-,4X7,5	
NC301	2401-000778	C-AL;220uF,20%,10V,GP,-,6.3x11,2.5m	
NC700	2401-000778	C-AL;220uF,20%,10V,GP,-,6.3x11,2.5m	
NC701	2401-000778	C-AL;220uF,20%,10V,GP,-,6.3x11,2.5m	
SC5	2401-000795	C-AL;220UF,20%,16V,GP,-,8X11.5,3.5M	
NC703	2401-001102	C-AL;330UF,20%,16V,GP,TP,8X12,5	
NC124	2401-001324	C-AL;470nF,20%,50V,GP,BK,3x5,1mm	
NC204	2401-001324	C-AL;470nF,20%,50V,GP,BK,3x5,1mm	
NC666	2401-001895	C-AL;100uF,20%,16V,GP,6.3x11mm,2.5m	
NC122	2401-001952	C-AL;4.7UF,20%,50V,-,TP,6.3X7,5	
NC50L	2401-001952	C-AL;4.7UF,20%,50V,-,TP,6.3X7,5	
NC50R	2401-001952	C-AL;4.7UF,20%,50V,-,TP,6.3X7,5	
NC54	2401-001952	C-AL;4.7UF,20%,50V,-,TP,6.3X7,5	
NC55L	2401-001952	C-AL;4.7UF,20%,50V,-,TP,6.3X7,5	
NC55R	2401-001952	C-AL;4.7UF,20%,50V,-,TP,6.3X7,5	
NL101	2701-000111	INDUCTOR-AXIAL;100uH,10%,2.5x3.4mm	
NL102	2701-000111	INDUCTOR-AXIAL;100uH,10%,2.5x3.4mm	
NL100	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
SL1	2701-000179	INDUCTOR-AXIAL;33uH,10%,4.2x9.8mm	
NL300	3301-000297	CORE-FERRITE BEAD;AA,3.6x1.2x5.7mm,1400,2900G	
NL301	3301-000297	CORE-FERRITE BEAD;AA,3.6x1.2x5.7mm,1400,2900G	
NL302	3301-000297	CORE-FERRITE BEAD;AA,3.6x1.2x5.7mm,1400,2900G	
NIC05	AC14-12001G	IC;KA78L05,T,-	
SCO4	AC14-12001G	IC;KA78L05,T,-	
	AJ59-20150R	DECK-CDP PCB ASSY;G3A1-6NG,-,-,-	
	CMS300-R	CMS300,CD MECHA;MAXN72/73/75	
	AH81-00252A	A/S-PARTS-SPEAKER SYSTEM;SPEAKER SYSTEM,PS N73	

Location no.	Code no.	Description & Specifiation	Remarks

***** MAXN75 Parts List *****

	AH26-00062A	TRANS-POWER;E185.8X63,-,-,-,50/60HZ,SILICON STEEL SH
	AH39-00021A	LEAD-CONNECTOR ASSY;-,5264,GT201-6,6P,300MM,2547#28,2P SHIEL
	AH39-00150A	POWER-CORD;-,-,2X0.75MM,10/16A 250,1135BS,-,BLACK,2
	AH39-00202A	LEAD CONNECTOR-ASSY;-,1533#28,-,3P,200MM,-,-,5264-3P,GIL-S-3
	AH42-20001Q	ANT-LOOP;-,KS980214-01,18.5uH,CONNECTOR
	AH59-00004Q	REMOCON—ASSY;-,-,-,22KEY,MAX-N75,SAMSUNG
	AH59-20006S	DECK;ADR241FTW,-,DC12V,-,-,MAXN75,-

AH92-00245A ASSY-PCB;SMK35/45,TUNER-T S.N.A.

TR6	2007-000030	R-CHIP;560OHM,5%,1/10W,DA,TP,2012
TR101	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216
TR102	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216
TR103	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216
TR104	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216
TR19	2007-000282	R-CHIP;100KOHM,5%,1/10W,DA,TP,2012
TR45	2007-000282	R-CHIP;100KOHM,5%,1/10W,DA,TP,2012
TR47	2007-000282	R-CHIP;100KOHM,5%,1/10W,DA,TP,2012
TR49	2007-000282	R-CHIP;100KOHM,5%,1/10W,DA,TP,2012
RR2	2007-000290	R-CHIP;100OHM,5%,1/10W,DA,TP,2012
TR24	2007-000290	R-CHIP;100OHM,5%,1/10W,DA,TP,2012
TR43	2007-000290	R-CHIP;100OHM,5%,1/10W,DA,TP,2012
TR2	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012
TR21	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012
TR22	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012
TR46	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012
TR48	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012
TR50	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012
TR53	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012
TR54	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012
TR56	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012
TR10	2007-000308	R-CHIP;10OHM,5%,1/10W,DA,TP,2012
TR20	2007-000409	R-CHIP;15KOHM,5%,1/10W,DA,TP,2012
TR28	2007-000457	R-CHIP;18KOHM,5%,1/10W,DA,TP,2012
TR52	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012
TR9	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012
TR35	2007-000493	R-CHIP;2.2KOHM,5%,1/10W,DA,TP,2012
TR36	2007-000493	R-CHIP;2.2KOHM,5%,1/10W,DA,TP,2012
TR40	2007-000493	R-CHIP;2.2KOHM,5%,1/10W,DA,TP,2012
TR7	2007-000518	R-CHIP;2.7KOHM,5%,1/10W,DA,TP,2012
TR11	2007-000572	R-CHIP;220OHM,5%,1/10W,DA,TP,2012
TR105	2007-000586	R-CHIP;22KOHM,5%,1/10W,DA,TP,2012
TR15	2007-000586	R-CHIP;22KOHM,5%,1/10W,DA,TP,2012
TR37	2007-000586	R-CHIP;22KOHM,5%,1/10W,DA,TP,2012
TR12	2007-000686	R-CHIP;3.3KOHM,5%,1/10W,DA,TP,2012
TR29	2007-000686	R-CHIP;3.3KOHM,5%,1/10W,DA,TP,2012
TR23	2007-000710	R-CHIP;3.9KOHM,5%,1/10W,DA,TP,2012
TR8	2007-000822	R-CHIP;390OHM,5%,1/10W,DA,TP,2012
TR4	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012
TR51	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012
TR17	2007-000981	R-CHIP;5.6KOHM,5%,1/10W,DA,TP,2012
TR25	2007-001043	R-CHIP;56OHM,5%,1/10W,DA,TP,2012
TR27	2007-001071	R-CHIP;6.8KOHM,5%,1/10W,DA,TP,2012
TR38	2007-001177	R-CHIP;8.2KOHM,5%,1/10W,DA,TP,2012
TR44	2007-001177	R-CHIP;8.2KOHM,5%,1/10W,DA,TP,2012
TC41	2203-000239	C-CERAMIC,CHIP;0.1nF,5%,50V,NP0,TP,2012
RC2	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012
TC20	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012
TC28	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012
TC29	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012
TC3	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012
TC44	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012
TC7	2203-000429	C-CERAMIC,CHIP;0.018nF,5%,50V,NP0,TP,2012
TC1	2203-000609	C-CERAMIC,CHIP;22nF,10%,50V,X7R,TP,2012
TC5	2203-000609	C-CERAMIC,CHIP;22nF,10%,50V,X7R,TP,2012
TC99	2203-000609	C-CERAMIC,CHIP;22nF,10%,50V,X7R,TP,2012
TC33	2203-000844	C-CERAMIC,CHIP;39nF,10%,50V,X7R,TP,2012,-
RC7	2203-000979	C-CERAMIC,CHIP;47nF,10%,50V,X7R,TP,2012
TC10	2203-000979	C-CERAMIC,CHIP;47nF,10%,50V,X7R,TP,2012
TC13	2203-000979	C-CERAMIC,CHIP;47nF,10%,50V,X7R,TP,2012
TC15	2203-000979	C-CERAMIC,CHIP;47nF,10%,50V,X7R,TP,2012
TC35	2203-000979	C-CERAMIC,CHIP;47nF,10%,50V,X7R,TP,2012
TC45	2203-000979	C-CERAMIC,CHIP;47nF,10%,50V,X7R,TP,2012
TC6	2203-000979	C-CERAMIC,CHIP;47nF,10%,50V,X7R,TP,2012
RC8	2203-001058	C-CERAMIC,CHIP;0.56nF,5%,50V,NP0,TP,2012
TC61	2203-001105	C-CERAMIC,CHIP;6.8nF,10%,50V,X7R,TP,2012
TC62	2203-001105	C-CERAMIC,CHIP;6.8nF,10%,50V,X7R,TP,2012
TC32	2203-001132	C-CERAMIC,CHIP;0.68nF,5%,50V,NP0,TP,2012
TC2	2203-001517	C-CERAMIC,CHIP;0.015nF,5%,50V,NP0,TP,2012
RC4	2203-001524	C-CERAMIC,CHIP;0.047nF,5%,50V,NP0,TP,2012
RC5	2203-001524	C-CERAMIC,CHIP;0.047nF,5%,50V,NP0,TP,2012
TC63	2203-001551	C-CERAMIC,CHIP;1.5nF,10%,50V,X7R,TP,2012
TC64	2203-001551	C-CERAMIC,CHIP;1.5nF,10%,50V,X7R,TP,2012
TC50	2203-001611	C-CERAMIC,CHIP;0.022nF,5%,50V,NP0,TP,2012
TC51	2203-001611	C-CERAMIC,CHIP;0.022nF,5%,50V,NP0,TP,2012
TD3	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP
TD4	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP
TD5	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP
TD6	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP
TZD1	0403-000367	DIODE-ZENER;UZ7.5BSC,7.5V,7.33-7.64V,500mW
RZD1	0403-000393	DIODE-ZENER;UZP5.1B,5.1V,4.8-5.4V,1W,DO-41
TZD2	0403-000393	DIODE-ZENER;UZP5.1B,5.1V,4.8-5.4V,1W,DO-41
TQ4	0501-000294	TR-SMALL SIGNAL;KSA708-Y,PNP,800mW,TO-92,TP,12
TQ2	0501-000392	TR-SMALL SIGNAL;KSC838-O,NPN,250mW,TO-92,-,70-
TQ3	0501-000392	TR-SMALL SIGNAL;KSC838-O,NPN,250mW,TO-92,-,70-
TQ1	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,TP,120-
TQ5	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,TP,120-
TQ6	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,TP,120-
TQ7	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,TP,120-
TR30	2001-000117	R-CARBON(S);68OHM,5%,1/2W,AA,TP,2.4X6.4MM
RR1A	2001-000118	R-CARBON(S);180ohm,5%,1/2W,AA,TP,2.4x6.4mm
TR44	2001-000118	R-CARBON(S);180ohm,5%,1/2W,AA,TP,2.4x6.4mm
TR58	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2MM
TR5	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM
-	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM
TR39	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM
TR1	2001-000331	R-CARBON;12KOHM,5%,1/8W,AA,TP,1.8X3.2MM
RR3	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM
RR4	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM
RR5	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM
TR32	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM
TR34	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM
TR55	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM
TR18	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM
TR3	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM
TR13	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM
TR40	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM
TR61	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM
TR62	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM
TR42	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM
TR16	2001-000745	R-CARBON;4.7OHM,5%,1/8W,AA,TP,1.8X3.2MM
TR41	2001-000802	R-CARBON;5.6Kohm,5%,1/8W,AA,TP,1.8x3.2m
TR57	2001-000802	R-CARBON;5.6Kohm,5%,1/8W,AA,TP,1.8x3.2m
TSR1	2103-000290	VR-SEMI;20Kohm,30%,1/10W,TOP
TC14	2201-000565	C-CERAMIC,DISC;47nF,20%,50V,Y5V,12.5x4.0mm,5mm,TP
TC39	2201-000565	C-CERAMIC,DISC;47nF,20%,50V,Y5V,12.5x4.0mm,5mm,TP
RC9	2202-000796	C-CERAMIC,MLC-AXIAL;1nF,10%,50V,Y5P,TP,3.5x19,-
TC40	2202-000796	C-CERAMIC,MLC-AXIAL;1nF,10%,50V,Y5P,TP,3.5x19,-
TC42	2202-000796	C-CERAMIC,MLC-AXIAL;1nF,10%,50V,Y5P,TP,3.5x19,-
TC48	2202-000807	C-CERAMIC,MLC-AXIAL;22NF,+80-20%,25V,Y5V,TP,3.5X19
TC21	2401-000240	C-AL;100uF,20%,10V,GP,TP,5x11,5
TC46	2401-000240	C-AL;100uF,20%,10V,GP,TP,5x11,5
TC12	2401-000419	C-AL;10UF,20%,16V,GP,-,4X7,5
TC26	2401-000419	C-AL;10UF,20%,16V,GP,-,4X7,5
TC27	2401-000419	C-AL;10UF,20%,16V,GP,-,4X7,5
TC30	2401-000419	C-AL;10UF,20%,16V,GP,-,4X7,5
RC1	2401-000907	C-AL;22UF,20%,16V,GP,-,5X11,2MM
TC34	2401-000907	C-AL;22UF,20%,16V,GP,-,5X11,2MM
TC37	2401-001022	C-AL;3.3UF,20%,50V,GP,-,5X11,2MM
TC38	2401-001164	C-AL;33UF,20%,16V,GP,-,5X11,2MM
TC47	2401-001895	C-AL;100uF,20%,16V,GP,6.3x11mm,2.5m
TC11	2401-001912	C-AL;1uF,20%,50V,GP,5x11mm,2mm,BK
TC17	2401-001912	C-AL;1uF,20%,50V,GP,5x11mm,2mm,BK
TC19	2401-001912	C-AL;1uF,20%,50V,GP,5x11mm,2mm,BK
TC16	2401-001954	C-AL;4.7UF,20%,50V,GP,TP,5X11MM,5
TC23	2401-001954	C-AL;4.7UF,20%,50V,GP,TP,5X11MM,5
TC25	2401-001954	C-AL;4.7UF,20%,50V,GP,TP,5X11MM,5
TC18	2401-001968	C-AL;470NF,20%,50V,GP,TP,5X11MM,5
TC43	2401-001968	C-AL;470NF,20%,50V,GP,TP,5X11MM,5
TC4	2401-001975	C-AL;47UF,20%,16V,GP,TP,5X11MM,5
TC9	2401-001975	C-AL;47UF,20%,16V,GP,TP,5X11MM,5
RC6	2401-002180	C-AL;2.2UF,20%,50V,GP,TP,5X11,5MM
RIC1	AH14-10008E	IC;BU1923F,SOP,+5V
VVC1	0405-000137	DIODE-VARACTOR;KV-1260,20V,100NA,T0-92S
TFL4	14529-304-610	FILTER CERAMIC;AHCM2-450BL
	2202-000263	C-CERAMIC,MLC-AXIAL;470pF,10%,50V,Y5P,TP,3.5x19,-
TX1	2801-000734	CRYSTAL-UNIT;7.2MHZ,50PPM,28-AAM,12PF,30OHM
RX1	2801-003601	CRYSTAL-UNIT;4.332MHz,30ppm,28-AAM,30pF,
TFL2	2903-000105	FILTER-CERAMIC;BP,10.7MHZ+-25KHZ,180KHZ+-50KH
TFL1	2903-000119	FILTER-CERAMIC;SFE10.7MJA-10-A
TWA1	3710-001421	CONNECTOR-SOCKET;14P,1R,2mm,ANGLE,SN
TJ2	3711-000814	CONNECTOR-HEADER;BOX,2P,1R,2.5mm,ANGLE,SN
TJ1	3716-000210	TERMINAL-BLOCK;-,-,-,60V,7A
HIC1	AH14-10007G	IC;LC72131,DIP,STICK PLL
TIC1	AH14-10008B	IC;LA1837,DIP,RF+MPX
TLPF1	AH26-00005A	TRANS-IF;-,LKS75M00-X000264-0,LOW PASS FILTER,-,7
TLPF2	AH26-00005A	TRANS-IF;-,LKS75M00-X000264-0,LOW PASS FILTER,-,7
TL2	AH26-10001E	TRANS-IF;KS940228-09,-,-,7.6X12.0,-,450KHZ,BULK,
TL3	AH26-10020A	TRANS-DET;-,7KLL,DET,-,7.8MM,91PF,11.32M
LW	AH27-00007A	COIL-OSC;LKS7FB00-0060BLO-0,-,LW OSC
OSC	AH27-00007A	COIL-OSC;LKS7FB00-0060BLO-0,-,LW OSC
MW	AH27-00008A	COIL-OSC;LKS75M00-0060LMO-0,-,MW OSC
OSC	AH27-00008A	COIL-OSC;LKS75M00-0060LMO-0,-,MW OSC
ANT	AH27-00011A	COIL-OSC;LKS75M00-X000262-0,-,LW ANT
LW	AH27-00011A	COIL-OSC;LKS75M00-X000262-0,-,LW ANT
ANT	AH27-00012A	COIL-OSC;LKS75M00-X000263-0,365UH,MW ANT
MW	AH27-00012A	COIL-OSC;LKS75M00-X000263-0,365UH,MW ANT
FM	AH40-10025S	TUNER-FM;KST-F404VA-1,4G,75ohm
PACK	AH40-10025S	TUNER-FM;KST-F404VA-1,4G,75ohm
FREE	AH61-20540A	HOLDER-TUNER;-,ABS,94HB,BLK,-,MAX940
	AH65-30010A	CLAMP-WIRE;DALB-2,-,-,-

AH92-00564A ASSY PCB;MAX-N75,MAIN S.N.A.

AD1	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP

Location no.	Code no.	Description & Specifiation	Remarks
AD10	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
AD2	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
AD4	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
AD7	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
AD8	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
AD9	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
CD1A	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
CD3	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
CD4	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
CD5	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
CD6	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
FD1	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
FD2	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
FD3	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
HD1	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
HD2	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
HD5	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
JD1	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
JD1A	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
JD2	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
JD2L	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
JD2R	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
JD3	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
JD4	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
LD1	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
RD4	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
RD6	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
HD3	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
HD4	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
RD1	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
RD2	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
RD3	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
RD5	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
RD9	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
RD7	0402-000151	DIODE-RECTIFIER;1N5392,100V,1.5A,DO-15,TP	
CZD1	0403-000354	DIODE-ZENER;UZ5.1B,5.1V,4.8-5.4V,500mW,DO-	
FZD3	0403-000354	DIODE-ZENER;UZ5.1B,5.1V,4.8-5.4V,500mW,DO-	
RZD4	0403-000354	DIODE-ZENER;UZ5.1B,5.1V,4.8-5.4V,500mW,DO-	
FZD1	0403-000363	DIODE-ZENER;UZ6.8BH,6.8V,6.8-7.2V,500mW,DO	
FZD2	0403-000363	DIODE-ZENER;UZ6.8BH,6.8V,6.8-7.2V,500mW,DO	
AZD1	0403-000369	DIODE-ZENER;UZ8.2BM,8.2V,7.9-8.5V,500MW	
AZD2	0403-000369	DIODE-ZENER;UZ8.2BM,8.2V,7.9-8.5V,500MW	
RZD3	0403-000379	DIODE-ZENER;UZP12B,12V,11.4-12.6V,1W,DO-41	
RZD7	0403-000379	DIODE-ZENER;UZP12B,12V,11.4-12.6V,1W,DO-41	
RZD8	0403-000380	DIODE-ZENER;UZP13B,13V,12.4-14.1V,1W,DO-41	
RZD5	0403-000396	DIODE-ZENER;UZP6.8B,6.8V,6.4-7.2V,1W,DO-41	
RZD1	0403-000570	DIODE-ZENER;UZP18B,18V,16.9-19.1V,1W,DO-41	
RZD2	0403-000570	DIODE-ZENER;UZP18B,18V,16.9-19.1V,1W,DO-41	
LQ3	0501-000010	TR-SMALL SIGNAL;KSC1008,NPN,800mW,TO-92,TP,120	
AQ9	0501-000294	TR-SMALL SIGNAL;KSA708-Y,PNP,800mW,TO-92,TP,12	
RQ4	0501-000294	TR-SMALL SIGNAL;KSA708-Y,PNP,800mW,TO-92,TP,12	
JQ8A	0501-000303	TR-SMALL SIGNAL;KSA733,PNP,250mW,TO-92,TP,120-	
LQ1	0501-000369	TR-SMALL SIGNAL;KSC2331-Y,NPN,1W,TO-92L,-,120-	
LQ2	0501-000369	TR-SMALL SIGNAL;KSC2331-Y,NPN,1W,TO-92L,-,120-	
AQ1L	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,TP,120-	
AQ1R	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,TP,120-	
AQ2L	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,TP,120-	
AQ2R	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,TP,120-	
CQ10	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,TP,120-	
CQ4	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,TP,120-	
CQ5	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,TP,120-	
CQ9	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,TP,120-	
FQ1L	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,TP,120-	
FQ1R	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,TP,120-	
JQ5	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,TP,120-	
JQ6	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,TP,120-	
JQ7	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,TP,120-	
RQ3	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,TP,120-	
AQ10	0501-000407	TR-SMALL SIGNAL;KSD471A-Y,NPN,800mW,TO-92,-,12	
HQ1L	0501-000407	TR-SMALL SIGNAL;KSD471A-Y,NPN,800mW,TO-92,-,12	
HQ1R	0501-000407	TR-SMALL SIGNAL;KSD471A-Y,NPN,800mW,TO-92,-,12	
JQ2L	0501-000407	TR-SMALL SIGNAL;KSD471A-Y,NPN,800mW,TO-92,-,12	
JQ2R	0501-000407	TR-SMALL SIGNAL;KSD471A-Y,NPN,800mW,TO-92,-,12	
CQ3	0501-000610	TR-SMALL SIGNAL;KSA928A-Y,PNP,1W,TO-92L,TP,160	
CQ6	0501-000610	TR-SMALL SIGNAL;KSA928A-Y,PNP,1W,TO-92L,TP,160	
CQ7	0501-000610	TR-SMALL SIGNAL;KSA928A-Y,PNP,1W,TO-92L,TP,160	
RQ1	0501-000610	TR-SMALL SIGNAL;KSA928A-Y,PNP,1W,TO-92L,TP,160	
AQ4	0504-000118	TR-DIGITAL;KSR1003,NPN,300MW,22K/22K,TO-92,TP	
CQ8	0504-000118	TR-DIGITAL;KSR1003,NPN,300MW,22K/22K,TO-92,TP	
JQ1	0504-000118	TR-DIGITAL;KSR1003,NPN,300MW,22K/22K,TO-92,TP	
JQ4	0504-000118	TR-DIGITAL;KSR1003,NPN,300MW,22K/22K,TO-92,TP	
JQ7L	0504-000118	TR-DIGITAL;KSR1003,NPN,300MW,22K/22K,TO-92,TP	
JQ7R	0504-000118	TR-DIGITAL;KSR1003,NPN,300MW,22K/22K,TO-92,TP	
JQ8	0504-000118	TR-DIGITAL;KSR1003,NPN,300MW,22K/22K,TO-92,TP	
AQ1	0504-001003	TR-DIGITAL;KSR2003,PNP,300MW,22K/22K,TO-92,TP	
CQ1	0504-001003	TR-DIGITAL;KSR2003,PNP,300MW,22K/22K,TO-92,TP	
CQ2	0504-001003	TR-DIGITAL;KSR2003,PNP,300MW,22K/22K,TO-92,TP	
FQ1	0504-001003	TR-DIGITAL;KSR2003,PNP,300MW,22K/22K,TO-92,TP	
JQ2	0504-001003	TR-DIGITAL;KSR2003,PNP,300MW,22K/22K,TO-92,TP	
JQ3	0504-001003	TR-DIGITAL;KSR2003,PNP,300MW,22K/22K,TO-92,TP	
JQ1L	0505-000197	FET-SILICON;2SK373Y,N,-,-,-,400MW,TO-92	
JQ1R	0505-000197	FET-SILICON;2SK373Y,N,-,-,-,400MW,TO-92	
JR13	2001-000005	R-CARBON;390ohm,5%,1/8W,AA,TP,1.8x3.2mm	

Location no.	Code no.	Description & Specifiation	Remarks
JR11R	2001-000008	R-CARBON;15KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
HR1	2001-000028	R-CARBON(S);100OHM,5%,1/2W,AA,TP,2.4X6.4MM	
HR2	2001-000028	R-CARBON(S);100OHM,5%,1/2W,AA,TP,2.4X6.4MM	
CR1	2001-000034	R-CARBON;220OHM,5%,1/4W,AA,TP,2.4X6.4MM	
FR12	2001-000034	R-CARBON;220OHM,5%,1/4W,AA,TP,2.4X6.4MM	
AR11	2001-000052	R-CARBON(S);3.3KOHM,5%,1/2W,AA,TP,2.4X6.4MM	
AR12	2001-000052	R-CARBON(S);3.3KOHM,5%,1/2W,AA,TP,2.4X6.4MM	
RR9	2001-000055	R-CARBON;4.7Kohm,5%,1/4W,AA,TP,2.4x6.4m	
LR1	2001-000109	R-CARBON(S);470OHM,5%,1/2W,AA,TP,2.4X6.4MM	
FR4R	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
FR12L	2001-000258	R-CARBON;1.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
FR10L	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
FR10R	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
BR1	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
DR3	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
AR10A	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CR12	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CR2	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CR21	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CR25	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CR27	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CR28	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CR29	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CR3	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CR30	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CR31	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CR34	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CR36	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CR4	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CR5	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CR9	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
DR3L	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
FR1L	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
FR3	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
FR7	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
HR4	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
JR11	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
JR8L	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
HR5L	2001-000302	R-CARBON;10OHM,5%,1/8W,AA,TP,1.8X3.2MM	
HR5R	2001-000302	R-CARBON;10OHM,5%,1/8W,AA,TP,1.8X3.2MM	
JR10L	2001-000411	R-CARBON;18KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
JR10R	2001-000411	R-CARBON;18KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
AR4R	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CR26	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
RR17	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
RR7	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
AR24	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CR24	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
FR8L	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
HR5	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
HR9L	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
HR9R	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
AR19	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
FR1	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
FR13L	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
FR7	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
JW48	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
RR14	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
RR10	2001-000563	R-CARBON;27KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
AR3R	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
AR5R	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
HR1R	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
RR11	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
RR5	2001-000613	R-CARBON;3.9KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
AR10	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
AR1L	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
BR1R	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CR14	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CR16	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CR18	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CR19	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CR20	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
DR4	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
DR5	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
HR3	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
JR12	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
JR13L	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
JW99	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
LR4	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
RR12	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
RR15	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
JR1	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
AR8	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
AR9	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
BR3L	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
BR3R	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
FR11L	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
FR11R	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
JR14	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
DR2L	2001-000802	R-CARBON;5.6Kohm,5%,1/8W,AA,TP,1.8x3.2m	
JR1L	2001-000802	R-CARBON;5.6Kohm,5%,1/8W,AA,TP,1.8x3.2m	
RR18	2001-000890	R-CARBON;6.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
FR6L	2001-000977	R-CARBON;8.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	

Location no.	Code no.	Description & Specifiation	Remarks
FR4	2001-001077	R-CARBON(S);150ohm,5%,1/2W,AA,TP,2.4x6.4mm	
FR8	2001-001077	R-CARBON(S);150ohm,5%,1/2W,AA,TP,2.4x6.4mm	
RR13	2001-001077	R-CARBON(S);150ohm,5%,1/2W,AA,TP,2.4x6.4mm	
LR3	2001-001096	R-CARBON(S);2.2OHM,5%,1/2W,AA,TP,2.4X6.4MM	
LR6	2001-001138	R-CARBON(S);390ohm,5%,1/2W,AA,TP,2.4x6.4mm	
RR16	2001-001138	R-CARBON(S);390ohm,5%,1/2W,AA,TP,2.4x6.4mm	
RR3	2001-001153	R-CARBON(S);47ohm,5%,1/2W,AA,TP,2.4x6.4mm	
RR4	2001-001153	R-CARBON(S);47ohm,5%,1/2W,AA,TP,2.4x6.4mm	
CR15	2001-001178	R-CARBON(S);680OHM,5%,1/2W,AA,TP,2.4X6.4MM	
CR17	2001-001178	R-CARBON(S);680OHM,5%,1/2W,AA,TP,2.4X6.4MM	
CR22	2001-001178	R-CARBON(S);680OHM,5%,1/2W,AA,TP,2.4X6.4MM	
RR30	2001-001192	R-CARBON(S);820OHM,5%,1/2W,AA,TP,2.4X6.4MM	
AR13	2003-000008	R-METAL OXIDE(S);100ohm,5%,1W,AA,TP,3.3x9mm	
AR15	2003-000008	R-METAL OXIDE(S);100ohm,5%,1W,AA,TP,3.3x9mm	
JSR2L	2103-000122	VR-SEMI;100Kohm,30%,1/10W,TOP	
JSR2R	2103-000122	VR-SEMI;100Kohm,30%,1/10W,TOP	
JSR3L	2103-000122	VR-SEMI;100Kohm,30%,1/10W,TOP	
JSR3R	2103-000122	VR-SEMI;100Kohm,30%,1/10W,TOP	
JSR1L	2103-000248	VR-SEMI;200KOHM,30%,1/10W,TOP	
JSR1R	2103-000248	VR-SEMI;200KOHM,30%,1/10W,TOP	
CVR1	2103-000341	VR-SEMI;2Kohm,30%,1/10W,TOP	
CVR2	2103-000341	VR-SEMI;2Kohm,30%,1/10W,TOP	
RC11	2201-000161	C-CERAMIC,DISC;10nF,+80-20%,500V,Y5V,TP,13.5x	
RC12	2201-000161	C-CERAMIC,DISC;10nF,+80-20%,500V,Y5V,TP,13.5x	
JC3L	2201-000368	C-CERAMIC,DISC;220PF,10%,50V,SL,TP,6.5X3.0,5	
JC3R	2201-000368	C-CERAMIC,DISC;220PF,10%,50V,SL,TP,6.5X3.0,5	
CC2	2201-000470	C-CERAMIC,DISC;330pF,10%,50V,SL,TP,6.5x3,5	
AC5L	2201-000565	C-CERAMIC,DISC;47nF,20%,50V,Y5V,12.5x4.0mm,5mm,TP	
AC5R	2201-000565	C-CERAMIC,DISC;47nF,20%,50V,Y5V,12.5x4.0mm,5mm,TP	
AC7L	2201-000565	C-CERAMIC,DISC;47nF,20%,50V,Y5V,12.5x4.0mm,5mm,TP	
AC7R	2201-000565	C-CERAMIC,DISC;47nF,20%,50V,Y5V,12.5x4.0mm,5mm,TP	
JC2L	2202-000796	C-CERAMIC,MLC-AXIAL;1nF,10%,50V,Y5P,TP,3.5x19,-	
JC1LA	2202-000820	C-CERAMIC,MLC-AXIAL;5.6NF,20%,16V,Y5R,TP,3.5X19,-	
JC1RA	2202-000820	C-CERAMIC,MLC-AXIAL;5.6NF,20%,16V,Y5R,TP,3.5X19,-	
AC6L	2301-000375	C-FILM,PEF;100nF,5%,50V,TP,11x12.5x6.5,7m	
AC6R	2301-000375	C-FILM,PEF;100nF,5%,50V,TP,11x12.5x6.5,7m	
FC6	2301-000375	C-FILM,PEF;100nF,5%,50V,TP,11x12.5x6.5,7m	
LC4	2301-000404	C-FILM,PEF;2.2NF,10%,50V,TP,5.5X7X3.2MM,5	
LC1	2301-000407	C-FILM,PEF;2.7NF,10%,50V,TP,5.5X7X3MM,5MM	
AC2	2301-000412	C-FILM,PEF;22NF,10%,50V,TP,6.5X10.5X4MM,5	
JC6L	2301-000419	C-FILM,PEF;27nF,10%,50V,TP,7.5x10.5x4mm,5	
JC6R	2301-000419	C-FILM,PEF;27nF,10%,50V,TP,7.5x10.5x4mm,5	
DC6L	2301-000422	C-FILM,PEF;3.3NF,10%,50V,TP,5.5X7X3MM,5MM	
DC6R	2301-000422	C-FILM,PEF;3.3NF,10%,50V,TP,5.5X7X3MM,5MM	
FC10	2301-000449	C-FILM,PEF;47NF,10%,50V,TP,8X11X4.5MM,5MM	
LC5	2301-000456	C-FILM,PEF;56NF,10%,50V,TP,8X12X4.5MM,5MM	
CC1	2401-000240	C-AL;100uF,20%,10V,GP,TP,5x11,5	
RC15	2401-000357	C-AL;100UF,20%,50V,GP,-,8X11.5,3.5M	
AC12	2401-000385	C-AL;10uF,20%,100V,GP,TP,6.3x11,5	
AC9	2401-000385	C-AL;10uF,20%,100V,GP,TP,6.3x11,5	
BC1L	2401-000419	C-AL;10UF,20%,16V,GP,-,4X7,5	
BC1R	2401-000419	C-AL;10UF,20%,16V,GP,-,4X7,5	
BC2	2401-000419	C-AL;10UF,20%,16V,GP,-,4X7,5	
BC3L	2401-000419	C-AL;10UF,20%,16V,GP,-,4X7,5	
BC3R	2401-000419	C-AL;10UF,20%,16V,GP,-,4X7,5	
JC1L	2401-000419	C-AL;10UF,20%,16V,GP,-,4X7,5	
JC1R	2401-000419	C-AL;10UF,20%,16V,GP,-,4X7,5	
JC4	2401-000419	C-AL;10UF,20%,16V,GP,-,4X7,5	
JC6	2401-000419	C-AL;10UF,20%,16V,GP,-,4X7,5	
CC1A	2401-000438	C-AL;10uF,20%,25V,GP,-,5x11,2mm	
CD6	2401-000438	C-AL;10uF,20%,25V,GP,-,5x11,2mm	
AC10	2401-000475	C-AL;10UF,20%,50V,GP,-,5X11,2MM	
AC11	2401-000475	C-AL;10UF,20%,50V,GP,-,5X11,2MM	
FC12L	2401-000475	C-AL;10UF,20%,50V,GP,-,5X11,2MM	
FC12R	2401-000475	C-AL;10UF,20%,50V,GP,-,5X11,2MM	
FC14L	2401-000475	C-AL;10UF,20%,50V,GP,-,5X11,2MM	
FC14R	2401-000475	C-AL;10UF,20%,50V,GP,-,5X11,2MM	
FC17L	2401-000475	C-AL;10UF,20%,50V,GP,-,5X11,2MM	
FC17R	2401-000475	C-AL;10UF,20%,50V,GP,-,5X11,2MM	
RC8	2401-000475	C-AL;10UF,20%,50V,GP,-,5X11,2MM	
FC3	2401-000778	C-AL;220uF,20%,10V,GP,-,6.3x11,2.5m	
FC8	2401-000778	C-AL;220uF,20%,10V,GP,-,6.3x11,2.5m	
JC5	2401-000778	C-AL;220uF,20%,10V,GP,-,6.3x11,2.5m	
HC1	2401-000795	C-AL;220UF,20%,16V,GP,-,8X11.5,3.5M	
HC2	2401-000795	C-AL;220UF,20%,16V,GP,-,8X11.5,3.5M	
RC16	2401-000795	C-AL;220UF,20%,16V,GP,-,8X11.5,3.5M	
FC2	2401-000970	C-AL;22uF,20%,50V,WT,TP,5x11,5	
AC1	2401-001465	C-AL;47UF,20%,10V,GP,-,5X11,2MM	
BC2L	2401-001465	C-AL;47UF,20%,10V,GP,-,5X11,2MM	
BC2R	2401-001465	C-AL;47UF,20%,10V,GP,-,5X11,2MM	
FC12	2401-001465	C-AL;47UF,20%,10V,GP,-,5X11,2MM	
JC3	2401-001465	C-AL;47UF,20%,10V,GP,-,5X11,2MM	
RC30	2401-001572	C-AL;47UF,20%,50V,GP,-,6.3X11,2.5MM	
DC2L	2401-001645	C-AL;680nF,20%,50V,GP,-,5x11,2mm	
DC2R	2401-001645	C-AL;680nF,20%,50V,GP,-,5x11,2mm	
-	2401-001895	C-AL;100uF,20%,16V,GP,6.3x11mm,2.5m	
DC1	2401-001895	C-AL;100uF,20%,16V,GP,6.3x11mm,2.5m	
DC1L	2401-001912	C-AL;1uF,20%,50V,GP,5x11mm,2mm,BK	
DC1R	2401-001912	C-AL;1uF,20%,50V,GP,5x11mm,2mm,BK	
DC3L	2401-001912	C-AL;1uF,20%,50V,GP,5x11mm,2mm,BK	
DC3R	2401-001912	C-AL;1uF,20%,50V,GP,5x11mm,2mm,BK	
DC4L	2401-001912	C-AL;1uF,20%,50V,GP,5x11mm,2mm,BK	
DC4R	2401-001912	C-AL;1uF,20%,50V,GP,5x11mm,2mm,BK	

Location no.	Code no.	Description & Specifiation	Remarks
DC5L	2401-001912	C-AL;1uF,20%,50V,GP,5x11mm,2mm,BK	
DC5R	2401-001912	C-AL;1uF,20%,50V,GP,5x11mm,2mm,BK	
JC7L	2401-001912	C-AL;1uF,20%,50V,GP,5x11mm,2mm,BK	
JC7R	2401-001912	C-AL;1uF,20%,50V,GP,5x11mm,2mm,BK	
JC8L	2401-001912	C-AL;1uF,20%,50V,GP,5x11mm,2mm,BK	
JC8R	2401-001912	C-AL;1uF,20%,50V,GP,5x11mm,2mm,BK	
RC7	2401-001912	C-AL;1uF,20%,50V,GP,5x11mm,2mm,BK	
RC6	2401-001938	C-AL;22UF,20%,25V,GP,BK,5X11MM,2MM	
AC2L	2401-001954	C-AL;4.7UF,20%,50V,GP,TP,5X11MM,5	
AC2R	2401-001954	C-AL;4.7UF,20%,50V,GP,TP,5X11MM,5	
FC18	2401-001954	C-AL;4.7UF,20%,50V,GP,TP,5X11MM,5	
FC18L	2401-001954	C-AL;4.7UF,20%,50V,GP,TP,5X11MM,5	
FC18R	2401-001954	C-AL;4.7UF,20%,50V,GP,TP,5X11MM,5	
FC19L	2401-001954	C-AL;4.7UF,20%,50V,GP,TP,5X11MM,5	
FC19R	2401-001954	C-AL;4.7UF,20%,50V,GP,TP,5X11MM,5	
FC2L	2401-001954	C-AL;4.7UF,20%,50V,GP,TP,5X11MM,5	
FC2R	2401-001954	C-AL;4.7UF,20%,50V,GP,TP,5X11MM,5	
HC3	2401-001954	C-AL;4.7UF,20%,50V,GP,TP,5X11MM,5	
RC5	2401-001954	C-AL;4.7UF,20%,50V,GP,TP,5X11MM,5	
AC4	2401-001975	C-AL;47UF,20%,16V,GP,TP,5X11MM,5	
BC1	2401-001975	C-AL;47UF,20%,16V,GP,TP,5X11MM,5	
DC2	2401-001975	C-AL;47UF,20%,16V,GP,TP,5X11MM,5	
HC2L	2401-001975	C-AL;47UF,20%,16V,GP,TP,5X11MM,5	
HC2R	2401-001975	C-AL;47UF,20%,16V,GP,TP,5X11MM,5	
JC1	2401-001975	C-AL;47UF,20%,16V,GP,TP,5X11MM,5	
LC6	2401-001975	C-AL;47UF,20%,16V,GP,TP,5X11MM,5	
FC20	2401-002180	C-AL;2.2UF,20%,50V,GP,TP,5X11,5MM	
HC1L	2401-002180	C-AL;2.2UF,20%,50V,GP,TP,5X11,5MM	
HC1R	2401-002180	C-AL;2.2UF,20%,50V,GP,TP,5X11,5MM	
RL3	2701-000178	INDUCTOR-AXIAL;33uH,10%,3x7mm	
JW151	2701-000179	INDUCTOR-AXIAL;33uH,10%,4.2x9.8mm	
LL2	2701-000298	INDUCTOR-AXIAL;470uH,10%,4.2x9.8mm	
RL1	2701-000298	INDUCTOR-AXIAL;470uH,10%,4.2x9.8mm	
RL2	2701-000298	INDUCTOR-AXIAL;470uH,10%,4.2x9.8mm	
FBD1	3301-000297	CORE-FERRITE BEAD;AA,3.6x1.2x5.7mm,1400,2900G	
-	3602-000147	FUSE-CLIP;250V,7.5A,30MOHM	
RF1*2	3602-000147	FUSE-CLIP;250V,7.5A,30MOHM	
RBD1	0402-001258	DIODE-BRIDGE;GBU606,600V,6A,SIP-4,BK	
RBD2	0402-001259	DIODE-BRIDGE;GBU806,600V,8A,SIP-4,BK	
M1	0503-001014	TR-DARLINGTON;2SD2495-P,NPN,30W,TO-220F,BK,6500-20000	
CIC1	0904-001316	IC-I/O CONTROLLER;M66010,24BIT,SOP,32P,200MIL,1.	
FIC3	1201-000163	IC-OP AMP;4560,SOP,8P,173MIL,DUAL,100V/mV,PLASTIC,	
HIC1	1201-000163	IC-OP AMP;4560,SOP,8P,173MIL,DUAL,100V/mV,PLASTIC,	
AIC1	1201-001397	IC-POWER AMP;499-240E,SIP,22P,78,SINGLE,40d	
RIC1	1203-001653	IC-VOLTAGE REGULATOR;4959,MULTIWATT,15P,700MIL,PLAS	
DIC1	1204-000134	IC-DNR PROCESSOR;KA2271B,DIP,16P,-,PLASTIC,16V,	
FIC2	1204-000156	IC-EQUALIZER;BA3834S,DIP,18P,-,PLASTIC,7V,-	
JIC1	1204-001471	IC-EQUALIZER;HA12211NT,DIP,30P,-,PLASTIC,15	
BIC1	1204-001474	IC-EQUALIZER;KA22241,SIP,9,-,PLASTIC,16,550	
FIC1	1204-001652	IC-SOUND PROCESSOR;M62433FP,QFP,80P,-,PLASTIC,7V,1370mW,-20	
RR8	2003-000455	R-METAL OXIDE(S);100ohm,5%,2W,AA,TP,4x12mm	
AR10L	2003-000471	R-METAL OXIDE(S);10ohm,5%,2W,AA,TP,4x12mm	
AR10R	2003-000471	R-METAL OXIDE(S);10ohm,5%,2W,AA,TP,4x12mm	
RR1	2003-000650	R-METAL OXIDE(S);330ohm,5%,2W,AA,TP,4x12mm	
PC1	2201-000546	C-CERAMIC,DISC;4.7NF,20%,400V,Y5U,BK,16X7,10	
PC2	2201-000546	C-CERAMIC,DISC;4.7NF,20%,400V,Y5U,BK,16X7,10	
AC7	2401-000230	C-AL;100uF,20%,100V,GP,TP,12.5x20,5	
AC8	2401-000230	C-AL;100uF,20%,100V,GP,TP,12.5x20,5	
RC13	2401-000230	C-AL;100uF,20%,100V,GP,TP,12.5x20,5	
RC1	2401-001942	C-AL;3300uF,20%,35V,GP,BK,18x35.5mm	
RC2	2401-003116	C-AL;4700uF,20%,35V,-,BK,18X35.5,7.	
RC3	2401-003383	C-AL;3300uF,20%,100V,GP,BK,25.4x50,	
RC4	2401-003383	C-AL;3300uF,20%,100V,GP,BK,25.4x50,	
DLPF1L	2909-000210	FILTER-LC;-,-,1dB,TP,30dB/19KHz,50dB/105KHz	
DLPF1R	2909-000210	FILTER-LC;-,-,1dB,TP,30dB/19KHz,50dB/105KHz	
RF2	3601-000282	FUSE;250V,4A,TIME-LAG,GLASS,5.2x20mm	
CW1	3708-000181	CONNECTOR-FPC/FC/PIC;16P,1.25mm,STRAIGHT,SN	
MW1	3708-000258	CONNECTOR-FPC/FC/PIC;30P,1.25mm,STRAIGHT,SN	
AW2	3711-000820	CONNECTOR-HEADER;BOX,2P,1R,2.5mm,STRAIGHT,SN	
JCW2	3711-000907	CONNECTOR-HEADER;BOX,3P,1R,2mm,STRAIGHT,SN	
CCW1	3711-002809	CONNECTOR-HEADER;BOX,8P,1R,2mm,STRAIGHT,SN	
JCW3	3711-003107	CONNECTOR-HEADER;BOX,3P,1R,2.5mm,STRAIGHT,SN	
JCW1	3711-003111	CONNECTOR-HEADER;BOX,6P,1R,2.5mm,-,BRAS	
RCW1	3711-003112	CONNECTOR-HEADER;BOX,8P,1R,2.5MM,STRAIGHT,SN	
TCW1	3711-004109	CONNECTOR-HEADER;3WALL,14P,1R,2mm,STRAIGHT,SN	
SPK	3716-000209	TERMINAL-BLOCK;,-,-,60V,7A	
H1	3722-000363	JACK-PHONE;9P,6.4MM,AU,BLK,-	
AUX	3722-000377	JACK-RCA;4P/2C,3.5MM,SN,BLK,#16~22	
JLF1L	AH26-10002X	COIL-TRAP;KS940830-05,BIAS-TRAP,30DB,7.6,51PF,105K	
JLF1R	AH26-10002X	COIL-TRAP;KS940830-05,BIAS-TRAP,30DB,7.6,51PF,105K	
LL1	AH26-10003C	COIL-TRAP;PCHNS-5371EQJ,BIAS-TRAP,-,-,850PF,105KHZ	
PL1	AH27-10001F	COIL-CHOKE;27UH,K,Q30,-,-,DR(6.5*7.5),-,-,	
PL2	AH27-10001F	COIL-CHOKE;27UH,K,Q30,-,-,DR(6.5*7.5),-,-,	
AL1L	AH27-90001A	COIL-SPRING;,2.2UH,-,-,SPRING	
AL1R	AH27-90001A	COIL-SPRING;,2.2UH,-,-,SPRING	
AL2L	AH27-90001A	COIL-SPRING;,2.2UH,-,-,SPRING	
AL2R	AH27-90001A	COIL-SPRING;,2.2UH,-,-,SPRING	
FAN	AH31-12006A	MOTOR-DC-FAN;D0825A-12M,12V DC/0.17A,-	
PJ1	AH37-22001N	JACK-CONNECTOR;10MM,YFW800-02,2P,BULK,-	
RW2	AH39-00196A	LEAD CONNECTOR-ASSY;-,-,-,-,1007#26,100MM,BK/WH,BK,5051-3P,5	
RW1	AH39-20560P	LEAD CONNECTOR-ASSY;-,5264,51088,8p,300m	
FR3L	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
FR3R	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	

Location no.	Code no.	Description & Specifiation	Remarks
JW149	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
FR18L	2007-000030	R-CHIP;560OHM,5%,1/10W,DA,TP,2012	
FR18R	2007-000030	R-CHIP;560OHM,5%,1/10W,DA,TP,2012	
JR4	2007-000032	R-CHIP;390KOHM,5%,1/10W,DA,TP,2012	
JW113	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
JW1A	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
JW2A	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
JW3A	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
AR8L	2007-000221	R-CHIP;1.2KOHM,5%,1/10W,DA,TP,2012	
AR8R	2007-000221	R-CHIP;1.2KOHM,5%,1/10W,DA,TP,2012	
JR8	2007-000221	R-CHIP;1.2KOHM,5%,1/10W,DA,TP,2012	
FR4L	2007-000241	R-CHIP;1.5KOHM,5%,1/10W,DA,TP,2012	
HR3L	2007-000241	R-CHIP;1.5KOHM,5%,1/10W,DA,TP,2012	
HR3R	2007-000241	R-CHIP;1.5KOHM,5%,1/10W,DA,TP,2012	
FR12R	2007-000267	R-CHIP;1.8KOHM,5%,1/10W,DA,TP,2012	
DR1	2007-000282	R-CHIP;100KOHM,5%,1/10W,DA,TP,2012	
DR6	2007-000282	R-CHIP;100KOHM,5%,1/10W,DA,TP,2012	
FR9	2007-000282	R-CHIP;100KOHM,5%,1/10W,DA,TP,2012	
AR5	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
CR10	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
CR11	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
CR35	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
CR7	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
DR3L	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
DR3R	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
FR13	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
FR14	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
FR1R	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
FR2	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
FR5	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
JR15	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
JR20	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
JR5	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
JR5L	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
JR5R	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
JR8R	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
JR9	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
LR2	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
BR6L	2007-000355	R-CHIP;12KOHM,5%,1/10W,DA,TP,2012	
BR6R	2007-000355	R-CHIP;12KOHM,5%,1/10W,DA,TP,2012	
JR11L	2007-000409	R-CHIP;15KOHM,5%,1/10W,DA,TP,2012	
AR4L	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
FR18	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
FR1A	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
JR15A	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
BR2	2007-000477	R-CHIP;1MOHM,5%,1/10W,DA,TP,2012	
AR4	2007-000493	R-CHIP;2.2KOHM,5%,1/10W,DA,TP,2012	
FR20	2007-000493	R-CHIP;2.2KOHM,5%,1/10W,DA,TP,2012	
FR8R	2007-000493	R-CHIP;2.2KOHM,5%,1/10W,DA,TP,2012	
FR9L	2007-000493	R-CHIP;2.2KOHM,5%,1/10W,DA,TP,2012	
FR9R	2007-000493	R-CHIP;2.2KOHM,5%,1/10W,DA,TP,2012	
HR2L	2007-000493	R-CHIP;2.2KOHM,5%,1/10W,DA,TP,2012	
HR2R	2007-000493	R-CHIP;2.2KOHM,5%,1/10W,DA,TP,2012	
HR4L	2007-000493	R-CHIP;2.2KOHM,5%,1/10W,DA,TP,2012	
HR4R	2007-000493	R-CHIP;2.2KOHM,5%,1/10W,DA,TP,2012	
JR4L	2007-000572	R-CHIP;220OHM,5%,1/10W,DA,TP,2012	
JR4R	2007-000572	R-CHIP;220OHM,5%,1/10W,DA,TP,2012	
FR10	2007-000586	R-CHIP;22KOHM,5%,1/10W,DA,TP,2012	
FR13R	2007-000586	R-CHIP;22KOHM,5%,1/10W,DA,TP,2012	
FR2L	2007-000586	R-CHIP;22KOHM,5%,1/10W,DA,TP,2012	
FR2R	2007-000586	R-CHIP;22KOHM,5%,1/10W,DA,TP,2012	
FR6	2007-000586	R-CHIP;22KOHM,5%,1/10W,DA,TP,2012	
JR3	2007-000586	R-CHIP;22KOHM,5%,1/10W,DA,TP,2012	
JR7L	2007-000586	R-CHIP;22KOHM,5%,1/10W,DA,TP,2012	
JR7R	2007-000586	R-CHIP;22KOHM,5%,1/10W,DA,TP,2012	
AR3L	2007-000686	R-CHIP;3.3KOHM,5%,1/10W,DA,TP,2012	
AR5L	2007-000686	R-CHIP;3.3KOHM,5%,1/10W,DA,TP,2012	
BR5L	2007-000686	R-CHIP;3.3KOHM,5%,1/10W,DA,TP,2012	
BR5R	2007-000686	R-CHIP;3.3KOHM,5%,1/10W,DA,TP,2012	
HR1L	2007-000686	R-CHIP;3.3KOHM,5%,1/10W,DA,TP,2012	
AR1	2007-000774	R-CHIP;33KOHM,5%,1/10W,DA,TP,2012	
AR6	2007-000774	R-CHIP;33KOHM,5%,1/10W,DA,TP,2012	
FR15	2007-000774	R-CHIP;33KOHM,5%,1/10W,DA,TP,2012	
BR2L	2007-000822	R-CHIP;390OHM,5%,1/10W,DA,TP,2012	
BR2R	2007-000822	R-CHIP;390OHM,5%,1/10W,DA,TP,2012	
DR2	2007-000830	R-CHIP;39KOHM,5%,1/10W,DA,TP,2012	
AR1R	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012	
BR1L	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012	
CR37	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012	
JR13R	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012	
JR6	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012	
RR6	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012	
AR2L	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012	
AR2R	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012	
AR7	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012	
DR1L	2007-000981	R-CHIP;5.6KOHM,5%,1/10W,DA,TP,2012	
DR1R	2007-000981	R-CHIP;5.6KOHM,5%,1/10W,DA,TP,2012	
DR2R	2007-000981	R-CHIP;5.6KOHM,5%,1/10W,DA,TP,2012	
JR1R	2007-000981	R-CHIP;5.6KOHM,5%,1/10W,DA,TP,2012	
JR7	2007-000981	R-CHIP;5.6KOHM,5%,1/10W,DA,TP,2012	
AR6L	2007-001039	R-CHIP;56KOHM,5%,1/10W,DA,TP,2012	
AR6R	2007-001039	R-CHIP;56KOHM,5%,1/10W,DA,TP,2012	
AR7L	2007-001039	R-CHIP;56KOHM,5%,1/10W,DA,TP,2012	
AR7R	2007-001039	R-CHIP;56KOHM,5%,1/10W,DA,TP,2012	
DR9L	2007-001071	R-CHIP;6.8KOHM,5%,1/10W,DA,TP,2012	
DR9R	2007-001071	R-CHIP;6.8KOHM,5%,1/10W,DA,TP,2012	
FR7L	2007-001071	R-CHIP;6.8KOHM,5%,1/10W,DA,TP,2012	
FR7R	2007-001071	R-CHIP;6.8KOHM,5%,1/10W,DA,TP,2012	
CR39	2007-001177	R-CHIP;8.2KOHM,5%,1/10W,DA,TP,2012	
CR6	2007-001177	R-CHIP;8.2KOHM,5%,1/10W,DA,TP,2012	
CR8	2007-001177	R-CHIP;8.2KOHM,5%,1/10W,DA,TP,2012	
FR6R	2007-001177	R-CHIP;8.2KOHM,5%,1/10W,DA,TP,2012	
JR10	2007-001177	R-CHIP;8.2KOHM,5%,1/10W,DA,TP,2012	
JR12L	2007-001177	R-CHIP;8.2KOHM,5%,1/10W,DA,TP,2012	
JR12R	2007-001177	R-CHIP;8.2KOHM,5%,1/10W,DA,TP,2012	
FC1A	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	
FC5L	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	
FC5R	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	
FC7	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	
FC9	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	
EMC1	2203-000239	C-CERAMIC,CHIP;0.1nF,5%,50V,NP0,TP,2012	
EMC2	2203-000239	C-CERAMIC,CHIP;0.1nF,5%,50V,NP0,TP,2012	
FC6L	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
FC6R	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
JC2	2203-000361	C-CERAMIC,CHIP;0.15nF,5%,50V,NP0,TP,2012	
FC5	2203-000374	C-CERAMIC,CHIP;15nF,10%,50V,X7R,TP,2012	
FC11L	2203-000533	C-CERAMIC,CHIP;2.7nF,10%,50V,X7R,TP,2012,-	
FC11R	2203-000533	C-CERAMIC,CHIP;2.7nF,10%,50V,X7R,TP,2012,-	
FC8L	2203-000533	C-CERAMIC,CHIP;2.7nF,10%,50V,X7R,TP,2012,-	
FC8R	2203-000533	C-CERAMIC,CHIP;2.7nF,10%,50V,X7R,TP,2012,-	
JC11L	2203-000595	C-CERAMIC,CHIP;0.22nF,5%,50V,NP0,TP,2012	
JC11R	2203-000595	C-CERAMIC,CHIP;0.22nF,5%,50V,NP0,TP,2012	
FC7L	2203-000671	C-CERAMIC,CHIP;27nF,10%,50V,X7R,TP,2012,-	
FC7R	2203-000671	C-CERAMIC,CHIP;27nF,10%,50V,X7R,TP,2012,-	
FC3L	2203-000761	C-CERAMIC,CHIP;330nF,10%,16V,X7R,TP,2012,-	
FC3R	2203-000761	C-CERAMIC,CHIP;330nF,10%,16V,X7R,TP,2012,-	
AC1L	2203-000787	C-CERAMIC,CHIP;0.33nF,5%,50V,NP0,TP,2012	
AC1R	2203-000787	C-CERAMIC,CHIP;0.33nF,5%,50V,NP0,TP,2012	
CC3	2203-000787	C-CERAMIC,CHIP;0.33nF,5%,50V,NP0,TP,2012	
CC4	2203-000787	C-CERAMIC,CHIP;0.33nF,5%,50V,NP0,TP,2012	
CC5	2203-000787	C-CERAMIC,CHIP;0.33nF,5%,50V,NP0,TP,2012	
FC4L	2203-000802	C-CERAMIC,CHIP;33nF,10%,50V,X7R,TP,2012	
FC4R	2203-000802	C-CERAMIC,CHIP;33nF,10%,50V,X7R,TP,2012	
JC10L	2203-000892	C-CERAMIC,CHIP;4.7nF,10%,50V,X7R,TP,2012	
JC10R	2203-000892	C-CERAMIC,CHIP;4.7nF,10%,50V,X7R,TP,2012	
AC11L	2203-000953	C-CERAMIC,CHIP;0.47nF,5%,50V,NP0,TP,2012	
AC11R	2203-000953	C-CERAMIC,CHIP;0.47nF,5%,50V,NP0,TP,2012	
FC1	2203-000953	C-CERAMIC,CHIP;0.47nF,5%,50V,NP0,TP,2012	
JC10L	2203-000979	C-CERAMIC,CHIP;47nF,10%,50V,X7R,TP,2012	
JC10R	2203-000979	C-CERAMIC,CHIP;47nF,10%,50V,X7R,TP,2012	
JC22	2203-000979	C-CERAMIC,CHIP;47nF,10%,50V,X7R,TP,2012	
JC27	2203-000979	C-CERAMIC,CHIP;47nF,10%,50V,X7R,TP,2012	
JC4L	2203-001058	C-CERAMIC,CHIP;0.56nF,5%,50V,NP0,TP,2012	
JC4R	2203-001058	C-CERAMIC,CHIP;0.56nF,5%,50V,NP0,TP,2012	
JC5L	2203-001058	C-CERAMIC,CHIP;0.56nF,5%,50V,NP0,TP,2012	
JC5R	2203-001058	C-CERAMIC,CHIP;0.56nF,5%,50V,NP0,TP,2012	
AC3L	2203-001090	C-CERAMIC,CHIP;0.005nF,0.25pF,50V,NP0,TP,2012	
AC3R	2203-001090	C-CERAMIC,CHIP;0.005nF,0.25pF,50V,NP0,TP,2012	
FC9L	2203-001214	C-CERAMIC,CHIP;8.2nF,10%,50V,X7R,TP,2012,-	
FC9R	2203-001214	C-CERAMIC,CHIP;8.2nF,10%,50V,X7R,TP,2012,-	
FC10L	2203-001230	C-CERAMIC,CHIP;0.82nF,5%,50V,NP0,TP,2012	
FC10R	2203-001230	C-CERAMIC,CHIP;0.82nF,5%,50V,NP0,TP,2012	
FC4	2203-001537	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,2012	
JC2R	2203-001537	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,2012	
FC1L	2203-001611	C-CERAMIC,CHIP;0.022nF,5%,50V,NP0,TP,2012	
FC1R	2203-001611	C-CERAMIC,CHIP;0.022nF,5%,50V,NP0,TP,2012	

AH92-00565A ASSY PCB;MAX-N75,FRONT **S.N.A.**

UIR1	0601-000564	LED-IR;SIDE-VIEW,1.5MM,100MW,5V,940MM
ULD17	0601-001238	LED;ROUND,RED,3.1mm,697nm
ULD21	0601-001432	LED;ROUND,BLUE,3mm,455nm
ULD22	0601-001432	LED;ROUND,BLUE,3mm,455nm
UPQ1	0603-000116	PHOTO-TR;NPN,30V,6V,40MA,100MW,-
UPQ2	0603-000116	PHOTO-TR;NPN,30V,6V,40MA,100MW,-
UPQ3	0603-000116	PHOTO-TR;NPN,30V,6V,40MA,100MW,-
OJACK1	0603-001051	OPTIC TRANSMITTER;5V,6Mb/s,5m,-15dBm,660nm,20mA
UIC5	1003-001162	IC-MOTOR DRIVER;KA3082,SIP,10PIN,25MIL,DOUBLE,
UIC3	1203-000276	IC-POSI.FIXED REG.;7805,TO-220,3P,-,PLASTIC,4.8/5
UX2	2801-001394	CRYSTAL-UNIT;32.768KHz,20ppm,28-AAY,12.5pF,
UX1	2802-000181	RESONATOR-CERAMIC;6MHZ,0.3%,BK,9.0X4.0X7.5MM
OFT1	2901-001139	FILTER-EMI ON BOARD;50V,.5A,-,390PF,7X2.5X5MM,TP,RADIAL
ELE1	3406-001047	SWITCH-ROTARY;5V DC,0.5mA,-,12mm
JOG	3406-001054	SWITCH-ROTARY;5V DC,0.5mA,-,7.5mm
UCW3	3708-000122	CONNECTOR-FPC/FC/PIC;11P,1.25mm,ANGLE,SN
UCW12	3708-000331	CONNECTOR-FPC/FC/PIC;9P,1.25mm,ANGLE,SN
UCW10	3708-000448	CONNECTOR-FPC/FC/PIC;6P,1.25MM,STRAIGHT,
UCW7	3708-000448	CONNECTOR-FPC/FC/PIC;6P,1.25MM,STRAIGHT,
UCW5	3708-000450	CONNECTOR-FPC/FC/PIC;11P,1.25MM,STRAIGHT,
UCW2	3708-000454	CONNECTOR-FPC/FC/PIC;22P,1.25MM,STRAIGHT,
UCW4	3708-000492	CONNECTOR-FPC/FC/PIC;9P,1.25MM,-,SN
UCW15	3708-001027	CONNECTOR-FPC/FC/PIC;6P,1.25MM,ANGLE,SN
UCW16	3708-001027	CONNECTOR-FPC/FC/PIC;6P,1.25MM,ANGLE,SN
UCW1	3708-001488	CONNECTOR-FPC/FC/PIC;30P,1.25mm,ANGLE,SN
UCW11	3711-000826	CONNECTOR-HEADER;BOX,2P,1R,2mm,ANGLE,SN
OCW1	3711-000907	CONNECTOR-HEADER;BOX,3P,1R,2mm,STRAIGHT,SN
UCW6	3711-000907	CONNECTOR-HEADER;BOX,3P,1R,2mm,STRAIGHT,SN

Location no.	Code no.	Description & Specifiation	Remarks
UCW9	3711-000907	CONNECTOR-HEADER;BOX,3P,1R,2mm,STRAIGHT,SN	
UCW3	3809-000142	CABLE-FLAT;300V,80C,200mm,11P,2mm,UL2877	
UCW4	3809-000142	CABLE-FLAT;300V,80C,200mm,11P,2mm,UL2877	
UCW5	3809-000142	CABLE-FLAT;300V,80C,200mm,11P,2mm,UL2877	
UCW10	3809-000148	CABLE-FLAT;300V,80C,250mm,9P,2mm,UL2877	
UCW11	3809-000148	CABLE-FLAT;300V,80C,250mm,9P,2mm,UL2877	
UCW12	3809-000148	CABLE-FLAT;300V,80C,250mm,9P,2mm,UL2877	
UCW4	3809-000148	CABLE-FLAT;300V,80C,250mm,9P,2mm,UL2877	
UCW5	3809-000148	CABLE-FLAT;300V,80C,250mm,9P,2mm,UL2877	
UCW6	3809-000148	CABLE-FLAT;300V,80C,250mm,9P,2mm,UL2877	
UCW7	3809-000148	CABLE-FLAT;300V,80C,250mm,9P,2mm,UL2877	
UCW8	3809-000148	CABLE-FLAT;300V,80C,250mm,9P,2mm,UL2877	
UCW9	3809-000148	CABLE-FLAT;300V,80C,250mm,9P,2mm,UL2877	
UCW10	3809-000199	CABLE-FLAT;30V,80C,300mm,6P,1.25mm,UL2896	
UCW11	3809-000199	CABLE-FLAT;30V,80C,300mm,6P,1.25mm,UL2896	
UCW12	3809-000199	CABLE-FLAT;30V,80C,300mm,6P,1.25mm,UL2896	
UCW13	3809-000199	CABLE-FLAT;30V,80C,300mm,6P,1.25mm,UL2896	
UCW14	3809-000199	CABLE-FLAT;30V,80C,300mm,6P,1.25mm,UL2896	
UCW15	3809-000199	CABLE-FLAT;30V,80C,300mm,6P,1.25mm,UL2896	
UCW7	3809-000199	CABLE-FLAT;30V,80C,300mm,6P,1.25mm,UL2896	
UCW8	3809-000199	CABLE-FLAT;30V,80C,300mm,6P,1.25mm,UL2896	
UCW9	3809-000199	CABLE-FLAT;30V,80C,300mm,6P,1.25mm,UL2896	
-	3809-001034	CABLE-FLAT;30V,80C,170MM,22P,1.25MM,UL289	
UCW1	3809-001184	CABLE-FLAT;30V,80C,160mm,30P,1.25mm,UL2896	
-	3809-001187	CABLE-FLAT;30V,80C,70mm,6P,1.25mm,UL2896	
REMO1	AC59-60060A	MODULE-REMOCON;GP1U281R,SHARP,38KHZ,-,-,-,-	
VFD	AH07-00020A	VF DISPLAY;HNA-15LM05,22SEG,138.2x48.3,MAX-N75	
OIC1	AH14-10004R	IC;M74HCU04,SOP,TAPE 14P	
MOTOR	AH31-10024A	MOTOR-DC;FF-130SH-14230,5VDC/150MA,	
OCW1	AH39-00023A	LEAD CONNECTOR-ASSY;-,51004-03,51004-03,03P,300MM,2547#28	
UCW6	AH39-00085A	LEAD CONNECTOR-ASSY;-,51004,5295,3P,150MM,1007#28	
UCW13	AH39-00192A	LEAD CONNECTOR-ASSY;-,-,-,-,#1007,28,50MM,BK/WH,BK,35023-2P,	
UCW17	AH39-00193A	LEAD CONNECTOR-ASSY;-,-,-,-,#1007,28,80MM,BK/WH,BK,-,51004-2	
	AH61-00373A	HOLDER-VFD;-,ABS 94HB,-,BLK,-,MAX-N75	
	AH61-00428A	HOLDER-SENSOR;-,ABS 94HB,-,BLK,-,MAX-N75	
UJW11	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
UJW23	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
UJW28	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
UJW29	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
UJW3	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
UJW30	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
UJW31	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
UJW50	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
UJW51	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
UJW62	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
UR146	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
UR16	2007-000221	R-CHIP;1.2KOHM,5%,1/10W,DA,TP,2012	
UR32	2007-000221	R-CHIP;1.2KOHM,5%,1/10W,DA,TP,2012	
UR17	2007-000241	R-CHIP;1.5KOHM,5%,1/10W,DA,TP,2012	
UR11	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
UR13	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
UR136	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
UR137	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
UR138	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
UR145	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
UR155	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
UR64	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
UR65	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
UR80	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
UJW52	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
UR15	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
UR31	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
UR66	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
UR67	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
UR68	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
UR69	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
UR70	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
UR71	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
UR72	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
UR73	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
UR75	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
UR76	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
UR77	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
UR78	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
UR200	2007-000477	R-CHIP;1MOHM,5%,1/10W,DA,TP,2012	
UR35	2007-000493	R-CHIP;2.2KOHM,5%,1/10W,DA,TP,2012	
UR5	2007-000493	R-CHIP;2.2KOHM,5%,1/10W,DA,TP,2012	
UR6	2007-000493	R-CHIP;2.2KOHM,5%,1/10W,DA,TP,2012	
UR90	2007-000493	R-CHIP;2.2KOHM,5%,1/10W,DA,TP,2012	
UR3	2007-000565	R-CHIP;220KOHM,5%,1/10W,DA,TP,2012	
UR20	2007-000686	R-CHIP;3.3KOHM,5%,1/10W,DA,TP,2012	
UR36	2007-000686	R-CHIP;3.3KOHM,5%,1/10W,DA,TP,2012	
UR156	2007-000876	R-CHIP;4.7MOHM,5%,1/10W,DA,TP,2012	
UR82	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012	
UR83	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012	
UR84	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012	
UR85	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012	
UR87	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012	
UR88	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012	
UR1A	2007-000981	R-CHIP;5.6KOHM,5%,1/10W,DA,TP,2012	
UR1	2007-001024	R-CHIP;560KOHM,5%,1/10W,DA,TP,2012	
UR38	2007-001071	R-CHIP;6.8KOHM,5%,1/10W,DA,TP,2012	
UR30	2007-001201	R-CHIP;820OHM,5%,1/10W,DA,TP,2012	

Location no.	Code no.	Description & Specifiation	Remarks
UR2	2007-001654	R-CHIP;10MOHM,1%,1/10W,DA,TP,2012	
UR30	2203-000595	C-CERAMIC,CHIP;0.22nF,5%,50V,NP0,TP,2012	
UR31	2203-000595	C-CERAMIC,CHIP;0.22nF,5%,50V,NP0,TP,2012	
UR32	2203-000595	C-CERAMIC,CHIP;0.22nF,5%,50V,NP0,TP,2012	
UC18	2203-000979	C-CERAMIC,CHIP;47nF,10%,50V,X7R,TP,2012	
UC13	2203-001611	C-CERAMIC,CHIP;0.022nF,5%,50V,NP0,TP,2012	
UC14	2203-001611	C-CERAMIC,CHIP;0.022nF,5%,50V,NP0,TP,2012	
UC11	2203-001619	C-CERAMIC,CHIP;0.027nF,5%,50V,NP0,TP,2012	
UC12	2203-001619	C-CERAMIC,CHIP;0.027nF,5%,50V,NP0,TP,2012	
UIC1	AH11-00015A	MASK ROM;LC86P6548-XXXX,100P,QFP,-,8BIT,-	
UIC2	AH14-10004M	IC;NJU3713G,SOP,TAPE 18P	
UD11	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
UD12	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
UD13	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
UD14	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
UD15	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
UD20	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
UD21	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
UD22	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
UD23	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
UZD1	0403-000344	DIODE-ZENER;UZ3.9B,3.9V,3.7-4.1V,500MW,	
UQ2	0504-000118	TR-DIGITAL;KSR1003,NPN,300MW,22K/22K,TO-92,TP	
UQ4	0504-000118	TR-DIGITAL;KSR1003,NPN,300MW,22K/22K,TO-92,TP	
UQ6	0504-000118	TR-DIGITAL;KSR1003,NPN,300MW,22K/22K,TO-92,TP	
UQ8	0504-000118	TR-DIGITAL;KSR1003,NPN,300MW,22K/22K,TO-92,TP	
UQ9	0504-000122	TR-DIGITAL;KSR1009Y,NPN,300mW,4.7K,TO-92,	
UQ10	0504-000128	TR-DIGITAL;-,NPN,200MW,22K/22K,SOT-23,TP	
UQ11	0504-000128	TR-DIGITAL;-,NPN,200MW,22K/22K,SOT-23,TP	
ULD10	0601-001232	LED;TR,LED,1PCS,130-260%	
ULD11	0601-001232	LED;TR,LED,1PCS,130-260%	
ULD12	0601-001232	LED;TR,LED,1PCS,130-260%	
ULD13	0601-001232	LED;TR,LED,1PCS,130-260%	
ULD18	0601-001232	LED;TR,LED,1PCS,130-260%	
ULD19	0601-001232	LED;TR,LED,1PCS,130-260%	
ULD2	0601-001232	LED;TR,LED,1PCS,130-260%	
ULD20	0601-001232	LED;TR,LED,1PCS,130-260%	
ULD4	0601-001232	LED;TR,LED,1PCS,130-260%	
ULD5	0601-001232	LED;TR,LED,1PCS,130-260%	
ULD7	0601-001232	LED;TR,LED,1PCS,130-260%	
ULD8	0601-001232	LED;TR,LED,1PCS,130-260%	
ULD3	0601-001236	LED;ROUND,AMB,3.1mm,610nm	
ULD6	0601-001236	LED;ROUND,AMB,3.1mm,610nm	
ULD9	0601-001236	LED;ROUND,AMB,3.1mm,610nm	
ULD1	0601-001238	LED;ROUND,RED,3.1mm,697nm	
ULD14	0601-001238	LED;ROUND,RED,3.1mm,697nm	
ULD15	0601-001238	LED;ROUND,RED,3.1mm,697nm	
ULD16	0601-001238	LED;ROUND,RED,3.1mm,697nm	
UR58	2001-000005	R-CARBON;390ohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR59	2001-000005	R-CARBON;390ohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR63	2001-000005	R-CARBON;390ohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR25	2001-000010	R-CARBON;68KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR53	2001-000010	R-CARBON;68KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR42	2001-000028	R-CARBON(S);100OHM,5%,1/2W,AA,TP,2.4X6.4MM	
UR44	2001-000221	R-CARBON;1.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR33	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR45	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR18	2001-000258	R-CARBON;1.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR34	2001-000258	R-CARBON;1.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR46	2001-000258	R-CARBON;1.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR121	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR166	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR167	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR100	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR101	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR102	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR103	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR104	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR105	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR106	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR135	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR139	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR140	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR141	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR142	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR143	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR144	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR23	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR39	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR51	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR7	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR8	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR92	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR93	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR94	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR95	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR96	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR97	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR98	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR99	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR4	2001-000362	R-CARBON;150OHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR57	2001-000362	R-CARBON;150OHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR60	2001-000362	R-CARBON;150OHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR62	2001-000362	R-CARBON;150OHM,5%,1/8W,AA,TP,1.8X3.2MM	

Location no.	Code no.	Description & Specifiation	Remarks
UR41	2001-000405	R-CARBON;180OHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR54	2001-000405	R-CARBON;180OHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR55	2001-000405	R-CARBON;180OHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR56	2001-000405	R-CARBON;180OHM,5%,1/8W,AA,TP,1.8X3.2MM	
UJW16	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UJW19	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR107	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR108	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR109	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR110	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR112	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR113	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR115	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR116	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR117	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR118	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR119	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR120	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR122	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR123	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR124	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR125	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR126	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR127	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR128	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR129	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR168	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR43	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR79	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR19	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR47	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR24	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR52	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR86	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR89	2001-000554	R-CARBON;270OHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR48	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR147	2001-000708	R-CARBON;39OHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR164	2001-000708	R-CARBON;39OHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR165	2001-000708	R-CARBON;39OHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR12	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR130	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR150	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR151	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR154	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR21	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR37	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR49	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR91	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR111	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR114	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR22	2001-000890	R-CARBON;6.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR38	2001-000890	R-CARBON;6.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR50	2001-000890	R-CARBON;6.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR14	2001-000995	R-CARBON;820OHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR26	2001-000995	R-CARBON;820OHM,5%,1/8W,AA,TP,1.8X3.2MM	
UR40	2001-001107	R-CARBON(S);220ohm,5%,1/2W,AA,TP,2.4x6.4mm	
UR157	2003-000468	R-METAL OXIDE(S);10ohm,5%,1W,AA,TP,3.3x9mm	
OC3	2201-000381	C-CERAMIC,DISC;22NF,20%,50V,Y5V,8.0x4.0mm,5mm,TP	
OC2	2201-000487	C-CERAMIC,DISC;33pF,5%,50V,SL,TP,5x3,5m	
UC8	2201-000565	C-CERAMIC,DISC;47nF,20%,50V,Y5V,12.5x4.0mm,5mm,TP	
UC9	2201-000565	C-CERAMIC,DISC;47nF,20%,50V,Y5V,12.5x4.0mm,5mm,TP	
UC16	2201-000783	C-CERAMIC,DISC;100nF,+80-20%,50V,Y5V,TP,8x3,5	
OC4	2401-000240	C-AL;100uF,20%,10V,GP,TP,5x11,5	
UC17	2401-000243	C-AL;100uF,20%,10V,GP,TP,6.3x5,5	
UC4	2401-000243	C-AL;100uF,20%,10V,GP,TP,6.3x5,5	
UC5	2401-000475	C-AL;10UF,20%,50V,GP,-,5X11,2MM	
UC6	2401-000475	C-AL;10UF,20%,50V,GP,-,5X11,2MM	
UC3	2401-000752	C-AL;220NF,20%,50V,GP,BK,3X5,1MM	
UC20	2401-001912	C-AL;1uF,20%,50V,GP,5x11mm,2mm,BK	
UC28	2401-001936	C-AL;22UF,20%,16V,GP,TP,5X11MM,5MM	
UC10	2401-001975	C-AL;47UF,20%,16V,GP,TP,5X11MM,5	
UC2	2401-002180	C-AL;2.2UF,20%,50V,GP,TP,5X11,5MM	
UC1	2409-000123	C-EDL;47000UF,4UA,5.5V,-,BK,-,5MM	
OBD1	3301-000297	CORE-FERRITE BEAD;AA,3.6x1.2x5.7mm,1400,2900G	
OBD2	3301-000297	CORE-FERRITE BEAD;AA,3.6x1.2x5.7mm,1400,2900G	
USW1	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW10	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW11	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW12	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW13	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW14	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW15	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW16	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW17	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW18	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW19	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW2	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW20	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW21	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW22	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW23	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW24	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW25	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	

Location no.	Code no.	Description & Specifiation	Remarks
USW26	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW27	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW28	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW29	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW3	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW30	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW31	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW32	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW33	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW34	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW35	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW36	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW37	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW4	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW5	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW6	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW7	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW8	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
USW9	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST	
	G3V1-H	**DECK CDP;CDP PACK**	**S.N.A.**
	AH92-00005A	**ASSY-PCB-CD MAIN;G3VI,CD PACK**	**S.N.A.**
NQ1502	0501-000314	TR-SMALL SIGNAL;KSA812,PNP,150mW,SOT-23,TP,90-	
NIC928	0904-001442	IC-DSP;9286,8Bit,QFP,80P,-,16.9344MHz,TR,CMOS,P	
NIC925	1003-000179	IC-MOTOR DRIVER;KA9258D,SOP,28P,-,SINGLE,-,ST,	
NIC922	1204-001286	IC-ASP;KB9223,QFP,80P,-,PLASTIC,6V,20	
NR109	2007-000282	R-CHIP;100KOHM,5%,1/10W,DA,TP,2012	
NR203	2007-000282	R-CHIP;100KOHM,5%,1/10W,DA,TP,2012	
NR300	2007-000282	R-CHIP;100KOHM,5%,1/10W,DA,TP,2012	
NR57L	2007-000282	R-CHIP;100KOHM,5%,1/10W,DA,TP,2012	
NR57R	2007-000282	R-CHIP;100KOHM,5%,1/10W,DA,TP,2012	
NR606	2007-000282	R-CHIP;100KOHM,5%,1/10W,DA,TP,2012	
NR602	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
NR603	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
NR104	2007-000338	R-CHIP;120KOHM,5%,1/10W,DA,TP,2012	
NR107	2007-000338	R-CHIP;120KOHM,5%,1/10W,DA,TP,2012	
NR100	2007-000355	R-CHIP;12KOHM,5%,1/10W,DA,TP,2012	
NR120	2007-000355	R-CHIP;12KOHM,5%,1/10W,DA,TP,2012	
NR121	2007-000355	R-CHIP;12KOHM,5%,1/10W,DA,TP,2012	
NR204	2007-000355	R-CHIP;12KOHM,5%,1/10W,DA,TP,2012	
NR103	2007-000395	R-CHIP;150KOHM,5%,1/10W,DA,TP,2012	
NR119	2007-000395	R-CHIP;150KOHM,5%,1/10W,DA,TP,2012	
NR13	2007-000395	R-CHIP;150KOHM,5%,1/10W,DA,TP,2012	
NR400	2007-000409	R-CHIP;15KOHM,5%,1/10W,DA,TP,2012	
NR115	2007-000444	R-CHIP;180KOHM,5%,1/10W,DA,TP,2012	
NR10	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
NR11	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
NR12	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
NR4	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
NR5	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
NR54L	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
NR54R	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
NR6	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
NR604	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
NR7	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
NR804	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
SR3	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
SR4	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
NR114	2007-000477	R-CHIP;1MOHM,5%,1/10W,DA,TP,2012	
NR50L	2007-000586	R-CHIP;22KOHM,5%,1/10W,DA,TP,2012	
NR50R	2007-000586	R-CHIP;22KOHM,5%,1/10W,DA,TP,2012	
NR101	2007-000593	R-CHIP;22OHM,5%,1/10W,DA,TP,2012	
NR200	2007-000653	R-CHIP;27KOHM,5%,1/10W,DA,TP,2012	
NR52L	2007-000653	R-CHIP;27KOHM,5%,1/10W,DA,TP,2012	
NR52R	2007-000653	R-CHIP;27KOHM,5%,1/10W,DA,TP,2012	
NR201	2007-000686	R-CHIP;3.3KOHM,5%,1/10W,DA,TP,2012	
NR202	2007-000686	R-CHIP;3.3KOHM,5%,1/10W,DA,TP,2012	
NR105	2007-000830	R-CHIP;39KOHM,5%,1/10W,DA,TP,2012	
NR995	2007-000830	R-CHIP;39KOHM,5%,1/10W,DA,TP,2012	
NR996	2007-000830	R-CHIP;39KOHM,5%,1/10W,DA,TP,2012	
NR997	2007-000830	R-CHIP;39KOHM,5%,1/10W,DA,TP,2012	
NR998	2007-000830	R-CHIP;39KOHM,5%,1/10W,DA,TP,2012	
NR53L	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012	
NR53R	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012	
NR55L	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012	
NR55R	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012	
SR2	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012	
NR117	2007-000898	R-CHIP;430Kohm,5%,1/10W,DA,TP,2012	
NR108	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012	
NR111	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012	
NR112	2007-001039	R-CHIP;56KOHM,5%,1/10W,DA,TP,2012	
NR116	2007-001195	R-CHIP;820KOHM,5%,1/10W,DA,TP,2012	
NR994	2007-001208	R-CHIP;82KOHM,5%,1/10W,DA,TP,2012	
NR999	2007-001208	R-CHIP;82KOHM,5%,1/10W,DA,TP,2012	
	2007-001216	R-CHIP;82OHM,5%,1/10W,DA,TP,2012	
NC107	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	
NC108	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	
NC119	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	
NC120	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	
NC121	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	
NC600	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	
NC901	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,2012	

Location no.	Code no.	Description & Specifiation	Remarks
NC1	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
NC103	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
NC112	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
NC113	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
NC116	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
NC205	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
NC502	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
NC503	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
NC504	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
NC53L	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
NC53R	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
NC602	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
NC800	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
NC804	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
NC905	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
SC1	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
SC2	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
SC6	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012	
NC190	2203-000335	C-CERAMIC,CHIP;0.012nF,5%,50V,NP0,TP,2012	
NC190	2203-000429	C-CERAMIC,CHIP;0.018nF,5%,50V,NP0,TP,2012	
NC117	2203-000477	C-CERAMIC,CHIP;1uF,+80-20%,16V,Y5V,TP,2012,-	
NC110	2203-000495	C-CERAMIC,CHIP;2.2nF,10%,50V,X7R,TP,2012	
NC118	2203-000787	C-CERAMIC,CHIP;0.33nF,5%,50V,NP0,TP,2012	
NC101	2203-000802	C-CERAMIC,CHIP;33nF,10%,50V,X7R,TP,2012	
NC111	2203-000802	C-CERAMIC,CHIP;33nF,10%,50V,X7R,TP,2012	
NC125	2203-000802	C-CERAMIC,CHIP;33nF,10%,50V,X7R,TP,2012	
NC100	2203-000892	C-CERAMIC,CHIP;4.7nF,10%,50V,X7R,TP,2012	
NC106	2203-000892	C-CERAMIC,CHIP;4.7nF,10%,50V,X7R,TP,2012	
NC200	2203-000979	C-CERAMIC,CHIP;47nF,10%,50V,X7R,TP,2012	
NC667	2203-000979	C-CERAMIC,CHIP;47nF,10%,50V,X7R,TP,2012	
NC115	2203-001137	C-CERAMIC,CHIP;68nF,+80-20%,50V,Y5V,TP,2012,-	
NC104	2203-001537	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,2012	
NC52L	2203-001537	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,2012	
NC52R	2203-001537	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,2012	
NC603	2203-001537	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,2012	
NC903	2203-001537	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,2012	
NC102	2203-001551	C-CERAMIC,CHIP;1.5nF,10%,50V,X7R,TP,2012	
NC201	2203-001551	C-CERAMIC,CHIP;1.5nF,10%,50V,X7R,TP,2012	
NC202	2203-001619	C-CERAMIC,CHIP;0.027nF,5%,50V,NP0,TP,2012	
NC203	2203-001619	C-CERAMIC,CHIP;0.027nF,5%,50V,NP0,TP,2012	
NL105	3301-000325	CORE-FERRITE BEAD;AB,3.2x2.5x1.3mm,-,-	
SIC1	1003-001162	IC-MOTOR DRIVER;KA3082,SIP,10PIN,25MIL,DOUBLE,	
SIC2	1003-001162	IC-MOTOR DRIVER;KA3082,SIP,10PIN,25MIL,DOUBLE,	
NXF100	2802-000211	RESONATOR-CERAMIC;16.93MHZ,0.5%,TP,10.0X5.0X10.0	
SCW5	3708-001131	CONNECTOR-FPC/FC/PIC;5P,1.25mm,STRAIGHT,SN	
WCW1	3708-001252	CONNECTOR-FPC/FC/PIC;16P,1mm,STRAIGHT-F,SN	
SCW1	3708-001438	CONNECTOR-FPC/FC/PIC;22P,1.25mm,ANGLE,SN	
NCW500	3711-000906	CONNECTOR-HEADER;BOX,3P,1R,2mm,ANGLE,SN	
SCW7	3711-003379	CONNECTOR-HEADER;NOWALL,3P,1R,2.5mm,STRAIGHT,SN	
NCW101	AH39-00060A	LEAD CONNECTOR-ASSY;-,51015-08,51004-08,8P,300MM,1007#28	
NCW102	AH39-20561P	LEAD CONNECTOR-ASSY;-,5295,PHR,6P,150mm,1007#28	
ND200	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
ND201	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
ND202	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
ND203	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,TP	
SZD1	0403-000352	DIODE-ZENER;UZ4.7BM,4.7V,4.4-5.0V,500mW,DO	
SZD2	0403-000361	DIODE-ZENER;UZ6.2BSB,6.2V,5.99-6.24V,50	
NQ1501	0501-000610	TR-SMALL SIGNAL;KSA928A-Y,PNP,1W,TO-92L,TP,160	
SR1	2001-000027	R-CARBON;100OHM,5%,1/4W,AA,TP,2.4X6.4MM	
NR106	2001-000319	R-CARBON;120KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
NR1	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
NR2	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
NR3	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
NR8	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
NR113	2001-000977	R-CARBON;8.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
NR555	2008-000140	R-FUSIBLE;2.2OHM,5%,1/2W,AA,TP,3.5X9.4MM	
NC400	2202-000243	C-CERAMIC,MLC-AXIAL;33PF,5%,50V,SL,3.5X19,-,TP	
NC300	2202-000796	C-CERAMIC,MLC-AXIAL;1nF,10%,50V,Y5P,TP,3.5x19,-	
NC106	2202-000817	C-CERAMIC,MLC-AXIAL;4.7NF,20%,16V,Y5R,TP,3.5X19,-	
NC117	2301-000389	C-FILM,PEF;150nF,5%,50V,TP,12.5x15x7.5,7m	
NC105	2401-000240	C-AL;100uF,20%,10V,GP,TP,5x11,5	
NC501	2401-000240	C-AL;100uF,20%,10V,GP,TP,5x11,5	
NC702	2401-000240	C-AL;100uF,20%,10V,GP,TP,5x11,5	
NC904	2401-000240	C-AL;100uF,20%,10V,GP,TP,5x11,5	
SC14	2401-000240	C-AL;100uF,20%,10V,GP,TP,5x11,5	
NC114	2401-000419	C-AL;10UF,20%,16V,GP,-,4X7,5	
NC301	2401-000778	C-AL;220uF,20%,10V,GP,-,6.3x11,2.5m	
NC700	2401-000778	C-AL;220uF,20%,10V,GP,-,6.3x11,2.5m	
NC701	2401-000778	C-AL;220uF,20%,10V,GP,-,6.3x11,2.5m	
SC5	2401-000795	C-AL;220UF,20%,16V,GP,-,8X11.5,3.5M	
NC703	2401-001102	C-AL;330UF,20%,16V,GP,TP,8X12.5	
NC124	2401-001324	C-AL;470nF,20%,50V,GP,BK,3x5,1mm	
NC204	2401-001324	C-AL;470nF,20%,50V,GP,BK,3x5,1mm	
NC666	2401-001895	C-AL;100uF,20%,16V,GP,6.3x11mm,2.5m	
NC122	2401-001952	C-AL;4.7UF,20%,50V,-,TP,6.3X7,5	
NC50L	2401-001952	C-AL;4.7UF,20%,50V,-,TP,6.3X7,5	
NC50R	2401-001952	C-AL;4.7UF,20%,50V,-,TP,6.3X7,5	
NC54	2401-001952	C-AL;4.7UF,20%,50V,-,TP,6.3X7,5	
NC55L	2401-001952	C-AL;4.7UF,20%,50V,-,TP,6.3X7,5	
NC55R	2401-001952	C-AL;4.7UF,20%,50V,-,TP,6.3X7,5	
NL101	2701-000111	INDUCTOR-AXIAL;100uH,10%,2.5x3.4mm	
NL102	2701-000111	INDUCTOR-AXIAL;100uH,10%,2.5x3.4mm	
NL100	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm	
SL1	2701-000179	INDUCTOR-AXIAL;33uH,10%,4.2x9.8mm	
NL300	3301-000297	CORE-FERRITE BEAD;AA,3.6x1.2x5.7mm,1400,2900G	
NL301	3301-000297	CORE-FERRITE BEAD;AA,3.6x1.2x5.7mm,1400,2900G	
NL302	3301-000297	CORE-FERRITE BEAD;AA,3.6x1.2x5.7mm,1400,2900G	
NIC05	AC14-12001G	IC;KA78L05,T,-	
SCO4	AC14-12001G	IC;KA78L05,T,-	
	AJ59-20150R	DECK-CDP PCB ASSY;G3A1-6NG,-,-,-	
	CMS300-R	CMS300,CD MECHA;MAXN72/73/75	
	AH81-00251A	A/S-PARTS-SPEAKER SYSTEM;SPEAKER SYSTEM,PS N75	